

Control Commands

Model No. PT-RCQ10
PT-FRQ100C
PT-RCQ80
PT-FRQ080C



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

Panasonic

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
BASIC OPERATIO N REMOTE CONTROL	POWER	ON		PON	QPW	001	✓	✓
		OFF (STANDBY)		POF		000	✓	✓
	INPUT SELECT	DVI		IIS:DVI	QIN	DVI	✓	✓
		HDMI1		IIS:HD1		HD1	✓	✓
		SDI1		IIS:SD1		SD1	✓	✓
		DIGITAL LINK		IIS:DL1		DL1	✓	✓
	INPUT SELECT (DIGITAL LINK)	COMPUTER1		IIS:DL1:PC1	QIN	DL1:PC1	✓	✓
		COMPUTER2		IIS:DL1:PC2		DL1:PC2	✓	✓
		VIDEO		IIS:DL1:VID		DL1:VID	✓	✓
		HDMI1		IIS:DL1:HD1		DL1:HD1	✓	✓
		HDMI2		IIS:DL1:HD2		DL1:HD2	✓	✓
		S-VIDEO		IIS:DL1:SVD		DL1:SVD	✓	✓
	INPUT SELECT (SLOT)	SLOT1 : SDI1		IIS:AU1, SD1	QIN	AU1, SD1	✓	✓
		SLOT1 : SDI2		IIS:AU1, SD2		AU1, SD2	✓	✓
		SLOT1 : SDI3		IIS:AU1, SD3		AU1, SD3	✓	✓
		SLOT1 : SDI4		IIS:AU1, SD4		AU1, SD4	✓	✓
		SLOT1 : HDMI1		IIS:AU1, HD1		AU1, HD1	✓	✓
		SLOT1 : HDMI2		IIS:AU1, HD2		AU1, HD2	✓	✓
		SLOT1 : DVI1		IIS:AU1, DV1		AU1, DV1	✓	✓
		SLOT1 : DVI2		IIS:AU1, DV2		AU1, DV2	✓	✓
		SLOT1 : DisplayPort1		IIS:AU1, DP1		AU1, DP1	✓	✓
		SLOT1 : DisplayPort2		IIS:AU1, DP2		AU1, DP2	✓	✓
	FREEZE	OFF		OFZ:0	QFZ	0	✓	✓
		ON		OFZ:1		1	✓	✓
	MENU KEY			OMN			✓	✓
	ENTER KEY			OEN			✓	✓
	UP KEY			OCU			✓	✓
	DOWN KEY			OCD			✓	✓
	LEFT KEY			OCL			✓	✓
	RIGHT KEY			OCR			✓	✓
	DEFAULT KEY			OST			✓	✓
	AUTO SETUP KEY			OAS			✓	✓
	SHUTTER	OFF		OSH:0	QSH	0	✓	✓
		ON		OSH:1		1	✓	✓
	SHUTTER(Toggle)	OFF		OSH	QSH	0	✓	✓
		ON				1	✓	✓
	FUNCTION KEY			FC1			✓	✓
	SYSTEM SELCTOR KEY			OSL			✓	✓
	ASPECT KEY			VS1			✓	✓
	NUMERIC KEY	0		ONK:0			✓	✓
		1		ONK:1			✓	✓
		2		ONK:2			✓	✓
		3		ONK:3			✓	✓
		4		ONK:4			✓	✓
		5		ONK:5			✓	✓
		6		ONK:6			✓	✓
		7		ONK:7			✓	✓
		8		ONK:8			✓	✓
		9		ONK:9			✓	✓
	LENS HOME POSITION	EXECUTE		VXX:LNSI1=+00001			✓	✓
	LENS SHIFT-HORIZONTAL	SLOW+		VXX:LNSI2=+00000			✓	✓
		SLOW-		VXX:LNSI2=+00001			✓	✓
		NORMAL+		VXX:LNSI2=+00100			✓	✓
		NORMAL-		VXX:LNSI2=+00101			✓	✓
		FAST+		VXX:LNSI2=+00200			✓	✓
		FAST-		VXX:LNSI2=+00201			✓	✓
	LENS SHIFT-VERTICAL	SLOW+		VXX:LNSI3=+00000			✓	✓
		SLOW-		VXX:LNSI3=+00001			✓	✓
		NORMAL+		VXX:LNSI3=+00100			✓	✓
		NORMAL-		VXX:LNSI3=+00101			✓	✓
		FAST+		VXX:LNSI3=+00200			✓	✓
		FAST-		VXX:LNSI3=+00201			✓	✓
	LENS FOCUS	SLOW+		VXX:LNSI4=+00000			✓	✓
		SLOW-		VXX:LNSI4=+00001			✓	✓
		NORMAL+		VXX:LNSI4=+00100			✓	✓
		NORMAL-		VXX:LNSI4=+00101			✓	✓
		FAST+		VXX:LNSI4=+00200			✓	✓
		FAST-		VXX:LNSI4=+00201			✓	✓
	LENS ZOOM	SLOW+		VXX:LNSI5=+00000			✓	✓
		SLOW-		VXX:LNSI5=+00001			✓	✓
		NORMAL+		VXX:LNSI5=+00100			✓	✓
		NORMAL-		VXX:LNSI5=+00101			✓	✓
		FAST+		VXX:LNSI5=+00200			✓	✓
		FAST-		VXX:LNSI5=+00201			✓	✓
	LENS POSITION HORIZONTAL	-02480		VXX:LNSI7=-02480	QVX:LNSI7	LNSI7=-02480	✓	✓
		+02480		VXX:LNSI7=+02480		LNSI7=+02480	✓	✓
	LENS POSITION VERTICAL	-03200		VXX:LNSI8=-03200	QVX:LNSI8	LNSI8=-03200	✓	✓
		+03200		VXX:LNSI8=+03200		LNSI8=+03200	✓	✓
	LENS POSITION H/V	-02480/-03200		VXX:LNSSB=-02480-03200	QVX:LNSSB	LNSSB=-02480-03200	✓	✓
		+02480/+03200		VXX:LNSSB=+02480+03200		LNSSB=+02480+03200	✓	✓
	STATUS KEY			STS			✓	✓
	LENS FOCUS KEY			OLF			✓	✓
	LENS SHIFT KEY			OLH			✓	✓
	LENS ZOOM KEY			OLZ			✓	✓
	DIGITAL LINK KEY			DLK			✓	✓
	INPUT MENU KEY			IPT			✓	✓
	SELF DIAGNOSIS				QVX:ERRS1 QVX:ERRS2	ERRS1=*****	✓	✓
						ERRS2=*****	✓	✓
	PICTURE MODE	DYNAMIC		VPM:DYN	QPM	DYN	✓	✓
		NATURAL		VPM:NAT		NAT	✓	✓
		STANDARD		VPM:STD		STD	✓	✓
		CINEMA		VPM:CIN		CIN	✓	✓
		GRAPHIC		VPM:GRA		GRA	✓	✓
		DICOM SIM.		VPM:DIC		DIC	✓	✓
		REC709		VPM:709		709	✓	✓
	CONTRAST	+1		VCN:001	QVR	001	✓	✓
		+63		VCN:063		063	✓	✓
	BRIGHTNESS	+1		VBR:001	QVB	001	✓	✓
		+63		VBR:063		063	✓	✓
	COLOR	+1		VCO:001	QVC	001	✓	✓
		+63		VCO:063		063	✓	✓
	TINT	+1		VTN:001	QVT	001	✓	✓
		+63		VTN:063		063	✓	✓
	SHARPNESS	0		VSR:000	QVS	000	✓	✓
		15		VSR:015		015	✓	✓
	WHITE GAIN	0		VWH:00	QWH	00	✓	✓
		10		VWH:10		10	✓	✓
	COLOR TEMPERATURE	USER1(USER)		OTE:04	QTE	4	✓	✓
		USER2		OTE:09		9	✓	✓
		DEFAULT		OTE:10		10	✓	✓
		3200K		OTE:3200		3200	✓	✓
		3300K		OTE:3300		3300	✓	✓
		9200K		OTE:9200		9200	✓	✓
		9300K		OTE:9300		9300	✓	✓
	COLOR TEMP-NAME SETTING USER1	COLORTEMP1		VXX:NCGS1=COLORTEMP1	QVX:NCGS1	NCGS1=COLORTEMP1	✓	✓
	COLOR TEMP-NAME SETTING USER2	COLORTEMP2		VXX:NCGS3=COLORTEMP2	QVX:NCGS3	NCGS3=COLORTEMP2	✓	✓
	COLOR TEMP-NAME CLEAR USER1	COLORTEMP1		VXX:NCLI1=+00000			✓	✓
	COLOR TEMP-NAME CLEAR USER2	COLORTEMP2		VXX:NCLI3=+00000			✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
PICTURE	WHITE BALANCE LOW-RED	-127		VOR:001	QOR	001	✓	✓
		+127		VOR:255		255	✓	✓
	WHITE BALANCE LOW-GREEN	-127		VOG:001	QOG	001	✓	✓
		+127		VOG:255		255	✓	✓
	WHITE BALANCE LOW-BLUE	-127		VOB:001	QOB	001	✓	✓
		+127		VOB:255		255	✓	✓
	WHITE BALANCE HIGH-RED	0		VHR:000	QHR	000	✓	✓
		+255		VHR:255		255	✓	✓
	WHITE BALANCE HIGH-GREEN	0		VHG:000	QHG	000	✓	✓
		+255		VHG:255		255	✓	✓
	WHITE BALANCE HIGH-BLUE	0		VHB:000	QHB	000	✓	✓
		+255		VHB:255		255	✓	✓
	GAMMA	1.8		VGA:1.8	QGA	1.8	✓	✓
		2.0		VGA:2.0		2.0	✓	✓
		2.2		VGA:2.2		2.2	✓	✓
		USER1		VGA:US1		US1	✓	✓
		DEFAULT		VGA:DEF		DEF	✓	✓
	GAMMA-NAME SETTING USER1	GAMMAUSER1		VXX:NCGS2=GAMMAUSER1	QVX:NCGS2	NCGS2=GAMMAUSER1	✓	✓
	GAMMA-NAME CLEAR USER1	GAMMAUSER1		VXX:NCLI2=+00000			✓	✓
	DAYLIGHT VIEW FRONT INSTALL	OFF		VXX:DLVI0=+00000	QVX:DLVI0	DLVI0=+00000	✓	✓
		AUTO(1)		VXX:DLVI0=+00001		DLVI0=+00001	✓	✓
		ON(2)		VXX:DLVI0=+00002		DLVI0=+00002	✓	✓
		ON(3)		VXX:DLVI0=+00003		DLVI0=+00003	✓	✓
		4		VXX:DLVI0=+00004		DLVI0=+00004	✓	✓
		5		VXX:DLVI0=+00005		DLVI0=+00005	✓	✓
		6		VXX:DLVI0=+00006		DLVI0=+00006	✓	✓
	NOISE REDUCTION	OFF		VNS:0	QNS	0	✓	✓
		1		VNS:1		1	✓	✓
		2		VNS:2		2	✓	✓
		3		VNS:3		3	✓	✓
	DYNAMIC CONTRAST/IRIS	OFF		OAI:0	QAI	0	✓	✓
		1		OAI:1		1	✓	✓
		2		OAI:2		2	✓	✓
		3		OAI:3		3	✓	✓
		USER		OAI:4		4	✓	✓
	DYNAMIC CONTRAST/AUTO IRIS (AUTO CONTRAST)	OFF		OAI:A000	QAI:A	000	✓	✓
		1		OAI:A001		001	✓	✓
		255		OAI:A255		255	✓	✓
	DYNAMIC CONTRAST (BRIGHT SIGNAL LEVEL)	6%		VXX:DYCI1=+00006	QVX:DYCI1	00006	✓	✓
		50%		VXX:DYCI1=+00050		00050	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT TIMER)	DISABLE		VXX:DYCS2=OFF	QVX:DYCS2	OFF	✓	✓
		0.0s		VXX:DYCS2=0.0		0.0	✓	✓
		10.0s		VXX:DYCS2=10.0		10.0	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT SIGNAL LEVEL)	0		VXX:DYCI3=+00000	QVX:DYCI3	00000	✓	✓
		5		VXX:DYCI3=+00005		00005	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-IN)	0.0s(OFF)		VXX:DYCS4=0.0	QVX:DYCS4	DYCS4=0.0	✓	✓
		0.5s		VXX:DYCS4=0.5		DYCS4=0.5	✓	✓
		1.0s		VXX:DYCS4=1.0		DYCS4=1.0	✓	✓
		1.5s		VXX:DYCS4=1.5		DYCS4=1.5	✓	✓
		2.0s		VXX:DYCS4=2.0		DYCS4=2.0	✓	✓
		2.5s		VXX:DYCS4=2.5		DYCS4=2.5	✓	✓
		3.0s		VXX:DYCS4=3.0		DYCS4=3.0	✓	✓
		3.5s		VXX:DYCS4=3.5		DYCS4=3.5	✓	✓
		4.0s		VXX:DYCS4=4.0		DYCS4=4.0	✓	✓
		5.0s		VXX:DYCS4=5.0		DYCS4=5.0	✓	✓
		7.0s		VXX:DYCS4=7.0		DYCS4=7.0	✓	✓
		10.0s		VXX:DYCS4=10.0		DYCS4=10.0	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-OUT)	0.0s(OFF)		VXX:DYCS5=0.0	QVX:DYCS5	DYCS5=0.0	✓	✓
		0.5s		VXX:DYCS5=0.5		DYCS5=0.5	✓	✓
		1.0s		VXX:DYCS5=1.0		DYCS5=1.0	✓	✓
		1.5s		VXX:DYCS5=1.5		DYCS5=1.5	✓	✓
		2.0s		VXX:DYCS5=2.0		DYCS5=2.0	✓	✓
		2.5s		VXX:DYCS5=2.5		DYCS5=2.5	✓	✓
		3.0s		VXX:DYCS5=3.0		DYCS5=3.0	✓	✓
		3.5s		VXX:DYCS5=3.5		DYCS5=3.5	✓	✓
		4.0s		VXX:DYCS5=4.0		DYCS5=4.0	✓	✓
		5.0s		VXX:DYCS5=5.0		DYCS5=5.0	✓	✓
		7.0s		VXX:DYCS5=7.0		DYCS5=7.0	✓	✓
		10.0s		VXX:DYCS5=10.0		DYCS5=10.0	✓	✓
	DYNAMIC CONTRAST/MANUAL IRIS (MANUAL INTENSITY)	OFF		OAI:M000	QAI:M	000	✓	✓
		1		OAI:M001		001	✓	✓
		255		OAI:M255		255	✓	✓
	DYNAMIC CONTRAST (DYNAMIC GAMMA)	OFF		OAI:D0	QAI:D	0	✓	✓
		1		OAI:D1		1	✓	✓
		2		OAI:D2		2	✓	✓
		3		OAI:D3		3	✓	✓
	SYSTEM SELECTOR RGB(Other)/DVI/SLOT-DVI	RGB		ORF:0	QRF	0	✓	✓
		YPbPr		ORF:1		1	✓	✓
	SYSTEM SELECTOR HDMI/DIGITAL LINK/SLOT-HDMI	RGB		ORF:0	QRF	0	✓	✓
		YPbPr		ORF:1		1	✓	✓
		AUTO		ORF:2		2	✓	✓
	DEFAULT PICTURE MODE	AUTO		VXX:DPMS1=AUT	QVX:DPMS1	DPMS1=AUT	✓	✓
		STANDARD		VXX:DPMS1=STD		DPMS1=STD	✓	✓
		DYNAMIC		VXX:DPMS1=DYN		DPMS1=DYN	✓	✓
		NATURAL		VXX:DPMS1=NAT		DPMS1=NAT	✓	✓
		CINEMA		VXX:DPMS1=CIN		DPMS1=CIN	✓	✓
		GRAPHIC		VXX:DPMS1=GRA		DPMS1=GRA	✓	✓
		DICOM SIM./DICOM		VXX:DPMS1=DIC		DPMS1=DIC	✓	✓
		REC709		VXX:DPMS1=709		DPMS1=709	✓	✓
	GEOMETRY	OFF		VXX:GMMI0=+00000	QVX:GMMI0	GMMI0=+00000	✓	✓
		KEYSTONE		VXX:GMMI0=+00001		GMMI0=+00001	✓	✓
		CURVED		VXX:GMMI0=+00002		GMMI0=+00002	✓	✓
		PC-1		VXX:GMMI0=+00003		GMMI0=+00003	✓	✓
		PC-2		VXX:GMMI0=+00004		GMMI0=+00004	✓	✓
		PC-3		VXX:GMMI0=+00005		GMMI0=+00005	✓	✓
		CORNER-CORRECTION		VXX:GMMI0=+00010		GMMI0=+00010	✓	✓
	GEOMETRY-KEYSTONE- LENS THROW RATIO	0.7	0.1 step	VXX:GMKS0=+00.7	QVX:GMKS0	GMKS0=+00.7	✓	✓
		16.5		VXX:GMKS0=+16.5		GMKS0=+16.5	✓	✓
	GEOMETRY-KEYSTONE- VERTICAL BALANCE	-60		VXX:GMKI4=-.00060	QVX:GMKI4	GMKI4=-.00060	✓	✓
		+60		VXX:GMKI4=+00060		GMKI4=+00060	✓	✓
	GEOMETRY-KEYSTONE- HORIZONTAL BALANCE	-30		VXX:GMKI7=-.00030	QVX:GMKI7	GMKI7=-.00030	✓	✓
		+30		VXX:GMKI7=+00030		GMKI7=+00030	✓	✓
	GEOMETRY-KEYSTONE- VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMKS8=-40.0	QVX:GMKS8	GMKS8=-40.0	✓	✓
		+40.0 (+45.0)*		VXX:GMKS8=+40.0		GMKS8=+40.0	✓	✓
	GEOMETRY-KEYSTONE- HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMKS9=-15.0	QVX:GMKS9	GMKS9=-15.0	✓	✓
		+15.0 (+40.0)*		VXX:GMKS9=+15.0		GMKS9=+15.0	✓	✓
	GEOMETRY-CURVED-LENS THROW RATIO	0.7	0.1 step	VXX:GMCS0=+00.7	QVX:GMCS0	GMCS0=+00.7	✓	✓
		16.5		VXX:GMCS0=+16.5		GMCS0=+16.5	✓	✓
	GEOMETRY-CURVED- VERTICAL ARC	-50 (-100)*		VXX:GMCI3=-.00050	QVX:GMCI3	GMCI3=-.00050	✓	✓
		+50 (+100)*		VXX:GMCI3=+00050		GMCI3=+00050	✓	✓
	GEOMETRY-CURVED- HORIZONTAL ARC	-50 (-100)*		VXX:GMCI7=-.00050	QVX:GMCI7	GMCI7=-.00050	✓	✓
		+50 (+100)*		VXX:GMCI7=+00050		GMCI7=+00050	✓	✓
	GEOMETRY-CURVED- VERTICAL BALANCE	-60		VXX:GMCI2=-.00060	QVX:GMCI2	GMCI2=-.00060	✓	✓
		+60		VXX:GMCI2=+00060		GMCI2=+00060	✓	✓
	GEOMETRY-CURVED- HORIZONTAL BALANCE	-30		VXX:GMCI6=-.00030	QVX:GMCI6	GMCI6=-.00030	✓	✓
		+30		VXX:GMCI6=+00030		GMCI6=+00030	✓	✓
	GEOMETRY-CURVED- VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMCS8=-40.0	QVX:GMCS8	GMCS8=-40.0	✓	✓
		+40.0 (+45.0)*		VXX:GMCS8=+40.0		GMCS8=+40.0	✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
POSITION	GEOMETRY-CURVED-HORIZONTAL KEYSTONE	-15.0 (-40.0)* +15.0 (+40.0)*	0.2 step	VXX:GMCS9=-15.0 VXX:GMCS9=+15.0	QVX:GMCS9	GMCS9=-15.0 GMCS9=+15.0	✓ ✓	✓ ✓
	GEOMETRY-CURVED-MAINTAIN ASPECT RATIO	OFF ON		VXX:GMCIA=+00000 VXX:GMCIA=+00001	QVX:GMCIA	GMCIA=+00000 GMCIA=+00001	✓ ✓	✓ ✓
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	min. max.		VXX:GMFI1=+00000 VXX:GMFI1=+00300	QVX:GMFI1	GMFI1=+00000 GMFI1=+00300	-120 +300	-120 +300
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	min. max.		VXX:GMFI2=+00000 VXX:GMFI2=+00300	QVX:GMFI2	GMFI2=+00000 GMFI2=+00300	-120 +300	-120 +300
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	min. max.		VXX:GMFI3=-00300 VXX:GMFI3=+00000	QVX:GMFI3	GMFI3=-00300 GMFI3=+00000	-300 +120	-300 +120
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	min. max.		VXX:GMFI4=-00300 VXX:GMFI4=+00000	QVX:GMFI4	GMFI4=-00300 GMFI4=+00000	-300 +120	-300 +120
	GEOMETRY-CORNER CORRECTION-LINEARITY(V)	min. max.		VXX:GMFI5=-00127 VXX:GMFI5=+00127	QVX:GMFI5	GMFI5=-00127 GMFI5=+00127	-127 +127	-127 +127
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	min. max.		VXX:GMFI6=+00000 VXX:GMFI6=+00480	QVX:GMFI6	GMFI6=+00000 GMFI6=+00480	-192 +480	-192 +480
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	min. max.		VXX:GMFI7=-00480 VXX:GMFI7=+00000	QVX:GMFI7	GMFI7=-00480 GMFI7=+00000	-480 +192	-480 +192
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	min. max.		VXX:GMFI8=+00000 VXX:GMFI8=+00480	QVX:GMFI8	GMFI8=+00000 GMFI8=+00480	-192 +480	-192 +480
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	min. max.		VXX:GMFI9=-00480 VXX:GMFI9=+00000	QVX:GMFI9	GMFI9=-00480 GMFI9=+00000	-480 +192	-480 +192
	GEOMETRY-CORNER CORRECTION-LINEARITY(H)	min. max.		VXX:GMFIA=-00127 VXX:GMFIA=+00127	QVX:GMFIA	GMFIA=-00127 GMFIA=+00127	-127 +127	-127 +127
	GEOMETRY - FREE GRID(ON/OFF)	OFF ON		VXX:GMGI1=+00000 VXX:GMGI1=+00001	QVX:GMGI1	GMGI1=+00000 GMGI1=+00001	✓ ✓	✓ ✓
	GEOMETRY - FREE GRID - INITIALIZE			VXX:GMGI2=+00001			✓	✓
	GEOMETRY - FREE GRID - GRID RESOLUTION	2x2 3x3 5x5 9x9 17x17		VXX:GMGI3=+00002 VXX:GMGI3=+00003 VXX:GMGI3=+00005 VXX:GMGI3=+00009 VXX:GMGI3=+00017	QVX:GMGI3	GMGI3=+00002 GMGI3=+00003 GMGI3=+00005 GMGI3=+00009 GMGI3=+00017	✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓
	GEOMETRY - FREE GRID - GRID COLOR	OFF WHITE BLACK RED GREEN BLUE CYAN MAGENTA YELLOW		VXX:GMGI4=+00000 VXX:GMGI4=+00001 VXX:GMGI4=+00002 VXX:GMGI4=+00003 VXX:GMGI4=+00004 VXX:GMGI4=+00005 VXX:GMGI4=+00006 VXX:GMGI4=+00007 VXX:GMGI4=+00008	QVX:GMGI4	GMGI4=+00000 GMGI4=+00001 GMGI4=+00002 GMGI4=+00003 GMGI4=+00004 GMGI4=+00005 GMGI4=+00006 GMGI4=+00007 GMGI4=+00008	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	GEOMETRY - FREE GRID - CONTROL POINTS	POINT HORIZONTAL LINE VERTICAL LINE		VXX:GMGI5=+00000 VXX:GMGI5=+00001 VXX:GMGI5=+00002	QVX:GMGI5	GMGI5=+00000 GMGI5=+00001 GMGI5=+00002	✓ ✓ ✓	✓ ✓ ✓
	GEOMETRY - FREE GRID - GRID WIDTH	1 10		VXX:GMGI7=+00001 VXX:GMGI7=+00010	QVX:GMGI7	GMGI7=+00001 GMGI7=+00010	✓ ✓	✓ ✓
	GEOMETRY - FREE GRID - CONTROL POINTS COLOR	WHITE BLACK RED GREEN BLUE CYAN MAGENTA YELLOW		VXX:GMGI8=+00001 VXX:GMGI8=+00002 VXX:GMGI8=+00003 VXX:GMGI8=+00004 VXX:GMGI8=+00005 VXX:GMGI8=+00006 VXX:GMGI8=+00007 VXX:GMGI8=+00008	QVX:GMGI8	GMGI8=+00001 GMGI8=+00002 GMGI8=+00003 GMGI8=+00004 GMGI8=+00005 GMGI8=+00006 GMGI8=+00007 GMGI8=+00008	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	SHIFT-HORIZONTAL	0 +4095		VTH:0000 VTH:4095	QTH	0000 4095	✓ ✓	✓ ✓
	SHIFT-VERTICAL	0 +4094		VTV:0000 VTV:4094	QTV	0000 4094	✓ ✓	✓ ✓
	ASPECT	AUTO/VID AUTO/DEFAULT NORMAL(4:3) WIDE(16:9) NATIVE(through) FULL(HV FIT) H-FIT V-FIT		VSE:0 VSE:1 VSE:2 VSE:5 VSE:6 VSE:9 VSE:10	QSE	0 1 2 5 6 9 10	✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓
	ZOOM-HORIZONTAL	50 999		OZH:050 OZH:999	QZH	050 999	✓ ✓	✓ ✓
	ZOOM-VERTICAL	50 999		OZV:050 OZV:999	QZV	050 999	✓ ✓	✓ ✓
	ZOOM-BOTH	50 999		OZO:050 OZO:999	QZO	050 999	✓ ✓	✓ ✓
	ZOOM-INTERLOCKED	OFF ON		OZS:0 OZS:1	QZS	0 1	✓ ✓	✓ ✓
	ZOOM-MODE	INTERNAL FULL		OZT:0 OZT:1	QZT	0 1	✓ ✓	✓ ✓
	DIGITAL CINEMA REALITY	AUTO OFF 30p/25p FIXED		OPD:0 OPD:1 OPD:2	QPD	0 1 2	✓ ✓ ✓	✓ ✓ ✓
	BLANKING-UPPER	min. max.		DBU:000 DBU:2398	QLU	000 2398	0 1198	0 1198
	BLANKING-LOWER	min. max.		DBB:000 DBB:2398	QLB	000 2398	0 1198	0 1198
	BLANKING-RIGHT	min. max.		DBR:000 DBR:3838	QLR	000 3838	0 1918	0 1918
	BLANKING-LEFT	min. max.		DBL:000 DBL:3838	QLL	000 3838	0 1918	0 1918
	CUSTOM MASKING *	OFF PC-1 PC-2 PC-3		VXX:MSKI1=+00000 VXX:MSKI1=+00001 VXX:MSKI1=+00002 VXX:MSKI1=+00003	QVX:MSKI1	MSKI1=+00000 MSKI1=+00001 MSKI1=+00002 MSKI1=+00003	✓ ✓ ✓ ✓	✓ ✓ ✓ ✓
	EDGE BLENDING	OFF ON USER		VXX:EDBI0=+00000 VXX:EDBI0=+00001 VXX:EDBI0=+00002	QVX:EDBI0	EDBI0=+00000 EDBI0=+00001 EDBI0=+00002	✓ ✓ ✓	✓ ✓ ✓
	EDGE BLENDING-UPPER ON/OFF	OFF ON		VGU:0 VGU:1	QGU	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-LOWER ON/OFF	OFF ON		VGB:0 VGB:1	QGB	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-LEFT ON/OFF	OFF ON		VGL:0 VGL:1	QGL	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-RIGHT ON/OFF	OFF ON		VGR:0 VGR:1	QGR	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-START-UPPER	min. max.		VEU:0000 VEU:2272	QEU	0000 2272	✓ ✓	✓ ✓
	EDGE BLENDING-START-LOWER	min. max.		VEB:0000 VEB:2272	QEB	0000 2272	✓ ✓	✓ ✓
	EDGE BLENDING-START-LEFT	min. max.		VEL:0000 VEL:3712	QEL	0000 3712	✓ ✓	✓ ✓
	EDGE BLENDING-START-RIGHT	min. max.		VER:0000 VER:3712	QER	0000 3712	✓ ✓	✓ ✓
	EDGE BLENDING-WIDTH-UPPER	min. max.		VXX:EUIWIO=+00000 VXX:EUIWIO=+02272	QVX:EUIWIO	EUIWIO=+00000 EUIWIO=+02272	✓ ✓	✓ ✓
	EDGE BLENDING-WIDTH-LOWER	min. max.		VXX:EBWIO=+00000 VXX:EBWIO=+02272	QVX:EBWIO	EBWIO=+00000 EBWIO=+02272	✓ ✓	✓ ✓
	EDGE BLENDING-WIDTH-LEFT	min. max.		VXX:ELWIO=+00000 VXX:ELWIO=+03712	QVX:ELWIO	ELWIO=+00000 ELWIO=+03712	✓ ✓	✓ ✓
	EDGE BLENDING-WIDTH-RIGHT	min. max.		VXX:ERWIO=+00000 VXX:ERWIO=+03712	QVX:ERWIO	ERWIO=+00000 ERWIO=+03712	✓ ✓	✓ ✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
ADVANCED	EDGE BLENDING-MARKER-ON/OFF	OFF ON		VGM:0 VGM:1	QGM	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJI:000.000.000.000 VJI:255.255.255.255	QJI	000.000.000.000 255.255.255.255	✓ ✓	✓ ✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-	OFF ON		VXX:EBII1=+00000 VXX:EBII1=+00001	QVX:EBII1	EBII1=+00000 EBII1=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJ0:000,000,000,000 VJ0:255,255,255,255	QJ0	000.000.000.000 255.255.255.255	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF ON		VXX:EBII2=+00000 VXX:EBII2=+00001	QVX:EBII2	EBII2=+00000 EBII2=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min. max.		VJU:0000 VJU:2272	QJU	0000 2272	0 1200	0 1200
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min. max.		VJB:0000 VJB:2272	QJB	0000 2272	0 1200	0 1200
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min. max.		VJL:0000 VJL:3712	QJL	0000 3712	0 1920	0 1920
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min. max.		VJR:0000 VJR:3712	QJR	0000 3712	0 1920	0 1920
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER KEYSTONE AREA	min. max.		VXX:EBBI4=-02272 VXX:EBBI4=+02272	QVX:EBBI4	EBBI4=-02272 EBBI4=+02272	1200 1200	1200 1200
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER KEYSTONE AREA	min. max.		VXX:EBBI5=-02272 VXX:EBBI5=+02272	QVX:EBBI5	EBBI5=-02272 EBBI5=+02272	-1200 1200	-1200 1200
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT KEYSTONE AREA	min. max.		VXX:EBBI6=-03712 VXX:EBBI6=+03712	QVX:EBBI6	EBBI6=-03712 EBBI6=+03712	-1920 1920	-1920 1920
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT KEYSTONE AREA	min. max.		VXX:EBBI7=-03712 VXX:EBBI7=+03712	QVX:EBBI7	EBBI7=-03712 EBBI7=+03712	-1920 1920	-1920 1920
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS0=000,000,000,000 VXX:EBBS0=255,255,255,255	QVX:EBBS0	EBBS0=000,000,000,000 EBBS0=255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS1=000,000,000,000 VXX:EBBS1=255,255,255,255	QVX:EBBS1	EBBS1=000,000,000,000 EBBS1=255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS2=000,000,000,000 VXX:EBBS2=255,255,255,255	QVX:EBBS2	EBBS2=000,000,000,000 EBBS2=255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS3=000,000,000,000 VXX:EBBS3=255,255,255,255	QVX:EBBS3	EBBS3=000,000,000,000 EBBS3=255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	OFF ON		VXX:EBII3=+00000 VXX:EBII3=+00001	QVX:EBII3	EBII3=+00000 EBII3=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	OFF ON		VXX:EBII4=+00000 VXX:EBII4=+00001	QVX:EBII4	EBII4=+00000 EBII4=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT INTERLOCKED	OFF ON		VXX:EBII5=+00000 VXX:EBII5=+00001	QVX:EBII5	EBII5=+00000 EBII5=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	OFF ON		VXX:EBII6=+00000 VXX:EBII6=+00001	QVX:EBII6	EBII6=+00000 EBII6=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-AUTO TESTPATTERN	OFF ON		VXX:EATII=+00000 VXX:EATII=+00001	QVX:EATII	EATII=+00000 EATII=+00001	✓ ✓	✓ ✓
	FRAME RESPONSE	NORMAL FAST FIXED		VXX:FDYIO=+00000 VXX:FDYIO=+00001 VXX:FDYIO=+00005	QVX:FDYIO	FDYIO=+00000 FDYIO=+00001 FDYIO=+00005	✓ ✓ ✓	✓ ✓ ✓
	SMOOTH PIXEL DRIVE	OFF ON		VXX:SPDI1=+00000 VXX:SPDI1=+00001	QVX:SPDI1	SPDI1=+00000 SPDI1=+00001	✓ ✓	✓ ✓
	RASTER POSITION-HORIZONTAL	-2048 +2047		VRH:2952 VRH:7047	QRH	2952 7047	✓ ✓	✓ ✓
	RASTER POSITION-VERTICAL	-2048 +2047		VRV:2952 VRV:7047	QRV	2952 7047	✓ ✓	✓ ✓
DISPLAY LANGUAGE	LANGUAGE	English German French Spanish Italian Japanese Chinese Russian Korea Portuguse		OLG:ENG OLG:DEU OLG:FRA OLG:ESP OLG:ITL OLG:JPN OLG:CHI OLG:RUS OLG:KOR OLG:POR	QLG	ENG DEU FRA ESP ITL JPN CHI RUS KOR POR	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	COLOR MATCHING	OFF 3COLORS 7COLORS MEASURED		VXX:CMAIO=+00000 VXX:CMAIO=+00001 VXX:CMAIO=+00002 VXX:CMAIO=+00004	QVX:CMAIO	CMAIO=+00000 CMAIO=+00001 CMAIO=+00002 CMAIO=+00004	✓ ✓ ✓ ✓	✓ ✓ ✓ ✓
	COLOR MATCHING-3COLORS-RED	0 (R,G,B) 2048,2048,2048(R,G,B)		VMR:0000,0000,0000 VMR:2048,2048,2048	QMR	0000,0000,0000 2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-3COLORS-GREEN	0 (R,G,B) 2048,2048,2048(R,G,B)		VMG:0000,0000,0000 VMG:2048,2048,2048	QMG	0000,0000,0000 2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-3COLORS-BLUE	0 (R,G,B) 2048,2048,2048(R,G,B)		VMB:0000,0000,0000 VMB:2048,2048,2048	QMB	0000,0000,0000 2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-3COLORS-WHITE	256 (GAIN) 2048(GAIN)		VMW:0256 VMW:2048	QMW	0256 2048	✓ ✓	✓ ✓
	COLOR MATCHING-3COLORS-AUTO TESTPATTERN	OFF ON		VXX:CATIO=+00000 VXX:CATIO=+00001	QVX:CATIO	CATIO=+00000 CATIO=+00001	✓ ✓	✓ ✓
	COLOR MATCHING-7COLORS-RED	0 (R,G,B) 2048(R,G,B)		VXX:C7CS0=0000,0000,0000 VXX:C7CS0=2048,2048,2048	QVX:C7CS0	C7CS0=0000,0000,0000 C7CS0=2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-7COLORS-GREEN	0 (R,G,B) 2048(R,G,B)		VXX:C7CS1=0000,0000,0000 VXX:C7CS1=2048,2048,2048	QVX:C7CS1	C7CS1=0000,0000,0000 C7CS1=2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-7COLORS-BLUE	0 (R,G,B) 2048(R,G,B)		VXX:C7CS2=0000,0000,0000 VXX:C7CS2=2048,2048,2048	QVX:C7CS2	C7CS2=0000,0000,0000 C7CS2=2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-7COLORS-CYAN	0 (R,G,B) 2048(R,G,B)		VXX:C7CS3=0000,0000,0000 VXX:C7CS3=2048,2048,2048	QVX:C7CS3	C7CS3=0000,0000,0000 C7CS3=2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-7COLORS-MAGENTA	0 (R,G,B) 2048(R,G,B)		VXX:C7CS4=0000,0000,0000 VXX:C7CS4=2048,2048,2048	QVX:C7CS4	C7CS4=0000,0000,0000 C7CS4=2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-7COLORS-YELLOW	0 (R,G,B) 2048(R,G,B)		VXX:C7CS5=0000,0000,0000 VXX:C7CS5=2048,2048,2048	QVX:C7CS5	C7CS5=0000,0000,0000 C7CS5=2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-7COLORS-WHITE	0 (R,G,B) 2048(R,G,B)		VXX:C7CS6=0000,0000,0000 VXX:C7CS6=2048,2048,2048	QVX:C7CS6	C7CS6=0000,0000,0000 C7CS6=2048,2048,2048	✓ ✓	✓ ✓
	COLOR MATCHING-7COLORS-AUTO TESTPATTERN	OFF ON		VXX:CATI1=+00000 VXX:CATI1=+00001	QVX:CATI1	CATI1=+00000 CATI1=+00001	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS0=00000,0001,0001 VXX:CMMS0=65535,0999,0999	QVX:CMMS0	CMMS0=00000,0001,0001 CMMS0=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS1=00000,0001,0001 VXX:CMMS1=65535,0999,0999	QVX:CMMS1	CMMS1=00000,0001,0001 CMMS1=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS2=00000,0001,0001 VXX:CMMS2=65535,0999,0999	QVX:CMMS2	CMMS2=00000,0001,0001 CMMS2=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS3=00000,0001,0001 VXX:CMMS3=65535,0999,0999	QVX:CMMS3	CMMS3=00000,0001,0001 CMMS3=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS4=00000,0001,0001 VXX:CMMS4=65535,0999,0999	QVX:CMMS4	CMMS4=00000,0001,0001 CMMS4=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS0=00000,0001,0001 VXX:CMTS0=65535,0999,0999	QVX:CMTS0	CMTS0=00000,0001,0001 CMTS0=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS1=00000,0001,0001 VXX:CMTS1=65535,0999,0999	QVX:CMTS1	CMTS1=00000,0001,0001 CMTS1=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS2=00000,0001,0001 VXX:CMTS2=65535,0999,0999	QVX:CMTS2	CMTS2=00000,0001,0001 CMTS2=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS3=00000,0001,0001 VXX:CMTS3=65535,0999,0999	QVX:CMTS3	CMTS3=00000,0001,0001 CMTS3=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS4=00000,0001,0001 VXX:CMTS4=65535,0999,0999	QVX:CMTS4	CMTS4=00000,0001,0001 CMTS4=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS5=00000,0001,0001 VXX:CMTS5=65535,0999,0999	QVX:CMTS5	CMTS5=00000,0001,0001 CMTS5=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS6=00000,0001,0001 VXX:CMTS6=65535,0999,0999	QVX:CMTS6	CMTS6=00000,0001,0001 CMTS6=65535,0999,0999	✓ ✓	✓ ✓
	COLOR MATCHING-MEASURED	OFF		VXX:CATI3=+00000	QVX:CATI3	CATI3=+00000	✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
	MODE-AUTO TESTPATTERN	ON		VXX:CATI3=+00001		CATI3=+00001	✓	✓
	COLOR CORRECTION	OFF		VCM:0	QMC	0	✓	✓
		USER		VCM:1		1	✓	✓
	COLOR CORRECTION-RED	-30		VXX:CCRI0=-00030	QVX:CCRI0	CCRI0=-00030	✓	✓
		+30		VXX:CCRI0=+00030		CCRI0=+00030	✓	✓
	COLOR CORRECTION-GREEN	-30		VXX:CCRI1=-00030	QVX:CCRI1	CCRI1=-00030	✓	✓
		+30		VXX:CCRI1=+00030		CCRI1=+00030	✓	✓
	COLOR CORRECTION-BLUE	-30		VXX:CCRI2=-00030	QVX:CCRI2	CCRI2=-00030	✓	✓
		+30		VXX:CCRI2=+00030		CCRI2=+00030	✓	✓
	COLOR CORRECTION-CYAN	-30		VXX:CCRI3=-00030	QVX:CCRI3	CCRI3=-00030	✓	✓
		+30		VXX:CCRI3=+00030		CCRI3=+00030	✓	✓
	COLOR CORRECTION-MAGENTA	-30		VXX:CCRI4=-00030	QVX:CCRI4	CCRI4=-00030	✓	✓
		+30		VXX:CCRI4=+00030		CCRI4=+00030	✓	✓
	COLOR CORRECTION-YELLOW	-30		VXX:CCRI5=-00030	QVX:CCRI5	CCRI5=-00030	✓	✓
		+30		VXX:CCRI5=+00030		CCRI5=+00030	✓	✓
	AUTO SIGNAL	OFF		VXX:AASI0=+00000	QVX:AASI0	AASI0=+00000	✓	✓
		ON		VXX:AASI0=+00001		AASI0=+00001	✓	✓
	AUTO SETUP -POSITION ADJ.	OFF		VXX:APAI0=+00000	QVX:APAI0	APAI0=+00000	✓	✓
		ON		VXX:APAI0=+00001		APAI0=+00001	✓	✓
	AUTO SETUP -SIGNAL LEVEL ADJ.	OFF		VXX:ASLI0=+00000	QVX:ASLI0	ASLI0=+00000	✓	✓
		ON		VXX:ASLI0=+00001		ASLI0=+00001	✓	✓
	BACKUP INPUT SETTING-BACKUP INPUT	PRIMARY		VXX:BACI1=+00001	QVX:BACI1	BACI1=+00001	✓	✓
		SECONDARY		VXX:BACI1=+00002		BACI1=+00002	✓	✓
		TOGGLE		VXX:BACI1=+00010		BACI1=+00010	✓	✓
	BACKUP INPUT SETTING-BACKUP INPUT MODE	OFF		VXX:BACI2=+00000	QVX:BACI2	BACI2=+00000	✓	✓
		2		VXX:BACI2=+00002		BACI2=+00002	✓	✓
		3		VXX:BACI2=+00003		BACI2=+00003	✓	✓
		4		VXX:BACI2=+00004		BACI2=+00004	✓	✓
	BACKUP INPUT SETTING-AUTOMATIC SWITCHING	DISABLE		VXX:BACI3=+00001	QVX:BACI3	BACI3=+00001	✓	✓
		ENABLE		VXX:BACI3=+00002		BACI3=+00002	✓	✓
	BACKUP INPUT SETTING-BACKUP INPUT STATUS	INACTIVE			QVX:BACI4	BACI4=+00000	✓	✓
		ACTIVE				BACI4=+00001	✓	✓
	DVI-D IN-EDID	EDID1		0ED:1	QED	1	✓	✓
		EDID2(PC)		0ED:2		2	✓	✓
		EDID3		0ED:3		3	✓	✓
	DVI-D IN-SIGNAL LEVEL	0-255 PC		VXX:DVII0=+00000	QVX:DVII0	DVII0=+00000	✓	✓
		15-235		VXX:DVII0=+00001		DVII0=+00001	✓	✓
		AUTO		VXX:DVII0=+00002		DVII0=+00002	✓	✓
	DVI-D IN-EDID MODE	DEFAULT		VXX:EDMI2=+00000	QVX:EDMI0	EDMI2=+00000	✓	✓
		SCREEN FIT		VXX:EDMI2=+00001		EDMI2=+00001	✓	✓
		USER		VXX:EDMI2=+00010		EDMI2=+00010	✓	✓
	DVI-D IN-EDID RESOLUTION	1024x768p		VXX:EDRS2=1024:0768:p	QVX:EDRS2	EDRS2=1024:0768:p	✓	✓
		1280x720p		VXX:EDRS2=1280:0720:p		EDRS2=1280:0720:p	✓	✓
		1280x768p		VXX:EDRS2=1280:0768:p		EDRS2=1280:0768:p	✓	✓
		1280x800p		VXX:EDRS2=1280:0800:p		EDRS2=1280:0800:p	✓	✓
		1280x1024p		VXX:EDRS2=1280:1024:p		EDRS2=1280:1024:p	✓	✓
		1366x768p		VXX:EDRS2=1366:0768:p		EDRS2=1366:0768:p	✓	✓
		1400x1050p		VXX:EDRS2=1400:1050:p		EDRS2=1400:1050:p	✓	✓
		1440x900p		VXX:EDRS2=1440:0900:p		EDRS2=1440:0900:p	✓	✓
		1600x900p		VXX:EDRS2=1600:0900:p		EDRS2=1600:0900:p	✓	✓
		1600x1200p		VXX:EDRS2=1600:1200:p		EDRS2=1600:1200:p	✓	✓
		1680x1050p		VXX:EDRS2=1680:1050:p		EDRS2=1680:1050:p	✓	✓
		1920x1080p		VXX:EDRS2=1920:1080:p		EDRS2=1920:1080:p	✓	✓
		1920x1080i		VXX:EDRS2=1920:1080:i		EDRS2=1920:1080:i	✓	✓
		1920x1200p		VXX:EDRS2=1920:1200:p		EDRS2=1920:1200:p	✓	✓
	DVI-D IN-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX:EDVI2=+06000	QVX:EDVI2	EDVI2=+06000	✓	✓
		50Hz		VXX:EDVI2=+05000		EDVI2=+05000	✓	✓
		48Hz		VXX:EDVI2=+04800		EDVI2=+04800	✓	✓
		30Hz		VXX:EDVI2=+03000		EDVI2=+03000	✓	✓
		25Hz		VXX:EDVI2=+02500		EDVI2=+02500	✓	✓
		24Hz		VXX:EDVI2=+02400		EDVI2=+02400	✓	✓
	DVI-D IN-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:EDDS1=*****:*:****	QVX:EDDS1	EDDS1=*****:*:****	✓	✓
		* PARAMETER1	1024x768	VXX:EDDS1=1024:0768:*:****		EDDS1=1024:0768:*:****	✓	✓
			1280x720	VXX:EDDS1=1280:0720:*:****		EDDS1=1280:0720:*:****	✓	✓
			1280x768	VXX:EDDS1=1280:0768:*:****		EDDS1=1280:0768:*:****	✓	✓
			1280x800	VXX:EDDS1=1280:0800:*:****		EDDS1=1280:0800:*:****	✓	✓
			1280x1024	VXX:EDDS1=1280:1024:*:****		EDDS1=1280:1024:*:****	✓	✓
			1366x768	VXX:EDDS1=1366:0768:*:****		EDDS1=1366:0768:*:****	✓	✓
			1400x1050	VXX:EDDS1=1400:1050:*:****		EDDS1=1400:1050:*:****	✓	✓
			1440x900	VXX:EDDS1=1440:0900:*:****		EDDS1=1440:0900:*:****	✓	✓
			1600x900	VXX:EDDS1=1600:0900:*:****		EDDS1=1600:0900:*:****	✓	✓
			1600x1200	VXX:EDDS1=1600:1200:*:****		EDDS1=1600:1200:*:****	✓	✓
			1680x1050	VXX:EDDS1=1680:1050:*:****		EDDS1=1680:1050:*:****	✓	✓
			1920x1080	VXX:EDDS1=1920:1080:*:****		EDDS1=1920:1080:*:****	✓	✓
			1920x1200	VXX:EDDS1=1920:1200:*:****		EDDS1=1920:1200:*:****	✓	✓
		* PARAMETER2	Progressive Interlace	VXX:EDDS1=*****:p:**** VXX:EDDS1=*****:i:****		EDDS1=*****:p:**** EDDS1=*****:i:****	✓	✓
		* PARAMETER3	60Hz	VXX:EDDS1=*****:*:6000		EDDS1=*****:*:6000	✓	✓
			50Hz	VXX:EDDS1=*****:*:5000		EDDS1=*****:*:5000	✓	✓
			48Hz	VXX:EDDS1=*****:*:4800		EDDS1=*****:*:4800	✓	✓
			30Hz	VXX:EDDS1=*****:*:3000		EDDS1=*****:*:3000	✓	✓
			25Hz	VXX:EDDS1=*****:*:2500		EDDS1=*****:*:2500	✓	✓
			24Hz	VXX:EDDS1=*****:*:2400		EDDS1=*****:*:2400	✓	✓
	DVI-D IN-EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX:ESDS1	ESDS1=*****:*:****	✓	✓
		* PARAMETER1	1024x768			ESDS1=1024:0768:*:****	✓	✓
			1280x720			ESDS1=1280:0720:*:****	✓	✓
			1280x768			ESDS1=1280:0768:*:****	✓	✓
			1280x800			ESDS1=1280:0800:*:****	✓	✓
			1280x1024			ESDS1=1280:1024:*:****	✓	✓
			1366x768			ESDS1=1366:0768:*:****	✓	✓
			1400x1050			ESDS1=1400:1050:*:****	✓	✓
			1440x900			ESDS1=1440:0900:*:****	✓	✓
			1600x900			ESDS1=1600:0900:*:****	✓	✓
			1600x1200			ESDS1=1600:1200:*:****	✓	✓
			1680x1050			ESDS1=1680:1050:*:****	✓	✓
			1920x1080			ESDS1=1920:1080:*:****	✓	✓
			1920x1200			ESDS1=1920:1200:*:****	✓	✓
		* PARAMETER2	Progressive Interlace			ESDS1=*****:p:**** ESDS1=*****:i:****	✓	✓
		* PARAMETER3	60Hz			ESDS1=*****:*:6000	✓	✓
			50Hz			ESDS1=*****:*:5000	✓	✓
			48Hz			ESDS1=*****:*:4800	✓	✓
			30Hz			ESDS1=*****:*:3000	✓	✓
			25Hz			ESDS1=*****:*:2500	✓	✓
			24Hz			ESDS1=*****:*:2400	✓	✓
	HDMI IN-SIGNAL LEVEL	0-1023		VXX:HSLI0=+00000	QVX:HSLI0	HSLI0=+00000	✓	✓
	HDMI IN-EDID MODE	64-940		VXX:HSLI0=+00001		HSLI0=+00001	✓	✓
		AUTO		VXX:HSLI0=+00002		HSLI0=+00002	✓	✓
		DEFAULT		VXX:EDMI3=+00000	QVX:EDMI3	EDMI3=+00000	✓	✓
	HDMI IN-EDID RESOLUTION	SCREEN FIT		VXX:EDMI3=+00001		EDMI3=+00001	✓	✓
		USER		VXX:EDMI3=+00010		EDMI3=+00010	✓	✓
		1024x768p		VXX:EDRS3=1024:0768:p	QVX:EDRS3	EDRS3=1024:0768:p	✓	✓
		1280x720p		VXX:EDRS3=1280:0720:p		EDRS3=1280:0720:p	✓	✓
		1280x768p		VXX:EDRS3=1280:0768:p		EDRS3=1280:0768:p	✓	✓
		1280x800p		VXX:EDRS3=1280:0800:p		EDRS3=1280:0800:p	✓	✓
		1280x1024p		VXX:EDRS3=1280:1024:p		EDRS3=1280:1024:p	✓	✓
		1366x768p		VXX:EDRS3=1366:0768:p		EDRS3=1366:0768:p	✓	✓
		1400x1050p		VXX:EDRS3=1400:1050:p		EDRS3=1400:1050:p	✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
		1440x900p		VXX:EDRS3=1440:0900:p		EDRS3=1440:0900:p	✓	✓
		1600x900p		VXX:EDRS3=1600:0900:p		EDRS3=1600:0900:p	✓	✓
		1600x1200p		VXX:EDRS3=1600:1200:p		EDRS3=1600:1200:p	✓	✓
		1680x1050p		VXX:EDRS3=1680:1050:p		EDRS3=1680:1050:p	✓	✓
		1920x1080p		VXX:EDRS3=1920:1080:p		EDRS3=1920:1080:p	✓	✓
		1920x1080i		VXX:EDRS3=1920:1080:i		EDRS3=1920:1080:i	✓	✓
		1920x1200p		VXX:EDRS3=1920:1200:p		EDRS3=1920:1200:p	✓	✓
		3840x2400p		VXX:EDRS3=3840:2400:p		EDRS3=3840:2400:p	✓	✓
	HDMI IN-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX:EDVI3=+06000	QVX:EDVI3	EDVI3=+06000	✓	✓
		50Hz		VXX:EDVI3=+05000		EDVI3=+05000	✓	✓
		48Hz		VXX:EDVI3=+04800		EDVI3=+04800	✓	✓
		30Hz		VXX:EDVI3=+03000		EDVI3=+03000	✓	✓
		25Hz		VXX:EDVI3=+02500		EDVI3=+02500	✓	✓
		24Hz		VXX:EDVI3=+02400		EDVI3=+02400	✓	✓
	HDMI IN-HDMI1 EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:EDHS1=*****:*:****	QVX:EHS1	EDHS1=*****:*:****	✓	✓
		* PARAMETER1	1024x768	VXX:EDHS1=1024:0768:*:****		EDHS1=1024:0768:*:****	✓	✓
			1280x720	VXX:EDHS1=1280:0720:*:****		EDHS1=1280:0720:*:****	✓	✓
			1280x768	VXX:EDHS1=1280:0768:*:****		EDHS1=1280:0768:*:****	✓	✓
			1280x800	VXX:EDHS1=1280:0800:*:****		EDHS1=1280:0800:*:****	✓	✓
			1280x1024	VXX:EDHS1=1280:1024:*:****		EDHS1=1280:1024:*:****	✓	✓
			1366x768	VXX:EDHS1=1366:0768:*:****		EDHS1=1366:0768:*:****	✓	✓
			1400x1050	VXX:EDHS1=1400:1050:*:****		EDHS1=1400:1050:*:****	✓	✓
			1440x900	VXX:EDHS1=1440:0900:*:****		EDHS1=1440:0900:*:****	✓	✓
			1600x900	VXX:EDHS1=1600:0900:*:****		EDHS1=1600:0900:*:****	✓	✓
			1600x1200	VXX:EDHS1=1600:1200:*:****		EDHS1=1600:1200:*:****	✓	✓
			1680x1050	VXX:EDHS1=1680:1050:*:****		EDHS1=1680:1050:*:****	✓	✓
			1920x1080	VXX:EDHS1=1920:1080:*:****		EDHS1=1920:1080:*:****	✓	✓
			1920x1200	VXX:EDHS1=1920:1200:*:****		EDHS1=1920:1200:*:****	✓	✓
			3840x2400	VXX:EDHS1=3840:2400:*:****		EDHS1=3840:2400:*:****	✓	✓
		* PARAMETER2	Progressive Interlace	VXX:EDHS1=*****:p:**** VXX:EDHS1=*****:i:****		EDHS1=*****:p:**** EDHS1=*****:i:****	✓	✓
		* PARAMETER3	60Hz	VXX:EDHS1=*****:*:6000		EDHS1=*****:*:6000	✓	✓
			50Hz	VXX:EDHS1=*****:*:5000		EDHS1=*****:*:5000	✓	✓
			48Hz	VXX:EDHS1=*****:*:4800		EDHS1=*****:*:4800	✓	✓
			30Hz	VXX:EDHS1=*****:*:3000		EDHS1=*****:*:3000	✓	✓
			25Hz	VXX:EDHS1=*****:*:2500		EDHS1=*****:*:2500	✓	✓
			24Hz	VXX:EDHS1=*****:*:2400		EDHS1=*****:*:2400	✓	✓
	HDMI IN-HDMI 1 EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX:ESHS1	ESHS1=*****:*:****	✓	✓
		* PARAMETER1	1024x768			ESHS1=1024:0768:*:****	✓	✓
			1280x720			ESHS1=1280:0720:*:****	✓	✓
			1280x768			ESHS1=1280:0768:*:****	✓	✓
			1280x800			ESHS1=1280:0800:*:****	✓	✓
			1280x1024			ESHS1=1280:1024:*:****	✓	✓
			1366x768			ESHS1=1366:0768:*:****	✓	✓
			1400x1050			ESHS1=1400:1050:*:****	✓	✓
			1440x900			ESHS1=1440:0900:*:****	✓	✓
			1600x900			ESHS1=1600:0900:*:****	✓	✓
			1600x1200			ESHS1=1600:1200:*:****	✓	✓
			1680x1050			ESHS1=1680:1050:*:****	✓	✓
			1920x1080			ESHS1=1920:1080:*:****	✓	✓
			1920x1200			ESHS1=1920:1200:*:****	✓	✓
			3840x2400			ESHS1=3840:2400:*:****	✓	✓
		* PARAMETER2	Progressive Interlace			ESHS1=*****:p:**** ESHS1=*****:i:****	✓	✓
		* PARAMETER3	60Hz			ESHS1=*****:*:6000	✓	✓
			50Hz			ESHS1=*****:*:5000	✓	✓
			48Hz			ESHS1=*****:*:4800	✓	✓
			30Hz			ESHS1=*****:*:3000	✓	✓
			25Hz			ESHS1=*****:*:2500	✓	✓
			24Hz			ESHS1=*****:*:2400	✓	✓
	HDMI IN-HDMI1 EDID SELECT	4K/60p		VXX:HESI1=+00000	QVX:HESI1	HESI1=+00000	✓	✓
		4K/30p		VXX:HESI1=+00001		HESI1=+00001	✓	✓
		2K		VXX:HESI1=+00002		HESI1=+00002	✓	✓
	DIGITAL LINK-SIGNAL LEVEL	AUTO		VXX:DKLI1=+00000	QVX:DKLI1	DKLI1=+00000	✓	✓
		0-1023 64-940		VXX:DKLI1=+00001 VXX:DKLI1=+00002		DKLI1=+00001 DKLI1=+00002	✓	✓
	DIGITAL LINK-EDID SELECT (SINGLE LINK)	EDID1:4K/60p		VXX:LESI1=+00000	QVX:LESI1	LESI1=+00000	✓	✓
		EDID2:4K/30p		VXX:LESI1=+00001		LESI1=+00001	✓	✓
		EDID3:2K		VXX:LESI1=+00002		LESI1=+00002	✓	✓
	DIGITAL LINK-EDID MODE	DEFAULT		VXX:EDMI4=+00000	QVX:EDMI4	EDMI4=+00000	✓	✓
		SCREEN FIT		VXX:EDMI4=+00001		EDMI4=+00001	✓	✓
		USER		VXX:EDMI4=+00010		EDMI4=+00010	✓	✓
	DIGITAL LINK-EDID RESOLUTION	1024x768p		VXX:EDRS4=1024:0768:p	QVX:EDRS4	EDRS4=1024:0768:p	✓	✓
		1280x720p		VXX:EDRS4=1280:0720:p		EDRS4=1280:0720:p	✓	✓
		1280x768p		VXX:EDRS4=1280:0768:p		EDRS4=1280:0768:p	✓	✓
		1280x800p		VXX:EDRS4=1280:0800:p		EDRS4=1280:0800:p	✓	✓
		1280x1024p		VXX:EDRS4=1280:1024:p		EDRS4=1280:1024:p	✓	✓
		1366x768p		VXX:EDRS4=1366:0768:p		EDRS4=1366:0768:p	✓	✓
		1400x1050p		VXX:EDRS4=1400:1050:p		EDRS4=1400:1050:p	✓	✓
		1440x900p		VXX:EDRS4=1440:0900:p		EDRS4=1440:0900:p	✓	✓
		1600x900p		VXX:EDRS4=1600:0900:p		EDRS4=1600:0900:p	✓	✓
		1600x1200p		VXX:EDRS4=1600:1200:p		EDRS4=1600:1200:p	✓	✓
		1680x1050p		VXX:EDRS4=1680:1050:p		EDRS4=1680:1050:p	✓	✓
		1920x1080p		VXX:EDRS4=1920:1080:p		EDRS4=1920:1080:p	✓	✓
		1920x1080i		VXX:EDRS4=1920:1080:i		EDRS4=1920:1080:i	✓	✓
		1920x1200p		VXX:EDRS4=1920:1200:p		EDRS4=1920:1200:p	✓	✓
		3840x2400p		VXX:EDRS4=3840:2400:p		EDRS4=3840:2400:p	✓	✓
	DIGITAL LINK-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX:EDVI4=+06000	QVX:EDVI4	EDVI4=+06000	✓	✓
		50Hz		VXX:EDVI4=+05000		EDVI4=+05000	✓	✓
		48Hz		VXX:EDVI4=+04800		EDVI4=+04800	✓	✓
		30Hz		VXX:EDVI4=+03000		EDVI4=+03000	✓	✓
		25Hz		VXX:EDVI4=+02500		EDVI4=+02500	✓	✓
		24Hz		VXX:EDVI4=+02400		EDVI4=+02400	✓	✓
	DIGITAL LINK-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:EDLS1=*****:*:****	QVX:EDLS1	EDLS1=*****:*:****	✓	✓
		* PARAMETER1	1024x768	VXX:EDLS1=1024:0768:*:****		EDLS1=1024:0768:*:****	✓	✓
			1280x720	VXX:EDLS1=1280:0720:*:****		EDLS1=1280:0720:*:****	✓	✓
			1280x768	VXX:EDLS1=1280:0768:*:****		EDLS1=1280:0768:*:****	✓	✓
			1280x800	VXX:EDLS1=1280:0800:*:****		EDLS1=1280:0800:*:****	✓	✓
			1280x1024	VXX:EDLS1=1280:1024:*:****		EDLS1=1280:1024:*:****	✓	✓
			1366x768	VXX:EDLS1=1366:0768:*:****		EDLS1=1366:0768:*:****	✓	✓
			1400x1050	VXX:EDLS1=1400:1050:*:****		EDLS1=1400:1050:*:****	✓	✓
			1440x900	VXX:EDLS1=1440:0900:*:****		EDLS1=1440:0900:*:****	✓	✓
			1600x900	VXX:EDLS1=1600:0900:*:****		EDLS1=1600:0900:*:****	✓	✓
			1600x1200	VXX:EDLS1=1600:1200:*:****		EDLS1=1600:1200:*:****	✓	✓
			1680x1050	VXX:EDLS1=1680:1050:*:****		EDLS1=1680:1050:*:****	✓	✓
			1920x1080	VXX:EDLS1=1920:1080:*:****		EDLS1=1920:1080:*:****	✓	✓
			1920x1200	VXX:EDLS1=1920:1200:*:****		EDLS1=1920:1200:*:****	✓	✓
			3840x2400	VXX:EDLS1=3840:2400:*:****		EDLS1=3840:2400:*:****	✓	✓
		* PARAMETER2	Progressive Interlace	VXX:EDLS1=*****:p:**** VXX:EDLS1=*****:i:****		EDLS1=*****:p:**** EDLS1=*****:i:****	✓	✓
		* PARAMETER3	60Hz	VXX:EDLS1=*****:*:6000		EDLS1=*****:*:6000	✓	✓
			50Hz	VXX:EDLS1=*****:*:5000		EDLS1=*****:*:5000	✓	✓
			48Hz	VXX:EDLS1=*****:*:4800		EDLS1=*****:*:4800	✓	✓
			30Hz	VXX:EDLS1=*****:*:3000		EDLS1=*****:*:3000	✓	✓
			25Hz	VXX:EDLS1=*****:*:2500		EDLS1=*****:*:2500	✓	✓
			24Hz	VXX:EDLS1=*****:*:2400		EDLS1=*****:*:2400	✓	✓
	DIGITAL LINK-EDID STATUS RESOLUTION / VERTICAL SCAN	* PARAMETER	1024x768		QVX:ESLS1	ESLS1=*****:*:**** ESLS1=1024:0768:*:****	✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
	FREQUENCY	* PARAMETER1	1280x720			ESLS1=1280:0720:*:****	✓	✓
			1280x768			ESLS1=1280:0768:*:****	✓	✓
			1280x800			ESLS1=1280:0800:*:****	✓	✓
			1280x1024			ESLS1=1280:1024:*:****	✓	✓
			1366x768			ESLS1=1366:0768:*:****	✓	✓
			1400x1050			ESLS1=1400:1050:*:****	✓	✓
			1440x900			ESLS1=1440:0900:*:****	✓	✓
			1600x900			ESLS1=1600:0900:*:****	✓	✓
			1600x1200			ESLS1=1600:1200:*:****	✓	✓
			1680x1050			ESLS1=1680:1050:*:****	✓	✓
			1920x1080			ESLS1=1920:1080:*:****	✓	✓
			1920x1200			ESLS1=1920:1200:*:****	✓	✓
			3840x2400			ESLS1=3840:2400:*:****	✓	✓
		* PARAMETER2	Progressive			ESLS1=*****:p:****	✓	✓
			Interlace			ESLS1=*****:i:****	✓	✓
		* PARAMETER3	60Hz			ESLS1=*****:*:6000	✓	✓
			50Hz			ESLS1=*****:*:5000	✓	✓
			48Hz			ESLS1=*****:*:4800	✓	✓
			30Hz			ESLS1=*****:*:3000	✓	✓
			25Hz			ESLS1=*****:*:2500	✓	✓
			24Hz			ESLS1=*****:*:2400	✓	✓
	SDI IN-SIGNAL LEVEL	64-940		0ED:SDI-LEVEL0	QED:SDI-LEVEL	0	✓	✓
		4-1019		0ED:SDI-LEVEL1		1	✓	✓
	SDI IN-SIGNAL LEVEL (SDI1)	64-940		VXX:SSLI1=+00000	QVX:SSLI1	SSLI1=+00000	✓	✓
		4-1019		VXX:SSLI1=+00001		SSLI1=+00001	✓	✓
	SDI IN-BIT DEPTH (SDI1)	AUTO		VXX:SBTI1=+00000	QVX:SBTI1	SBTI1=+00000	✓	✓
		12-bit		VXX:SBTI1=+00001		SBTI1=+00001	✓	✓
		10-bit		VXX:SBTI1=+00002		SBTI1=+00002	✓	✓
	SDI IN-3G SDI MAPPING (SDI1)	AUTO		VXX:SGMI1=+00000	QVX:SGMI1	SGMI1=+00000	✓	✓
		LEVEL A		VXX:SGMI1=+00001		SGMI1=+00001	✓	✓
		LEVEL B		VXX:SGMI1=+00002		SGMI1=+00002	✓	✓
	SDI RESOLUTION	* PARAMETER		VXX:*****=+*****	QVX:*****	*****=+*****	✓	✓
		* PARAMETER1	SDI1	VXX:SRSI1=+*****		SRSI1=+*****	✓	✓
		* PARAMETER2	AUTO	VXX:*****=+00000		*****=+00000	✓	✓
			1280x720p	VXX:*****=+00003		*****=+00003	✓	✓
			1920x1080i	VXX:*****=+00005		*****=+00005	✓	✓
			1920x1080p	VXX:*****=+00006		*****=+00006	✓	✓
			1920x1080sF	VXX:*****=+00007		*****=+00007	✓	✓
			2048x1080p	VXX:*****=+00009		*****=+00009	✓	✓
	SDI SYSTEM SELECTOR	* PARAMETER		VXX:SYSS1=*:****:*****	QVX:SYSS1=*:****	SYSS1=*:****:*****	✓	✓
		* PARAMETER1, 2	SDI1	VXX:SYSS1=1:1		SYSS1=1:1:*****	✓	✓
		* PARAMETER3	AUTO	VXX:SYSS1=*:****:00000		SYSS1=*:****:00000	✓	✓
			RGB	VXX:SYSS1=*:****:00001		SYSS1=*:****:00001	✓	✓
			YPbPr4:4:4	VXX:SYSS1=*:****:00002		SYSS1=*:****:00002	✓	✓
			YPbPr4:2:2	VXX:SYSS1=*:****:00003		SYSS1=*:****:00003	✓	✓
	SLOT - SDI IN - SDI LINK(ET-MDN12G10)	* PARAMETER		VXX:*****=VXX:*****=+00000		*****=*****=+*****	✓	✓
		* PARAMETER1, 2	SLOT1	VXX:SLSS1=VXX:SLKI3=+*****		SLSS1=SLKI3=+*****	✓	✓
		* PARAMETER3	SNGLE LINK	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			DUAL LINK	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓
			QUAD LINK	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓
			AUTO	VXX:*****=VXX:*****=+00010		*****=*****=+00010	✓	✓
	SLOT : SDI : SDI RESOLUTION	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2 (ET-MDN12G10)	SLOT1:SDI1	VXX:SLSS1=VXX:SRSI1=+*****		SLSS1=SRSI1=+*****	✓	✓
			SLOT1:SDI2	VXX:SLSS1=VXX:SRSI2=+*****		SLSS1=SRSI2=+*****	✓	✓
			SLOT1:SDI3	VXX:SLSS1=VXX:SRSI3=+*****		SLSS1=SRSI3=+*****	✓	✓
			SLOT1:SDI4	VXX:SLSS1=VXX:SRSI4=+*****		SLSS1=SRSI4=+*****	✓	✓
			DUAL LINK(SLOT1:SDI1+3)	VXX:SLSS1=VXX:SRDI1=+*****		SLSS1=SRDI1=+*****	✓	✓
			QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:SRQI1=+*****		SLSS1=SRQI1=+*****	✓	✓
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			1280x720p	VXX:*****=VXX:*****=+00003		*****=*****=+00003	✓	✓
			1920x1080i	VXX:*****=VXX:*****=+00005		*****=*****=+00005	✓	✓
			1920x1080p	VXX:*****=VXX:*****=+00006		*****=*****=+00006	✓	✓
			1920x1080sF	VXX:*****=VXX:*****=+00007		*****=*****=+00007	✓	✓
			2048x1080p	VXX:*****=VXX:*****=+00009		*****=*****=+00009	✓	✓
			3840x2160p	VXX:*****=VXX:*****=+00011		*****=*****=+00011	✓	✓
			4096x2160p	VXX:*****=VXX:*****=+00013		*****=*****=+00013	✓	✓
	SLOT : SDI : SDI 3G-SDI MAPPING	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SGMI1=+*****		SLSS1=SGMI1=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SGMI2=+*****		SLSS1=SGMI2=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SGMI3=+*****		SLSS1=SGMI3=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SGMI4=+*****		SLSS1=SGMI4=+*****	✓	✓
			DUAL LINK(SLOT1:SDI1+3)	VXX:SLSS1=VXX:DGMI1=+*****		SLSS1=DGMI1=+*****	✓	✓
			QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:QGMI1=+*****		SLSS1=QGMI1=+*****	✓	✓
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			LEVEL A	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓
			LEVEL B	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓
		* PARAMETER3 (ET-MDN12G10)	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			TYPE1/LEVEL A	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓
			TYPE2/LEVEL B	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓
	SLOT : SDI : SDI SYSTEM SELECTOR	* PARAMETER		VXX:*****=VXX:*****=*:****:*****	QVX:*****=QVX:*****=*:****	*****=*****=*:****:*****	✓	✓
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SYSS1=1:1:****	QVX:SLSS1=QVX:SYSS1=1:1	SLSS1=SYSS1=1:1:*****	✓	✓
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SYSS1=1:2:****	QVX:SLSS1=QVX:SYSS1=1:2	SLSS1=SYSS1=1:2:*****	✓	✓
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SYSS1=1:3:****	QVX:SLSS1=QVX:SYSS1=1:3	SLSS1=SYSS1=1:3:*****	✓	✓
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SYSS1=1:4:****	QVX:SLSS1=QVX:SYSS1=1:4	SLSS1=SYSS1=1:4:*****	✓	✓
			DUAL LINK(SLOT1:SDI1+3)	VXX:SLSS1=VXX:SYSS1=2:13:****	QVX:SLSS1=QVX:SYSS1=2:13	SLSS1=SYSS1=2:13:*****	✓	✓
			QUAD LINK(SLOT1:SDI1+2+3+4)	VXX:SLSS1=VXX:SYSS1=4:1234:****	QVX:SLSS1=QVX:SYSS1=4:1234	SLSS1=SYSS1=4:1234:*****	✓	✓
		* PARAMETER3	AUTO	VXX:*****=VXX:SYSS1=*:****:00000		*****=SYSS1=*:****:00000	✓	✓
			RGB	VXX:*****=VXX:SYSS1=*:****:00001		*****=SYSS1=*:****:00001	✓	✓
			YPbPr4:4:4	VXX:*****=VXX:SYSS1=*:****:00002		*****=SYSS1=*:****:00002	✓	✓
			YPbPr4:2:2	VXX:*****=VXX:SYSS1=*:****:00003		*****=SYSS1=*:****:00003	✓	✓
	SLOT : SDI : BIT DEPTH	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SBTI1=+*****		SLSS1=SBTI1=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SBTI2=+*****		SLSS1=SBTI2=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SBTI4=+*****		SLSS1=SBTI4=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SBTI5=+*****		SLSS1=SBTI5=+*****	✓	✓
			DUAL LINK(SDI1+3)	VXX:SLSS1=VXX:SBTI3=+*****		SLSS1=SBTI3=+*****	✓	✓
			QUAD LINK (SDI1+2+3+4)	VXX:SLSS1=VXX:SBTI7=+*****		SLSS1=SBTI7=+*****	✓	✓
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			12-bit	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓
			10-bit	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓
	SLOT : SDI : SIGNAL LEVEL	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SSLI1=+*****		SLSS1=SSLI1=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI2)	VXX:SLSS1=VXX:SSLI2=+*****		SLSS1=SSLI2=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI3)	VXX:SLSS1=VXX:SSLI4=+*****		SLSS1=SSLI4=+*****	✓	✓
			SINGLE LINK(SLOT1:SDI4)	VXX:SLSS1=VXX:SSLI5=+*****		SLSS1=SSLI5=+*****	✓	✓
			DUAL LINK(SDI1+3)	VXX:SLSS1=VXX:SSLI3=+*****		SLSS1=SSLI3=+*****	✓	✓
			QUAD LINK (SDI1+2+3+4)	VXX:SLSS1=VXX:SSLI7=+*****		SLSS1=SSLI7=+*****	✓	✓
		* PARAMETER3	64-940	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			4-1019	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓
	SLOT : HDMI : SIGNAL LEVEL	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	HDMI1	VXX:SLSS1=VXX:HSLI1=+*****		SLSS1=HSLI1=+*****	✓	✓
			HDMI2	VXX:SLSS1=VXX:HSLI2=+*****		SLSS1=HSLI2=+*****	✓	✓
		* PARAMETER3	0-1023	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			64-940	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓
			AUTO	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓
	SLOT : HDMI : EDID SELECT	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	HDMI1	VXX:SLSS1=VXX:HESI1=+*****		SLSS1=HESI1=+*****	✓	✓
			HDMI2	VXX:SLSS1=VXX:HESI2=+*****		SLSS1=HESI2=+*****	✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
		* PARAMETER3	EDID1:4K/60p EDID2:4K/30p EDID3:2K	VXX:*****=VXX:*****=+00000 VXX:*****=VXX:*****=+00001 VXX:*****=VXX:*****=+00002		*****=*****=+00000 *****=*****=+00001 *****=*****=+00002	✓	✓
		* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	HDMI1 HDMI2	VXX:SLSS1=VXX:EDMI3=+***** VXX:SLSS1=VXX:EDMI6=+*****		SLSS1=EDMI3=+***** SLSS1=EDMI6=+*****	✓	✓
		* PARAMETER3	DEFAULT USER	VXX:*****=VXX:*****=+00000 VXX:*****=VXX:*****=+00010		*****=*****=+00000 *****=*****=+00010	✓	✓
		* PARAMETER		VXX:*****=VXX:*****=*****:*	QVX:*****=QVX:*****	*****=*****=*****:*	✓	✓
		* PARAMETER1, 2	HDMI1 HDMI2	VXX:SLSS1=VXX:EDRS3=*****:* VXX:SLSS1=VXX:EDRS6=*****:*		SLSS1=EDRS3=*****:* SLSS1=EDRS6=*****:*	✓	✓
		* PARAMETER3	1024x768	VXX:*****=VXX:*****=1024:0768:*		*****=*****=1024:0768:*	✓	✓
			1280x720	VXX:*****=VXX:*****=1280:0720:*		*****=*****=1280:0720:*	✓	✓
			1280x800	VXX:*****=VXX:*****=1280:0800:*		*****=*****=1280:0800:*	✓	✓
			1280x1024	VXX:*****=VXX:*****=1280:1024:*		*****=*****=1280:1024:*	✓	✓
			1366x768	VXX:*****=VXX:*****=1366:0768:*		*****=*****=1366:0768:*	✓	✓
			1400x1050	VXX:*****=VXX:*****=1400:1050:*		*****=*****=1400:1050:*	✓	✓
			1440x900	VXX:*****=VXX:*****=1440:0900:*		*****=*****=1440:0900:*	✓	✓
			1600x900	VXX:*****=VXX:*****=1600:0900:*		*****=*****=1600:0900:*	✓	✓
			1600x1200	VXX:*****=VXX:*****=1600:1200:*		*****=*****=1600:1200:*	✓	✓
			1680x1050	VXX:*****=VXX:*****=1680:1050:*		*****=*****=1680:1050:*	✓	✓
			1920x1080	VXX:*****=VXX:*****=1920:1080:*		*****=*****=1920:1080:*	✓	✓
			1920x1200	VXX:*****=VXX:*****=1920:1200:*		*****=*****=1920:1200:*	✓	✓
			3840x2400	VXX:*****=VXX:*****=3840:2400:*		*****=*****=3840:2400:*	✓	✓
		* PARAMETER4	Progressive Interlace	VXX:*****=VXX:*****=*****:p VXX:*****=VXX:*****=*****:i		*****=*****=*****:p *****=*****=*****:i	✓	✓
	SLOT : HDMI : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	HDMI1 HDMI2	VXX:SLSS1=VXX:EDVI3=+***** VXX:SLSS1=VXX:EDVI6=+*****		SLSS1=EDVI3=+***** SLSS1=EDVI6=+*****	✓	✓
		* PARAMETER3	60Hz	VXX:*****=VXX:*****=+06000		*****=*****=+06000	✓	✓
			50Hz	VXX:*****=VXX:*****=+05000		*****=*****=+05000	✓	✓
			48Hz	VXX:*****=VXX:*****=+04800		*****=*****=+04800	✓	✓
			30Hz	VXX:*****=VXX:*****=+03000		*****=*****=+03000	✓	✓
			25Hz	VXX:*****=VXX:*****=+02500		*****=*****=+02500	✓	✓
		* PARAMETER4	Progressive Interlace	VXX:*****=VXX:*****=*****:p VXX:*****=VXX:*****=*****:i		*****=*****=*****:p *****=*****=*****:i	✓	✓
	SLOT : HDMI : EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:*****=VXX:*****=*****:*	QVX:*****=QVX:*****	*****=*****=*****:*	✓	✓
		* PARAMETER1, 2	HDMI1 HDMI2	VXX:SLSS1=VXX:EDHS1=*****:* VXX:SLSS1=VXX:EDHS2=*****:*		SLSS1=EDHS1=*****:* SLSS1=EDHS2=*****:*	✓	✓
		* PARAMETER3	1024x768	VXX:*****=VXX:*****=1024:0768:*		*****=*****=1024:0768:*	✓	✓
			1280x720	VXX:*****=VXX:*****=1280:0720:*		*****=*****=1280:0720:*	✓	✓
			1280x800	VXX:*****=VXX:*****=1280:0800:*		*****=*****=1280:0800:*	✓	✓
			1280x1024	VXX:*****=VXX:*****=1280:1024:*		*****=*****=1280:1024:*	✓	✓
			1366x768	VXX:*****=VXX:*****=1366:0768:*		*****=*****=1366:0768:*	✓	✓
			1400x1050	VXX:*****=VXX:*****=1400:1050:*		*****=*****=1400:1050:*	✓	✓
			1440x900	VXX:*****=VXX:*****=1440:0900:*		*****=*****=1440:0900:*	✓	✓
			1600x900	VXX:*****=VXX:*****=1600:0900:*		*****=*****=1600:0900:*	✓	✓
			1600x1200	VXX:*****=VXX:*****=1600:1200:*		*****=*****=1600:1200:*	✓	✓
			1680x1050	VXX:*****=VXX:*****=1680:1050:*		*****=*****=1680:1050:*	✓	✓
			1920x1080	VXX:*****=VXX:*****=1920:1080:*		*****=*****=1920:1080:*	✓	✓
			1920x1200	VXX:*****=VXX:*****=1920:1200:*		*****=*****=1920:1200:*	✓	✓
			3840x2400	VXX:*****=VXX:*****=3840:2400:*		*****=*****=3840:2400:*	✓	✓
		* PARAMETER4	Progressive Interlace	VXX:*****=VXX:*****=*****:p VXX:*****=VXX:*****=*****:i		*****=*****=*****:p *****=*****=*****:i	✓	✓
		* PARAMETERS5	60Hz	VXX:*****=VXX:*****=*****:*		*****=*****=*****:*	✓	✓
			50Hz	VXX:*****=VXX:*****=*****:*		*****=*****=*****:*	✓	✓
			48Hz	VXX:*****=VXX:*****=*****:*		*****=*****=*****:*	✓	✓
			30Hz	VXX:*****=VXX:*****=*****:*		*****=*****=*****:*	✓	✓
			25Hz	VXX:*****=VXX:*****=*****:*		*****=*****=*****:*	✓	✓
	SLOT : HDMI : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX:*****=QVX:*****	*****=*****=*****:*	✓	✓
		* PARAMETER1, 2	HDMI1 HDMI2			SLSS1=ESHS1=*****:* SLSS1=ESHS2=*****:*	✓	✓
		* PARAMETER3	1024x768			*****=*****=1024:0768:*	✓	✓
			1280x720			*****=*****=1280:0720:*	✓	✓
			1280x800			*****=*****=1280:0800:*	✓	✓
			1280x1024			*****=*****=1280:1024:*	✓	✓
			1366x768			*****=*****=1366:0768:*	✓	✓
			1400x1050			*****=*****=1400:1050:*	✓	✓
			1440x900			*****=*****=1440:0900:*	✓	✓
			1600x900			*****=*****=1600:0900:*	✓	✓
			1600x1200			*****=*****=1600:1200:*	✓	✓
			1680x1050			*****=*****=1680:1050:*	✓	✓
			1920x1080			*****=*****=1920:1080:*	✓	✓
			1920x1200			*****=*****=1920:1200:*	✓	✓
			3840x2400			*****=*****=3840:2400:*	✓	✓
		* PARAMETER4	Progressive Interlace			*****=*****=*****:p *****=*****=*****:i	✓	✓
		* PARAMETER5	60Hz			*****=*****=*****:*	✓	✓
			50Hz			*****=*****=*****:*	✓	✓
			48Hz			*****=*****=*****:*	✓	✓
			30Hz			*****=*****=*****:*	✓	✓
			25Hz			*****=*****=*****:*	✓	✓
	SLOT : DVI : SIGNAL LEVEL	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	DVI1 DVI2	VXX:SLSS1=VXX:DVII0=+***** VXX:SLSS1=VXX:DVII2=+*****		SLSS1=DVII0=+***** SLSS1=DVII2=+*****	✓	✓
		* PARAMETER3	0-255(PC)	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			16-235	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓
			AUTO	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓
	SLOT : DVI : EDID SELECT	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	DVI1 DVI2	VXX:SLSS1=VXX:DSLII1=+***** VXX:SLSS1=VXX:DSLII2=+*****		SLSS1=DSLII1=+***** SLSS1=DSLII2=+*****	✓	✓
		* PARAMETER3	EDID1:4K/60p	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			EDID2:4K/30p	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓
			EDID3:2K	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓
	SLOT : DVI : EDID MODE	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	DVI1 DVI2	VXX:SLSS1=VXX:EDMI2=+***** VXX:SLSS1=VXX:EDMI5=+*****		SLSS1=EDMI2=+***** SLSS1=EDMI5=+*****	✓	✓
		* PARAMETER3	DEFAULT	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
			USER	VXX:*****=VXX:*****=+00010		*****=*****=+00010	✓	✓
		* PARAMETER		VXX:*****=VXX:*****=*****:*	QVX:*****=QVX:*****	*****=*****=*****:*	✓	✓
	SLOT : DVI : EDID RESOLUTION	* PARAMETER1, 2	DVI1 DVI2	VXX:SLSS1=VXX:EDRS2=*****:* VXX:SLSS1=VXX:EDRS5=*****:*		SLSS1=EDRS2=*****:* SLSS1=EDRS5=*****:*	✓	✓
		* PARAMETER3	1024x768	VXX:*****=VXX:*****=1024:0768:*		*****=*****=1024:0768:*	✓	✓
			1280x720	VXX:*****=VXX:*****=1280:0720:*		*****=*****=1280:0720:*	✓	✓
			1280x800	VXX:*****=VXX:*****=1280:0800:*		*****=*****=1280:0800:*	✓	✓
			1280x1024	VXX:*****=VXX:*****=1280:1024:*		*****=*****=1280:1024:*	✓	✓
			1366x768	VXX:*****=VXX:*****=1366:0768:*		*****=*****=1366:0768:*	✓	✓
			1400x1050	VXX:*****=VXX:*****=1400:1050:*		*****=*****=1400:1050:*	✓	✓
			1440x900	VXX:*****=VXX:*****=1440:0900:*		*****=*****=1440:0900:*	✓	✓
			1600x900	VXX:*****=VXX:*****=1600:0900:*		*****=*****=1600:0900:*	✓	✓
			1600x1200	VXX:*****=VXX:*****=1600:1200:*		*****=*****=1600:1200:*	✓	✓
			1680x1050	VXX:*****=VXX:*****=1680:1050:*		*****=*****=1680:1050:*	✓	✓
			1920x1080	VXX:*****=VXX:*****=1920:1080:*		*****=*****=1920:1080:*	✓	✓
			1920x1200	VXX:*****=VXX:*****=1920:1200:*		*****=*****=1920:1200:*	✓	✓
			Progressive Interlace	VXX:*****=VXX:*****=*****:p VXX:*****=VXX:*****=*****:i		*****=*****=*****:p *****=*****=*****:i	✓	✓
		* PARAMETER4				*****=*****=*****:i	✓	✓
	SLOT : DVI : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	DVI1	VXX:SLSS1=VXX:EDVI2=+*****		SLSS1=EDVI2=+*****	✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
	SLOT : DVI1 : EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER1, 2	DVI2	VXX: SLSS1=VXX: EDVI5=+*****		SLSS1=EDVI5=+*****	✓	✓
		* PARAMETER3	60Hz	VXX: *****=VXX: *****=+06000		*****=*****=+06000	✓	✓
			50Hz	VXX: *****=VXX: *****=+05000		*****=*****=+05000	✓	✓
			48Hz	VXX: *****=VXX: *****=+04800		*****=*****=+04800	✓	✓
			30Hz	VXX: *****=VXX: *****=+03000		*****=*****=+03000	✓	✓
			24Hz	VXX: *****=VXX: *****=+02400		*****=*****=+02400	✓	✓
		* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓
		* PARAMETER		VXX: *****=VXX: *****=*****: *, *****	QVX: *****=QVX: *****	*****=*****=*****: *, *****	✓	✓
		* PARAMETER1, 2	DVI1	VXX: SLSS1=VXX: EDDS1=*****: *, *****		SLSS1=EDDS1=*****: *, *****	✓	✓
		* PARAMETER3	DVI2	VXX: SLSS1=VXX: EDDS2=*****: *, *****		SLSS1=EDDS2=*****: *, *****	✓	✓
			1024x768	VXX: *****=VXX: *****=1024:0768: *, *****		*****=*****=1024:0768: *, *****	✓	✓
			1280x720	VXX: *****=VXX: *****=1280:0720: *, *****		*****=*****=1280:0720: *, *****	✓	✓
			1280x800	VXX: *****=VXX: *****=1280:0800: *, *****		*****=*****=1280:0800: *, *****	✓	✓
			1280x1024	VXX: *****=VXX: *****=1280:1024: *, *****		*****=*****=1280:1024: *, *****	✓	✓
			1366x768	VXX: *****=VXX: *****=1366:0768: *, *****		*****=*****=1366:0768: *, *****	✓	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050: *, *****		*****=*****=1400:1050: *, *****	✓	✓
			1440x900	VXX: *****=VXX: *****=1440:0900: *, *****		*****=*****=1440:0900: *, *****	✓	✓
			1600x900	VXX: *****=VXX: *****=1600:0900: *, *****		*****=*****=1600:0900: *, *****	✓	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200: *, *****		*****=*****=1600:1200: *, *****	✓	✓
			1680x1050	VXX: *****=VXX: *****=1680:1050: *, *****		*****=*****=1680:1050: *, *****	✓	✓
			1920x1080	VXX: *****=VXX: *****=1920:1080: *, *****		*****=*****=1920:1080: *, *****	✓	✓
			1920x1200	VXX: *****=VXX: *****=1920:1200: *, *****		*****=*****=1920:1200: *, *****	✓	✓
		* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓
		* PARAMETERS5	60Hz	VXX: *****=VXX: *****=*****: *, 6000		*****=*****=*****: *, 6000	✓	✓
			50Hz	VXX: *****=VXX: *****=*****: *, 5000		*****=*****=*****: *, 5000	✓	✓
			48Hz	VXX: *****=VXX: *****=*****: *, 4800		*****=*****=*****: *, 4800	✓	✓
			30Hz	VXX: *****=VXX: *****=*****: *, 3000		*****=*****=*****: *, 3000	✓	✓
			24Hz	VXX: *****=VXX: *****=*****: *, 2400		*****=*****=*****: *, 2400	✓	✓
	SLOT : DVI1 : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX: *****=QVX: *****	*****=*****=*****: *, *****	✓	✓
		* PARAMETER1, 2	DVI1			SLSS1=ESDS1=*****: *, *****	✓	✓
		* PARAMETER3	DVI2			SLSS1=ESDS2=*****: *, *****	✓	✓
			1024x768			*****=*****=1024:0768: *, *****	✓	✓
			1280x720			*****=*****=1280:0720: *, *****	✓	✓
			1280x800			*****=*****=1280:0800: *, *****	✓	✓
			1280x1024			*****=*****=1280:1024: *, *****	✓	✓
			1366x768			*****=*****=1366:0768: *, *****	✓	✓
			1400x1050			*****=*****=1400:1050: *, *****	✓	✓
			1440x900			*****=*****=1440:0900: *, *****	✓	✓
			1600x900			*****=*****=1600:0900: *, *****	✓	✓
			1600x1200			*****=*****=1600:1200: *, *****	✓	✓
			1680x1050			*****=*****=1680:1050: *, *****	✓	✓
			1920x1080			*****=*****=1920:1080: *, *****	✓	✓
			1920x1200			*****=*****=1920:1200: *, *****	✓	✓
		* PARAMETER4	Progressive Interlace			*****=*****=*****: p: ***** *****=*****=*****: i: *****	✓	✓
		* PARAMETER5	60Hz			*****=*****=*****: *, 6000	✓	✓
			50Hz			*****=*****=*****: *, 5000	✓	✓
			48Hz			*****=*****=*****: *, 4800	✓	✓
			30Hz			*****=*****=*****: *, 3000	✓	✓
			24Hz			*****=*****=*****: *, 2400	✓	✓
	SLOT : DisplayPort : SIGNAL LEVEL	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: DPLI1=+*****		SLSS1=DPLI1=+*****	✓	✓
		* PARAMETER3	DisplayPort2	VXX: SLSS1=VXX: DPLI2=+*****		SLSS1=DPLI2=+*****	✓	✓
			0-1023	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			64-940	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓
			AUTO	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓	✓
	SLOT : DisplayPort : EDID MODE	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDMI8=+*****		SLSS1=EDMI8=+*****	✓	✓
		* PARAMETER3	DisplayPort2	VXX: SLSS1=VXX: EDMI9=+*****		SLSS1=EDMI9=+*****	✓	✓
			DEFAULT	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			USER	VXX: *****=VXX: *****=+00010		*****=*****=+00010	✓	✓
	SLOT : DisplayPort : EDID RESOLUTION	* PARAMETER		VXX: *****=VXX: *****=*****: *	QVX: *****=QVX: *****	*****=*****=*****: *	✓	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDRS8=*****: *		SLSS1=EDRS8=*****: *	✓	✓
		* PARAMETER3	DisplayPort2	VXX: SLSS1=VXX: EDRS9=*****: *		SLSS1=EDRS9=*****: *	✓	✓
			1024x768	VXX: *****=VXX: *****=1024:0768: *		*****=*****=1024:0768: *	✓	✓
			1280x720	VXX: *****=VXX: *****=1280:0720: *		*****=*****=1280:0720: *	✓	✓
			1280x800	VXX: *****=VXX: *****=1280:0800: *		*****=*****=1280:0800: *	✓	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050: *		*****=*****=1400:1050: *	✓	✓
			1600x900	VXX: *****=VXX: *****=1600:0900: *		*****=*****=1600:0900: *	✓	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200: *		*****=*****=1600:1200: *	✓	✓
			1920x1080	VXX: *****=VXX: *****=1920:1080: *		*****=*****=1920:1080: *	✓	✓
			1920x1200	VXX: *****=VXX: *****=1920:1200: *		*****=*****=1920:1200: *	✓	✓
			3840x2400	VXX: *****=VXX: *****=3840:2400: *		*****=*****=3840:2400: *	✓	✓
		* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓
	SLOT : DisplayPort : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=+*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDVI8=+*****		SLSS1=EDVI8=+*****	✓	✓
		* PARAMETER3	DisplayPort2	VXX: SLSS1=VXX: EDVI9=+*****		SLSS1=EDVI9=+*****	✓	✓
			60Hz	VXX: *****=VXX: *****=+06000		*****=*****=+06000	✓	✓
			50Hz	VXX: *****=VXX: *****=+05000		*****=*****=+05000	✓	✓
			48Hz	VXX: *****=VXX: *****=+04800		*****=*****=+04800	✓	✓
			30Hz	VXX: *****=VXX: *****=+03000		*****=*****=+03000	✓	✓
	SLOT : DisplayPort : EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: *****=VXX: *****=*****: *, *****	QVX: *****=QVX: *****	*****=*****=*****: *, *****	✓	✓
		* PARAMETER1, 2	DisplayPort1	VXX: SLSS1=VXX: EDPS1=*****: *, *****		SLSS1=EDPS1=*****: *, *****	✓	✓
		* PARAMETER3	DisplayPort2	VXX: SLSS1=VXX: EDPS2=*****: *, *****		SLSS1=EDPS2=*****: *, *****	✓	✓
			1024x768	VXX: *****=VXX: *****=1024:0768: *, *****		*****=*****=1024:0768: *, *****	✓	✓
			1280x720	VXX: *****=VXX: *****=1280:0720: *, *****		*****=*****=1280:0720: *, *****	✓	✓
			1280x800	VXX: *****=VXX: *****=1280:0800: *, *****		*****=*****=1280:0800: *, *****	✓	✓
			1400x1050	VXX: *****=VXX: *****=1400:1050: *, *****		*****=*****=1400:1050: *, *****	✓	✓
			1600x900	VXX: *****=VXX: *****=1600:0900: *, *****		*****=*****=1600:0900: *, *****	✓	✓
			1600x1200	VXX: *****=VXX: *****=1600:1200: *, *****		*****=*****=1600:1200: *, *****	✓	✓
			1920x1080	VXX: *****=VXX: *****=1920:1080: *, *****		*****=*****=1920:1080: *, *****	✓	✓
			1920x1200	VXX: *****=VXX: *****=1920:1200: *, *****		*****=*****=1920:1200: *, *****	✓	✓
			3840x2400	VXX: *****=VXX: *****=3840:2400: *, *****		*****=*****=3840:2400: *, *****	✓	✓
		* PARAMETER4	Progressive Interlace	VXX: *****=VXX: *****=*****: p VXX: *****=VXX: *****=*****: i		*****=*****=*****: p *****=*****=*****: i	✓	✓
		* PARAMETERS5	60Hz	VXX: *****=VXX: *****=*****: *, 6000		*****=*****=*****: *, 6000	✓	✓
			50Hz	VXX: *****=VXX: *****=*****: *, 5000		*****=*****=*****: *, 5000	✓	✓
			48Hz	VXX: *****=VXX: *****=*****: *, 4800		*****=*****=*****: *, 4800	✓	✓
			30Hz	VXX: *****=VXX: *****=*****: *, 3000		*****=*****=*****: *, 3000	✓	✓
			25Hz	VXX: *****=VXX: *****=*****: *, 2500		*****=*****=*****: *, 2500	✓	✓
	SLOT : DisplayPort : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX: *****=QVX: *****	*****=*****=*****: *, *****	✓	✓
		* PARAMETER1, 2	DisplayPort1			SLSS1=ESPS1=*****: *, *****	✓	✓
		* PARAMETER3	DisplayPort2			SLSS1=ESPS2=*****: *, *****	✓	✓
			1024x768			*****=*****=1024:0768: *, *****	✓	✓
			1280x720			*****=*****=1280:0720: *, *****	✓	✓
			1280x800			*****=*****=1280:0800: *, *****	✓	✓
			1400x1050			*****=*****=1400:1050: *, *****	✓	✓
			1600x900			*****=*****=1600:0900: *, *****	✓	✓
			1600x1200			*****=*****=1600:1200: *, *****	✓	✓
			1920x1080			*****=*****=1920:1080: *, *****	✓	✓
			1920x1200			*****=*****=1920:1200: *, *****	✓	✓
			3840x2400			*****=*****=3840:2400: *, *****	✓	✓
		* PARAMETER4	Progressive Interlace			*****=*****=*****: p: ***** *****=*****=*****: i: *****	✓	✓

				CONTROL		QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C	
		* PARAMETERS5	60Hz			*****=*****=:*:6000	✓	✓	
			50Hz			*****=*****=:*:5000	✓	✓	
			48Hz			*****=*****=:*:4800	✓	✓	
			30Hz			*****=*****=:*:3000	✓	✓	
			25Hz			*****=*****=:*:2500	✓	✓	
	MULTI PROJECTOR SYNC - MODE	OFF		VXX:MPSI1=+00000	QYX:MPSI1	MPSI1=+00000	✓	✓	
		MASTER		VXX:MPSI1=+00001		MPSI1=+00001	✓	✓	
		SLAVE		VXX:MPSI1=+00002		MPSI1=+00002	✓	✓	
	FRAME SYNC SETTING(MULTI PROJECTOR SYNC) - CONTRAST	OFF		VXX:CSYI1=+00000	QVX:CSYI1	CSYI1=+00000	✓	✓	
		ON		VXX:CSYI1=+00001		CSYI1=+00001	✓	✓	
	MULTI PROJECTOR SYNC - SHUTTER SYNC.	OFF		VXX:SSYI1=+00000	QVX:SSYI1	SSYI1=+00000	✓	✓	
		ON		VXX:SSYI1=+00001		SSYI1=+00001	✓	✓	
	MULTI PROJECTOR SYNC - TERMINAL SELECT	BNC		VXX:TSLI1=+00000	QVX:TSLI1	TSLI1=+00000	✓	✓	
		SERIAL		VXX:TSLI1=+00001		TSLI1=+00001	✓	✓	
	INPUT GUIDE	OFF		OID:0	QDI	0	✓	✓	
		ON (SIMPLE)		OID:1		1	✓	✓	
	OSD POSITION	UPPER LEFT		ODP:1	QDP	1	✓	✓	
		CETRE LEFT		ODP:2		2	✓	✓	
		LOWER LEFT		ODP:3		3	✓	✓	
		TOP CENTER		ODP:4		4	✓	✓	
		CENTER		ODP:5		5	✓	✓	
		LOEER CENTER		ODP:6		6	✓	✓	
		UPPER RIGHT		ODP:7		7	✓	✓	
		CENTER RIGHT		ODP:8		8	✓	✓	
		LOWER RIGHT		ODP:9		9	✓	✓	
	OSD ROTATION	OFF		VXX:OSRI1=+00000	QVX:OSRI1	OSRI1=+00000	✓	✓	
		CLOCKWISE		VXX:OSRI1=+00001		OSRI1=+00001	✓	✓	
		COUNTER CLOCKWISE		VXX:OSRI1=+00002		OSRI1=+00002	✓	✓	
	OSD MEMORY	OFF		VXX:OMYI0=+00000	QVX:OMYI0	OMYI0=+00000	✓	✓	
		ON		VXX:OMYI0=+00001		OMYI0=+00001	✓	✓	
	ON SCREEN	OFF		OOS:0	QOS	0	✓	✓	
		ON		OOS:1		1	✓	✓	
	WARNING MESSAGE	OFF		VXX:WMDI0=+00000	QVX:WMDI0	WMDI0=+00000	✓	✓	
		ON		VXX:WMDI0=+00001		WMDI0=+00001	✓	✓	
	OSD DESIGN	1(YELLOW)		MOD:0	QOD	0	✓	✓	
		2(BLUE)		MOD:1		1	✓	✓	
		3(WHITE)		MOD:2		2	✓	✓	
		4(GREEN)		MOD:3		3	✓	✓	
		5(PEACH)		MOD:4		4	✓	✓	
		6(BROWN)		MOD:5		5	✓	✓	
	MENU MODE	NORMAL		VXX:MMDI1=+00000	QVX:MMDI1	MMDI1=+00000	✓	✓	
		SIMPLE		VXX:MMDI1=+00001		MMDI1=+00001	✓	✓	
	SCREEN SETTING	16:10		VSF:0	QSF	0	✓	✓	
		16:9		VSF:1		1	✓	✓	
		4:3		VSF:2		2	✓	✓	
	SCREEN POSITION-VERTICAL	min.		VXX:VSPI0=-00120	QVX:VSPI0	VSPI0=-00120	-60	-60	
		max.		VXX:VSPI0=+00120		VSPI0=+00120	60	60	
	SCREEN POSITION-HOROZONTAL	min.		VXX:HSPI0=-00320	QVX:HSPI0	HSPI0=-00320	-160	-160	
		max.		VXX:HSPI0=+00320		HSPI0=+00320	+160	+160	
	STARTUP LOGO	OFF		MLO:0	QL0	0	✓	✓	
		USER LOGO		MLO:1		1	✓	✓	
		DEFAULT LOGO		MLO:2		2	✓	✓	
	UNIFORMITY-PC CORRECTION *	OFF		VXX:UFMI1=+00000	QVX:UFMI1	UFMI1=+00000	✓	✓	
		ON(PC)		VXX:UFMI1=+00001		UFMI1=+00001	✓	✓	
	UNIFORMITY- WHITE/RED/GREEN/RED	* PARAMETER		ES\$:*, ****, ****, **	ES\$:*, **	** ****, ****	✓	✓	
		* PARAMETER 1	WHITE	ES\$:W, ****, ****, **	ES\$:W, **	** ****, ****	✓	✓	
			RED	ES\$:R, ****, ****, **	ES\$:R, **	** ****, ****	✓	✓	
			GREEN	ES\$:G, ****, ****, **	ES\$:G, **	** ****, ****	✓	✓	
			BLUE	ES\$:B, ****, ****, **	ES\$:B, **	** ****, ****	✓	✓	
		* PARAMETER 2	VERTICAL(-127)	ES\$:*, -127, ****, **	ES\$:*, **	** -127, ****	✓	✓	
			VERTICAL(+127)	ES\$:*, +127, ****, **	ES\$:*, **	** +127, ****	✓	✓	
		* PARAMETER 3	HORIZONTAL(-127)	ES\$:*, ****, -127, **	ES\$:*, **	** ****, -127	✓	✓	
			HOROZONTAL(+127)	ES\$:*, ****, +127, **	ES\$:*, **	** ****, +127	✓	✓	
		* PARAMETER 4	L1(OFF)	ES\$:*, ****, ****, 0*	ES\$:*, 0*	0*, ****, ****	✓	✓	
			L1(ON)	ES\$:*, ****, ****, 1*	ES\$:*, 1*	1*, ****, ****	✓	✓	
			L2(OFF)	ES\$:*, ****, ****, *0	ES\$:*, *0	*0, ****, ****	✓	✓	
			L2(ON)	ES\$:*, ****, ****, *1	ES\$:*, *1	*1, ****, ****	✓	✓	
	SHUTTER SETTING-FADE IN	0.0s(OFF)		VXX:SEFS1=0.0	QVX:SEFS1	SEFS1=0.0	✓	✓	
		0.5s		VXX:SEFS1=0.5		SEFS1=0.5	✓	✓	
		1.0s		VXX:SEFS1=1.0		SEFS1=1.0	✓	✓	
		1.5s		VXX:SEFS1=1.5		SEFS1=1.5	✓	✓	
		2.0s		VXX:SEFS1=2.0		SEFS1=2.0	✓	✓	
		2.5s		VXX:SEFS1=2.5		SEFS1=2.5	✓	✓	
		3.0s		VXX:SEFS1=3.0		SEFS1=3.0	✓	✓	
		3.5s		VXX:SEFS1=3.5		SEFS1=3.5	✓	✓	
		4.0s		VXX:SEFS1=4.0		SEFS1=4.0	✓	✓	
		5.0s		VXX:SEFS1=5.0		SEFS1=5.0	✓	✓	
		7.0s		VXX:SEFS1=7.0		SEFS1=7.0	✓	✓	
		10.0s		VXX:SEFS1=10.0		SEFS1=10.0	✓	✓	
	SHUTTER SETTING-FADE OUT	0.0s(OFF)		VXX:SEFS2=0.0	QVX:SEFS2	SEFS2=0.0	✓	✓	
		0.5s		VXX:SEFS2=0.5		SEFS2=0.5	✓	✓	
		1.0s		VXX:SEFS2=1.0		SEFS2=1.0	✓	✓	
		1.5s		VXX:SEFS2=1.5		SEFS2=1.5	✓	✓	
		2.0s		VXX:SEFS2=2.0		SEFS2=2.0	✓	✓	
		2.5s		VXX:SEFS2=2.5		SEFS2=2.5	✓	✓	
		3.0s		VXX:SEFS2=3.0		SEFS2=3.0	✓	✓	
		3.5s		VXX:SEFS2=3.5		SEFS2=3.5	✓	✓	
		4.0s		VXX:SEFS2=4.0		SEFS2=4.0	✓	✓	
		5.0s		VXX:SEFS2=5.0		SEFS2=5.0	✓	✓	
		7.0s		VXX:SEFS2=7.0		SEFS2=7.0	✓	✓	
		10.0s		VXX:SEFS2=10.0		SEFS2=10.0	✓	✓	
	SHUTTER SETTING-STARTUP	OPEN		VXX:SEFI3=+00000	QVX:SEFI3	SEFI3=+00000	✓	✓	
		CLOSE		VXX:SEFI3=+00001		SEFI3=+00001	✓	✓	
	BACK COLOR	BLUE		OBC:0	QBC	0	✓	✓	
		BLACK		OBC:1		1	✓	✓	
		USER LOGO		OBC:2		2	✓	✓	
		DEFAULT LOGO		OBC:3		3	✓	✓	
	WAVEFORM MONITOR	OFF		OWM:0	QWM	0	✓	✓	
		LUMINANCE		OWM:5		5	✓	✓	
		RED		OWM:6		6	✓	✓	
		GREEN		OWM:7		7	✓	✓	
		BLUE		OWM:8		8	✓	✓	
	WAVEFORM MONITOR-LINE ADJ.	0		VXX:WMLI0=+00000	QVX:WMLI0	WMLI0=+00000	✓	✓	
		+2159		VXX:WMLI0=+02159		WMLI0=+02159	✓	✓	
	AC VOLTAGE				QVX:VMOI2	VMOI2=+00000 VMOI2=+99999	✓	✓	
	CUT OFF-RED	OFF		VXX:CUTI1=+00000	QVX:CUTI1	CUTI1=+00000	✓	✓	
		ON		VXX:CUTI1=+00001		CUTI1=+00001	✓	✓	
	CUT OFF-GREEN	OFF		VXX:CUTI2=+00000	QVX:CUTI2	CUTI2=+00000	✓	✓	
		ON		VXX:CUTI2=+00001		CUTI2=+00001	✓	✓	
	CUT OFF-BLUE	OFF		VXX:CUTI3=+00000	QVX:CUTI3	CUTI3=+00000	✓	✓	
		ON		VXX:CUTI3=+00001		CUTI3=+00001	✓	✓	
	STATUS			STS			✓	✓	
	PROJECTOR ID	0(ALL)		RIS:00			✓	✓	
		64		RIS:64			✓	✓	
	ID ALL	OFF		RVS:0	QVY	0	✓	✓	
		ON		RVS:1		1	✓	✓	
	PROJECTION METHOD	FRONT/DESK		OIL:0	QSP	0	✓	✓	

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
	INSTALLATION	REAR/DESK		OIL:1		1	✓	✓
		FRONT/CEILING		OIL:2		2	✓	✓
		REAR/CEILING		OIL:3		3	✓	✓
		FRONT/AUTO		OIL:4		4	✓	✓
		REAR/AUTO		OIL:5		5	✓	✓
	PROJECTION METHOD(AUTO)	FRONT/DESK			QVX:PJMI2	PJMI2=+00000	✓	✓
		REAR/DESK				PJMI2=+00001	✓	✓
		FRONT/CEILING				PJMI2=+00002	✓	✓
		REAR/CEILING				PJMI2=+00003	✓	✓
	AUTO COOLING CONDITION- STATUS	FLOOR			QVX:ADRI1	ADRI1=+00000	✓	✓
		CEILING				ADRI1=+00001	✓	✓
		VERTICAL UP				ADRI1=+00002	✓	✓
		VERTICAL DOWN				ADRI1=+00003	✓	✓
		PORTRAIT				ADRI1=+00004	✓	✓
	OPERATING MODE	NORMAL		VXX:OPEI1=+00000	QVX:OPEI1	OPEI1=+00000	✓	✓
		ECO		VXX:OPEI1=+00001		OPEI1=+00001	✓	✓
		QUIET1(QUIET)		VXX:OPEI1=+00021		OPEI1=+00021	✓	✓
		QUIET2		VXX:OPEI1=+00022		OPEI1=+00022	✓	
		USER1(USER)		VXX:OPEI1=+00101		OPEI1=+00101	✓	✓
		USER2		VXX:OPEI1=+00102		OPEI1=+00102	✓	✓
		USER3		VXX:OPEI1=+00103		OPEI1=+00103	✓	✓
	LIGHT OUTPUT	min.		VXX:LOPI2=+00050	QVX:LOPI2	LOPI2=+00050	8%	10%
		max.		VXX:LOPI2=+01000		LOPI2=+01000	100%	100%
	MAX LIGHT OUTPUT	min.		VXX:LOPI3=+00050	QVX:LOPI3	LOPI3=+00050	8%	10%
		max.		VXX:LOPI3=+01000		LOPI3=+01000	100%	100%
	BRIGHTNESS CONTROL-SETUP- CALIBRATION TIME	OFF		VXX:BTMI1=+00000	QVX:BTMI1	BTMI1=+00000	✓	✓
		00:01		VXX:BTMI1=+00001		BTMI1=+00001	✓	✓
		23:59		VXX:BTMI1=+02359		BTMI1=+02359	✓	✓
		00:00		VXX:BTMI1=+02400		BTMI1=+02400	✓	✓
	BRIGHTNESS CONTROL-SETUP- CALIBRATION MESSAGE	OFF		VXX:BMGI1=+00000	QVX:BMGI1	BMGI1=+00000	✓	✓
		ON		VXX:BMGI1=+00001		BMGI1=+00001	✓	✓
	BRIGHTNESS CONTROL-SETUP- CONSTANT MODE	OFF		VXX:BCMI0=+00000	QVX:BCMI0	BCMI0=+00000	✓	✓
		AUTO		VXX:BCMI0=+00001		BCMI0=+00001	✓	✓
		PC		VXX:BCMI0=+00002		BCMI0=+00002	✓	✓
	BRIGHTNESS CONTROL-SETUP- LINK	OFF		VXX:BCLI0=+00000	QVX:BCLI0	BCLI0=+00000	✓	✓
		GROUP A		VXX:BCLI0=+00001		BCLI0=+00001	✓	✓
		GROUP B		VXX:BCLI0=+00002		BCLI0=+00002	✓	✓
		GROUP C		VXX:BCLI0=+00003		BCLI0=+00003	✓	✓
		GROUP D		VXX:BCLI0=+00004		BCLI0=+00004	✓	✓
	BRIGHTNESS CONTROL-SETUP APPLY STANDBY MODE	APPLY		VXX:BCSI0=+00001			✓	✓
		NORMAL		VXX:STMI0=+00000	QVX:STMI0	STMI0=+00000	✓	✓
		ECO		VXX:STMI0=+00003		STMI0=+00003	✓	✓
	QUICK STARTUP	OFF		VXX:QSUI1=+00000	QVX:QSUI1	QSUI1=+00000	✓	✓
		ON		VXX:QSUI1=+00001		QSUI1=+00001	✓	✓
	QUICK STARTUP-VALID PERIOD	30MIN.		VXX:QSUI2=+00030	QVX:QSUI2	QSUI2=+00030	✓	✓
		60MIN.		VXX:QSUI2=+00060		QSUI2=+00060	✓	✓
		90MIN.		VXX:QSUI2=+00090		QSUI2=+00090	✓	✓
	SCHEDULE	OFF		VXX:SCHIO=+00000	QVX:SCHIO	SCHIO=+00000	✓	✓
		ON		VXX:SCHIO=+00001		SCHIO=+00001	✓	✓
	SCHEDLE-PROGRAM ASSIGN	OFF		VXX:SPGI*=+00000	QVX:SPGI*	SPGI*=+00000	✓	✓
		PROGRAM1		VXX:SPGI*=+00001		SPGI*=+00001	✓	✓
		PROGRAM2		VXX:SPGI*=+00002		SPGI*=+00002	✓	✓
		PROGRAM3		VXX:SPGI*=+00003		SPGI*=+00003	✓	✓
		PROGRAM4		VXX:SPGI*=+00004		SPGI*=+00004	✓	✓
		PROGRAM5		VXX:SPGI*=+00005		SPGI*=+00005	✓	✓
		PROGRAM6		VXX:SPGI*=+00006		SPGI*=+00006	✓	✓
		PROGRAM7		VXX:SPGI*=+00007		SPGI*=+00007	✓	✓
		* PARAMETER	SUN	VXX:SPGI0=+0000*	QVX:SPGI0	SPGI0=+0000*	✓	✓
			MON	VXX:SPGI1=+0000*	QVX:SPGI1	SPGI1=+0000*	✓	✓
			TUE	VXX:SPGI2=+0000*	QVX:SPGI2	SPGI2=+0000*	✓	✓
			WED	VXX:SPGI3=+0000*	QVX:SPGI3	SPGI3=+0000*	✓	✓
			THU	VXX:SPGI4=+0000*	QVX:SPGI4	SPGI4=+0000*	✓	✓
			FRI	VXX:SPGI5=+0000*	QVX:SPGI5	SPGI5=+0000*	✓	✓
			SAT	VXX:SPGI6=+0000*	QVX:SPGI6	SPGI6=+0000*	✓	✓
	SCHEDLE-COMMAND SETTING	COMMAND Del		VXX:SCCS*=**00****	QVX:SCCS*=**	SCCS*=**00****	✓	✓
		STANDBY		VXX:SCCS*=**10****		SCCS*=**10****	✓	✓
		POWER ON		VXX:SCCS*=**11****		SCCS*=**11****	✓	✓
		SHUTTER OPEN		VXX:SCCS*=**20****		SCCS*=**20****	✓	✓
		SHUTTER CLOSE		VXX:SCCS*=**21****		SCCS*=**21****	✓	✓
		DVI-D INPUT		VXX:SCCS*=**51****		SCCS*=**51****	✓	✓
		SDI1 INPUT		VXX:SCCS*=**52****		SCCS*=**52****	✓	✓
		HDMI1 INPUT		VXX:SCCS*=**53****		SCCS*=**53****	✓	✓
		SLOT1-1 INPUT		VXX:SCCS*=**68****		SCCS*=**68****	✓	✓
		SLOT1-2 INPUT		VXX:SCCS*=**69****		SCCS*=**69****	✓	✓
		SLOT1-3 INPUT		VXX:SCCS*=**6C****		SCCS*=**6C****	✓	✓
		SLOT1-4 INPUT		VXX:SCCS*=**6D****		SCCS*=**6D****	✓	✓
		NORMAL		VXX:SCCS*=**70****		SCCS*=**70****	✓	✓
		ECO		VXX:SCCS*=**71****		SCCS*=**71****	✓	✓
		USER1(USER)		VXX:SCCS*=**75****		SCCS*=**75****	✓	✓
		USER2		VXX:SCCS*=**76****		SCCS*=**76****	✓	✓
		USER3		VXX:SCCS*=**77****		SCCS*=**77****	✓	✓
		SILENT1(QUIET1/QUIET)		VXX:SCCS*=**7A****		SCCS*=**7A****	✓	✓
		SILENT2(QUIET2)		VXX:SCCS*=**7B****		SCCS*=**7B****	✓	
		DIGITAL LINK		VXX:SCCS*=**B0****		SCCS*=**B0****	✓	✓
		INPUT 1		VXX:SCCS*=**B1****		SCCS*=**B1****	✓	✓
		INPUT 2		VXX:SCCS*=**B2****		SCCS*=**B2****	✓	✓
		INPUT 3		VXX:SCCS*=**B3****		SCCS*=**B3****	✓	✓
		INPUT 4		VXX:SCCS*=**B4****		SCCS*=**B4****	✓	✓
		INPUT 5		VXX:SCCS*=**B5****		SCCS*=**B5****	✓	✓
		INPUT 6		VXX:SCCS*=**B6****		SCCS*=**B6****	✓	✓
		INPUT 7		VXX:SCCS*=**B7****		SCCS*=**B7****	✓	✓
		INPUT 8		VXX:SCCS*=**B8****		SCCS*=**B8****	✓	✓
		INPUT 9		VXX:SCCS*=**B9****		SCCS*=**B9****	✓	✓
		INPUT 10		VXX:SCCS*=**BA****		SCCS*=**BA****	✓	✓
		QUICK STARTUP OFF		VXX:SCCS*=**A2****		SCCS*=**A2****	✓	✓
		QUICK STARTUP ON		VXX:SCCS*=**A3****		SCCS*=**A3****	✓	✓
		* PARAMETER1	PROGRAM1	VXX:SCCS1=*****	QVX:SCCS1=**	SCCS1=*****	✓	✓
			PROGRAM2	VXX:SCCS2=*****	QVX:SCCS2=**	SCCS2=*****	✓	✓
			PROGRAM3	VXX:SCCS3=*****	QVX:SCCS3=**	SCCS3=*****	✓	✓
			PROGRAM4	VXX:SCCS4=*****	QVX:SCCS4=**	SCCS4=*****	✓	✓
			PROGRAM5	VXX:SCCS5=*****	QVX:SCCS5=**	SCCS5=*****	✓	✓
			PROGRAM6	VXX:SCCS6=*****	QVX:SCCS6=**	SCCS6=*****	✓	✓
			PROGRAM7	VXX:SCCS7=*****	QVX:SCCS7=**	SCCS7=*****	✓	✓
		* PARAMETER2	COMMAND 1	VXX:SCCS*=01*****	QVX:SCCS*=01	SCCS*=01*****	✓	✓
			COMMAND 16	VXX:SCCS*=16*****	QVX:SCCS*=16	SCCS*=16*****	✓	✓
		* PARAMETER3	00:00	VXX:SCCS*=****0000		SCCS*=****0000	✓	✓
			23:59	VXX:SCCS*=****2359		SCCS*=****2359	✓	✓
	STARTUP INPUT SELECT	DVI-D		VXX:SISS1=DVI	QVX:SISS1	SISS1=DVI	✓	✓
		HDMI1		VXX:SISS1=HD1		SISS1=HD1	✓	✓
		DIGITAL LINK		VXX:SISS1=DL1		SISS1=DL1	✓	✓
		SDI1		VXX:SISS1=SD1		SISS1=SD1	✓	✓
		SLOT1 : SDI1		VXX:SISS1=AU1, SD1		SISS1=AU1, SD1	✓	✓
		SLOT1 : SDI2		VXX:SISS1=AU1, SD2		SISS1=AU1, SD2	✓	✓
		SLOT1 : SDI3		VXX:SISS1=AU1, SD3		SISS1=AU1, SD3	✓	✓
		SLOT1 : SDI4		VXX:SISS1=AU1, SD4		SISS1=AU1, SD4	✓	✓
		SLOT1 : HDMI1		VXX:SISS1=AU1, HD1		SISS1=AU1, HD1	✓	✓
		SLOT1 : HDMI2		VXX:SISS1=AU1, HD2		SISS1=AU1, HD2	✓	✓
		SLOT1 : DVI1		VXX:SISS1=AU1, DV1		SISS1=AU1, DV1	✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
PROJECTOR SETUP	STARTUP INPUT SELECT (DIGITAL LINK)	SLOT1 : DV12		VXX:SISS1=AU1, DV2		SISS1=AU1, DV2	✓	✓
		SLOT1 : DisplayPort1		VXX:SISS1=AU1, DP1		SISS1=AU1, DP1	✓	✓
		SLOT1 : DisplayPort2		VXX:SISS1=AU1, DP2		SISS1=AU1, DP2	✓	✓
		LAST USED		VXX:SISS1=LSU		SISS1=LSU	✓	✓
		LAST USED		VXX:SISI2=+00000	QVX:SISI2	SISI2=+00000	✓	✓
		INPUT1		VXX:SISI2=+00001		SISI2=+00001	✓	✓
		INPUT2		VXX:SISI2=+00002		SISI2=+00002	✓	✓
		INPUT3		VXX:SISI2=+00003		SISI2=+00003	✓	✓
		INPUT4		VXX:SISI2=+00004		SISI2=+00004	✓	✓
		INPUT5		VXX:SISI2=+00005		SISI2=+00005	✓	✓
		INPUT6		VXX:SISI2=+00006		SISI2=+00006	✓	✓
		INPUT7		VXX:SISI2=+00007		SISI2=+00007	✓	✓
		INPUT8		VXX:SISI2=+00008		SISI2=+00008	✓	✓
		INPUT9		VXX:SISI2=+00009		SISI2=+00009	✓	✓
		INPIT10		VXX:SISI2=+00010		SISI2=+00010	✓	✓
	RS232C-RESPONSE	OFF		RVS:0	QVY	0	✓	✓
		ON		RVS:1		1	✓	✓
	NO SIGNAL SHUT-OFF	DISABLE		OAF:00	QAF	00	✓	✓
		10min		OAF:10		10	✓	✓
		20min		OAF:20		20	✓	✓
		30min		OAF:30		30	✓	✓
		40min		OAF:40		40	✓	✓
		50min		OAF:50		50	✓	✓
		60min		OAF:60		60	✓	✓
		70min		OAF:70		70	✓	✓
		80min		OAF:80		80	✓	✓
		90min		ODR:90		90	✓	✓
	NO SIGNAL LIGHTS-OUT	DISABLE		VXX:SLOI1=+00000	QVX:SLOI1	SLOI1=+00000	✓	✓
		10SEC.		VXX:SLOI1=+00010		SLOI1=+00010	✓	✓
		20SEC.		VXX:SLOI1=+00020		SLOI1=+00020	✓	✓
		30SEC.		VXX:SLOI1=+00030		SLOI1=+00030	✓	✓
		1MIN.		VXX:SLOI1=+00060		SLOI1=+00060	✓	✓
		2MIN.		VXX:SLOI1=+00120		SLOI1=+00120	✓	✓
		3MIN.		VXX:SLOI1=+00180		SLOI1=+00180	✓	✓
		5MIN.		VXX:SLOI1=+00300		SLOI1=+00300	✓	✓
	NO SIGNAL SETTING - SECONDARY INPUT	OFF		VXX:SINS1=OFF	QVX:SINS1	SINS1=OFF	✓	✓
		DVI		VXX:SINS1=DVI		SINS1=DVI	✓	✓
		HDMI1		VXX:SINS1=HDI1		SINS1=HDI1	✓	✓
		SDI1		VXX:SINS1=SD1		SINS1=SD1	✓	✓
		DIGITAL LINK		VXX:SINS1=DL1		SINS1=DL1	✓	✓
		SLOT1 : SDI1		SLOT1 : SDI1		SINS1=AU1, SD1	✓	✓
		SLOT1 : SDI2		SLOT1 : SDI2		SINS1=AU1, SD2	✓	✓
		SLOT1 : SDI3		SLOT1 : SDI3		SINS1=AU1, SD3	✓	✓
		SLOT1 : SDI4		SLOT1 : SDI4		SINS1=AU1, SD4	✓	✓
		SLOT1 : HDMI1		SLOT1 : HDMI1		SINS1=AU1, HD1	✓	✓
		SLOT1 : HDMI2		SLOT1 : HDMI2		SINS1=AU1, HD2	✓	✓
		SLOT1 : DVI-D1		SLOT1 : DVI-D1		SINS1=AU1, DV1	✓	✓
		SLOT1 : DVI-D2		SLOT1 : DVI-D2		SINS1=AU1, DV2	✓	✓
		SLOT1 : DisplayPort1		SLOT1 : DisplayPort1		SINS1=AU1, DP1	✓	✓
		SLOT1 : DisplayPort2		SLOT1 : DisplayPort2		SINS1=AU1, DP2	✓	✓
	REMOTE2 - MODE	DEFAULT		VXX:RMPI0=+00000	QVX:RMPI0	RMPI0=+00000	✓	✓
		USER		VXX:RMPI0=+00001		RMPI0=+00001	✓	✓
	REMOTE2 - PIN2	NONE		VXX:RMPS1=P2<NONE	QVX:RMPS1=P2	RMPS1=P2<NONE	✓	✓
		POWER		VXX:RMPS1=P2<POWER		RMPS1=P2<POWER	✓	✓
	REMOTE2 - PIN3 - 7	* PARAMETER		VXX:RMPS1=P*<*****	QVX:RMPS1=P*		✓	✓
		* PARAMETER1	PIN3	VXX:RMPS1=P3<*****		RMPS1=P3<*****	✓	✓
			PIN4	VXX:RMPS1=P4<*****		RMPS1=P4<*****	✓	✓
			PIN5	VXX:RMPS1=P5<*****		RMPS1=P5<*****	✓	✓
			PIN6	VXX:RMPS1=P6<*****		RMPS1=P6<*****	✓	✓
			PIN7	VXX:RMPS1=P7<*****		RMPS1=P7<*****	✓	✓
		* PARAMETER2	NONE	VXX:RMPS1=P*<NONE		RMPS1=P*<NONE	✓	✓
			HDMI	VXX:RMPS1=P*<HDMI		RMPS1=P*<HDMI	✓	✓
			HDMI1	VXX:RMPS1=P*<HDMI1		RMPS1=P*<HDMI1	✓	✓
			SDI1	VXX:RMPS1=P*<SD1		RMPS1=P*<SD1	✓	✓
			DIGITAL LINK	VXX:RMPS1=P*<DLINK		RMPS1=P*<DLINK	✓	✓
			SLOT1 : SDI1	VXX:RMPS1=P*<AU1, SD1		RMPS1=P*<AU1, SD1	✓	✓
			SLOT1 : SDI2	VXX:RMPS1=P*<AU1, SD2		RMPS1=P*<AU1, SD2	✓	✓
			SLOT1 : SDI3	VXX:RMPS1=P*<AU1, SD3		RMPS1=P*<AU1, SD3	✓	✓
			SLOT1 : SDI4	VXX:RMPS1=P*<AU1, SD4		RMPS1=P*<AU1, SD4	✓	✓
			SLOT1 : HDMI1	VXX:RMPS1=P*<AU1, HD1		RMPS1=P*<AU1, HD1	✓	✓
			SLOT1 : HDMI2	VXX:RMPS1=P*<AU1, HD2		RMPS1=P*<AU1, HD2	✓	✓
			SLOT1 : DVI1	VXX:RMPS1=P*<AU1, DV1		RMPS1=P*<AU1, DV1	✓	✓
			SLOT1 : DVI2	VXX:RMPS1=P*<AU1, DV2		RMPS1=P*<AU1, DV2	✓	✓
			SLOT1 : DisplayPort1	VXX:RMPS1=P*<AU1, DP1		RMPS1=P*<AU1, DP1	✓	✓
			SLOT1 : DisplayPort2	VXX:RMPS1=P*<AU1, DP2		RMPS1=P*<AU1, DP2	✓	✓
	REMOTE2 - PIN8	NONE	NONE	VXX:RMPS1=P8<NONE	QVX:RMPS1=P8	RMPS1=P8<NONE	✓	✓
		SHUTTER	SHUTTER	VXX:RMPS1=P8<SHUTTER		RMPS1=P8<SHUTTER	✓	✓
	FUNCTION BUTTON	DISABLE		OFC:0	QFC	0	✓	✓
		SYSTEM SELECTOR		OFC:1		1	✓	✓
		SYSTEM DAYLIGHT VIEW		OFC:2		2	✓	✓
		SUB MEMORY		OFC:3		3	✓	✓
		FREEZE		OFC:4		4	✓	✓
		WAVEFORM MONITOR		OFC:6		6	✓	✓
		PROJECTION METHOD		OFC:10		10	✓	✓
		GEOMETRY		OFC:13		13	✓	✓
		OSD POSITION		OFC:14		14	✓	✓
	DATE AND TIME-DATE SETTING	Year: yyyy		TSD:201506151	QGD	201506161	✓	✓
		Month: mm		TSD:yyyymmddw		yyyymmddw	✓	✓
		Date: dd					✓	✓
		Day:w(1~7:Mon~Sun)					✓	✓
	DATE AND TIME-TIME SETTING	Hour: hh		TST:154503	QGT	154503	✓	✓
		Minute: mm		TST:hmmss		hmmss	✓	✓
		Second: ss					✓	✓
	DATE AND TIME-NTP SYNCHRONIZATION	OFF		VXX:NTPI0=+00000	QVX:NTPI0	NTPI0=+00000	✓	✓
		ON		VXX:NTPI0=+00001		NTPI0=+00001	✓	✓
	LENS TYPE	NORMAL		VXX:LNSI6=+00000	QVX:LNSI6	LNSI6=+00000	✓	✓
		DLE035		VXX:LNSI6=+00001		LNSI6=+00001	✓	✓
		DLE020		VXX:LNSI6=+00002		LNSI6=+00002	✓	✓
	LENS CALIBRATION	EXECUTE (ALL)		VXX:LNSI0=+00001			✓	✓
	INITIALIZE-ALL USER DATA	USER INITILIZE		VXX:RSTS1=0password			✓	✓
		USER RESTORE		VXX:RSTS1=1password			✓	✓
	INITIAL START UP	STANDBY		OPY:0	QPY	0	✓	✓
		ON		OPY:1		1	✓	✓
		LAST MEMORY		OPY:2		2	✓	✓
	MODEL NAME	MODEL NAME			QID	MODELNAME	✓	✓
	SERIAL NUMBER	SW0101234			QSN	SW0101234	✓	✓
	PROJECTOR RUNTIME	7864320H			QVX:RTMS1	RTMS1=7864320	✓	✓
	LAMP1(LIGHT1) RUNTIME	9999H			Q\$L:1	9999	✓	✓
	LAMP2(LIGHT2) RUNTIME	9999H			Q\$L:2	9999	✓	✓
	LIGHT1 RUNTIME	7864320H			QVX:LRTS3=00	LRTS3=00:7864320	✓	✓
	LIGHT2 RUNTIME	7864320H			QVX:LRTS3=01	LRTS3=01:7864320	✓	✓
	LIGHT STATUS	ALL OFF			QLS	0	✓	✓
		1:ON, 2:OFF				1	✓	✓
		1:OFF, 2:ON				2	✓	✓
		ALL ON				3	✓	✓
	CONTINUOUS LIGHTING TIME	7864320H00M			QVX:CLTS1	CLTS1=7864320:00	✓	✓
	CONSOLIDATED RUNTIME	7864320H			QVX:CRTS1	CRTS1=7864320	✓	✓
	LAMP(LIGHT) CONTROL STATUS	LAMP OFF			Q\$S	0	✓	✓

				CONTROL	QUERY		RCQ10 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS	COMMANDS	CALL BACK	RCQ10 FRQ100C	RCQ80 FRQ080C
	POWER STATUS	In turning ON				1	✓	✓
		LAMP ON				2	✓	✓
		LAMP Cooling				3	✓	✓
		POWER OFF			QVX:POWI1	POWI1=+00001	✓	✓
		In turning ON				POWI1=+00002	✓	✓
		POWER ON				POWI1=+00003	✓	✓
		Cooling				POWI1=+00004	✓	✓
		MAC ADDRESS	AB0102030405		QMA	AB0102030405	✓	✓
	MAIN FIRMWARE VERSION	V1.00.01		QVX:SVRS0	SVRS0=1.00.01	✓	✓	
	SUB FIRMWARE VERSION	V1.00.01		QVX:SVRS2	SVRS2=1.00.01	✓	✓	
	INPUT SIGNAL NAME	CHANNEL1 (MAIN CH)		QVX:NSGS1	NSGS1=*****	✓	✓	
	TEMPERATURE (INTAKE)	0030/0080		QTM:0	0030/0080	✓	✓	
	TEMPERATURE (EXHAUST AIR)	0030/0080		QTM:1	0030/0080	✓	✓	
	TEMPERATURE (OPTICS MODULE)	0030/0080		QTM:2	0030/0080	✓	✓	
TEMPERATURE (LIGHT1 / LIGHT1-	0030/0080		QTM:11	0030/0080	✓	✓		
TEMPERATURE (LIGHT2 / LIGHT1-	0030/0080		QTM:12	0030/0080	✓	✓		
LAN data Cloning Write protect	OFF		LCL:WRP0	QCL:WRP	QCL:WRP0	✓	✓	
	ON		LCL:WRP1		QCL:WRP1	✓	✓	
TEST PATTERN	TEST PATTERN	Off		OTS:00	QTS	00	✓	✓
		White		OTS:01		01	✓	✓
		Black		OTS:02		02	✓	✓
		Window		OTS:05		05	✓	✓
		Reversed Window		OTS:06		06	✓	✓
		Cross Hatch		OTS:07		07	✓	✓
		Color Bar V		OTS:08		08	✓	✓
		Convergence		OTS:11		11	✓	✓
		Color Bar Side		OTS:51		51	✓	✓
		16:9/4:3		OTS:59		59	✓	✓
		Focus Red		OTS:70		70	✓	✓
		Focus Green		OTS:71		71	✓	✓
		Focus Blue		OTS:72		72	✓	✓
		Focus Cyan		OTS:73		73	✓	✓
		Focus Magenta		OTS:74		74	✓	✓
		Focus Yellow		OTS:75		75	✓	✓
		Focus		OTS:78		78	✓	✓
		SIGNAL LIST	SIGNAL LIST-REGISTRATION			OEM		
SIGNAL LIST-DELETE	A1			ODM:A1			✓	✓
	A2			ODM:A2			✓	✓
	A7			ODM:A7			✓	✓
	A8			ODM:A8			✓	✓
	L1			ODM:L1			✓	✓
	L2			ODM:L2			✓	✓
	L7			ODM:L7			✓	✓
	L8			ODM:L8			✓	✓
SUB MEMORY LIST-CHANGEOVER	01			OCS:01			✓	✓
	96			OCS:96			✓	✓
SUB MEMORY LIST-CHANGEOVER (EXTENDED)	01			OCS:01-01			✓	✓
	96			OCS:95-96			✓	✓
SUB MEMORY LIST-REGISTRATION				OES			✓	✓
SUB MEMORY LIST-DELETE	01		ODS:01-01			✓	✓	
	96		ODS:95-96			✓	✓	
SUB MEMORY USAGE STATE	01			QSB	01	✓	✓	
	96				96	✓	✓	
SECURITY	SECURITY SETTING	OFF			QVX:SPWI1	SPWI1=+00000	✓	✓
		ON				SPWI1=+00001	✓	✓
		CONTROL DEVICE SETUP-CONTROL PANEL	DISABLE		VXX:CDSI1=+00000	QVX:CDSI1	CDSI1=+00000	✓
		ENABLE		VXX:CDSI1=+00001		CDSI1=+00001	✓	✓
		USER		VXX:CDSI1=+00002		CDSI1=+00002	✓	✓
		CONTROL DEVICE SETUP-REMOTE CONTROL	DISABLE		VXX:CDSI2=+00000	QVX:CDSI2	CDSI2=+00000	✓
		ENABLE		VXX:CDSI2=+00001		CDSI2=+00001	✓	✓
	USER		VXX:CDSI2=+00002		CDSI2=+00002	✓	✓	
NETWORK	WIRELESS LAN	OFF(DISABLE)		ONS:0	QVX:WLSI1	WLSI1=+00000	✓	✓
		ON(ENABLE)		ONS:14		WLSI1=+00014	✓	✓
	DIGITAL LINK MODE	AUTO		VXX:DKMI1=+00001	QVX:DKMI1	DKMI1=+00001	✓	✓
		DIGITAL LINK		VXX:DKMI1=+00002		DKMI1=+00002	✓	✓
		ETHERNET		VXX:DKMI1=+00003		DKMI1=+00003	✓	✓
		LONG REACH MODE		VXX:DKMI1=+00004		DKMI1=+00004	✓	✓
	DIGITAL LINK STATUS-LINK	NO LINK			QVX:DKSI1	DKSI1=+00000	✓	✓
		DIGITAL LINK				DKSI1=+00001	✓	✓
		LPM				DKSI1=+00002	✓	✓
		ETHERNET				DKSI1=+00003	✓	✓
	DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL			QVX:DKSI2	DKSI2=+00000	✓	✓
		OFF				DKSI2=+00001	✓	✓
		ON				DKSI2=+00002	✓	✓
		DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255			QVX:DKSI3	DKSI3=- 00255	✓
		0				DKSI3=+00000	✓	✓
		DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	-255			QVX:DKSI4	DKSI4=- 00255	✓
		0				DKSI4=+00000	✓	✓
		DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2-...			QVX:DL1S1	DL1S1=HD1:HDMI1,****:***	✓
	PROJECTOR NAME SETTING	PROJECTOR1		VXX:NCGS8=PROJECTOR1	QVX:NCGS8	NCGS8=PROJECTOR1	✓	✓
	Art-Net SETUP	OFF		VXX:DANI1=+00000	QVX:DANI1	DANI1=+00000	✓	✓
		ON(2.*.*)		VXX:DANI1=+00002		DANI1=+00002	✓	✓
		ON(10.*.*)		VXX:DANI1=+00003		DANI1=+00003	✓	✓
		ON(MANUAL)		VXX:DANI1=+00004		DANI1=+00004	✓	✓
	Art-Net SETUP-START ADDRESS	1		VXX:DANI3=+00001	QVX:DANI3	DANI3=+00001	✓	✓
501			VXX:DANI3=+00501		DANI3=+00501	✓	✓	
Art-Net SETUP-NET	0		VXX:DANI4=+00000	QVX:DANI4	DANI4=+00000	✓	✓	
	127		VXX:DANI4=+00127		DANI4=+00127	✓	✓	
Art-Net SETUP-SUB NET	0		VXX:DANI5=+00000	QVX:DANI5	DANI5=+00000	✓	✓	
	15		VXX:DANI5=+00015		DANI5=+00015	✓	✓	
Art-Net SETUP-UNIVERS	0		VXX:DANI6=+00000	QVX:DANI6	DANI6=+00000	✓	✓	
	15		VXX:DANI6=+00015		DANI6=+00015	✓	✓	
Art-Net SETUP-CHANNEL SETTING	DEFAULT		VXX:DANI8=+00000	QVX:DANI8	DANI8=+00000	✓	✓	
	1		VXX:DANI8=+00001		DANI8=+00001	✓	✓	
	2		VXX:DANI8=+00002		DANI8=+00002	✓	✓	
	USER		VXX:DANI8=+00100		DANI8=+00100	✓	✓	

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.