

Control Commands

Model No. **PT-RZ570 series**
PT-RZ575 series
PT-FRZ570C
PT-FRZ575C



PT-RZ570 series
PT-FRZ570C



PT-RZ575 series
PT-FRZ575C

- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
BASIC OPERATION REMOTE CONTROL	POWER	ON		PON	QPW	000	✓	✓
		OFF (STANDBY)		POF		001	✓	✓
	VOLUME	UP		AUU			✓	✓
		DOWN		AUD			✓	✓
	INPUT SELECT	COMPUTER1		IIS:RG1	QIN	RG1	✓	✓
		COMPUTER2		IIS:RG2		RG2	✓	✓
		VIDEO		IIS:VID		VID	✓	✓
		DVI		IIS:DVI		DVI	✓	✓
		HDMI1		IIS:HD1		HD1	✓	✓
		HDMI2		IIS:HD2		HD2	✓	✓
		DIGITAL LINK		IIS:DL1		DL1	✓	✓
	INPUT SELECT (DIGITAL LINK)	COMPUTER1		IIS:DL1:PC1		DL1:PC1	✓	✓
		COMPUTER2		IIS:DL1:PC2		DL1:PC2	✓	✓
		VIDEO		IIS:DL1:VID		DL1:VID	✓	✓
		HDMI1		IIS:DL1:HD1		DL1:HD1	✓	✓
		HDMI2		IIS:DL1:HD2		DL1:HD2	✓	✓
	FREEZE	OFF		OFZ:0	QFZ	0	✓	✓
		ON		OFZ:1		1	✓	✓
	MENU KEY			OMN			✓	✓
	RETURN KEY			OBK			✓	✓
	ENTER KEY			OEN			✓	✓
	UP KEY			OCU			✓	✓
	DOWN KEY			OCD			✓	✓
	LEFT KEY			OCL			✓	✓
	RIGHT KEY			OCR			✓	✓
	DEFAULT KEY			OST			✓	✓
	AUTO SETUP KEY			OAS			✓	✓
	SHUTTER	ON		OSH:0	QSH	0	✓	✓
		OFF		OSH:1		1	✓	✓
	SHUTTER(Toggle)			OSH			✓	✓
	FUNCTION KEY			FC1			✓	✓
	SYSTEM SELECTOR KEY			OSL			✓	✓
	ASPECT KEY			VS1			✓	✓
	ECO			OEC			✓	✓
	NUMERIC KEY	0		ONK:0			✓	✓
		1		ONK:1			✓	✓
		2		ONK:2			✓	✓
		3		ONK:3			✓	✓
		4		ONK:4			✓	✓
		5		ONK:5			✓	✓
		6		ONK:6			✓	✓
		7		ONK:7			✓	✓
		8		ONK:8			✓	✓
		9		ONK:9			✓	✓
	LENS HOME POSITION	EXECUTE		VXX:LNSI1=+00001				✓
	LENS SHIFT-HORIZONTAL	SLOW+		VXX:LNSI2=+00000				✓
		SLOW-		VXX:LNSI2=+00001				✓
		NORMAL+		VXX:LNSI2=+00100				✓
		NORMAL-		VXX:LNSI2=+00101				✓
		FAST+		VXX:LNSI2=+00200				✓
		FAST-		VXX:LNSI2=+00201				✓
	LENS SHIFT-VERTICAL	SLOW+		VXX:LNSI3=+00000				✓
		SLOW-		VXX:LNSI3=+00001				✓
		NORMAL+		VXX:LNSI3=+00100				✓
		NORMAL-		VXX:LNSI3=+00101				✓
		FAST+		VXX:LNSI3=+00200				✓
		FAST-		VXX:LNSI3=+00201				✓
	LENS FOCUS	SLOW+		VXX:LNSI4=+00000				✓
		SLOW-		VXX:LNSI4=+00001				✓
		NORMAL+		VXX:LNSI4=+00100				✓
		NORMAL-		VXX:LNSI4=+00101				✓
		FAST+		VXX:LNSI4=+00200				✓
		FAST-		VXX:LNSI4=+00201				✓
	STATUS KEY			STS			✓	✓
	LENS FOCUS KEY			OLF				✓
	LENS SHIFT KEY			OLH				✓
	DIGITAL LINK KEY			DLK			✓	✓
	INPUT MENU KEY			IPT			✓	✓
	SCREEN ADJUSTMENT			OSA			✓	✓
	AUDIO MUTE	OFF		AMT:0	QMT	0	✓	✓
		ON		AMT:1		1	✓	✓
PICTURE	PICTURE MODE	DYNAMIC		VPM:DYN	QPM	DYN	✓	✓
		NATURAL		VPM:NAT		NAT	✓	✓
		STANDARD		VPM:STD		STD	✓	✓
		CINEMA		VPM:CIN		CIN	✓	✓
		GRAPHIC		VPM:GRA		GRA	✓	✓
		DICOM SIM.		VMP:DIC		DIC	✓	✓
		REC709		VPM:709		709	✓	✓
	CONTRAST	-31		VCN:001	QVR	001	✓	✓
		+31		VCN:063		063	✓	✓
	BRAIGHTNESS	-31		VBR:001	QVB	001	✓	✓
		+31		VBR:063		063	✓	✓
	COLOR	-31		VCO:001	QVC	001	✓	✓
		+31		VCO:063		063	✓	✓
	TINT	-31		VTN:001	QVT	001	✓	✓
		+31		VTN:063		063	✓	✓
	SHARPNESS	0		VSR:000	QVS	000	✓	✓
		15		VSR:015		015	✓	✓
	WHITE GAIN	0		VWH:00	QWH	00	✓	✓
		10		VWH:10		10	✓	✓
	COLOR TEMPERATURE	LOW		OTE:0	QTE	0	✓	✓
		HIGH		OTE:2		2	✓	✓
		USER1(USER)		OTE:04		4	✓	✓
		DEFAULT		OTE:10		10	✓	✓
	COLOR TEMP-NAME SETTING USER1	COLORTEMP1		VXX:NCGS1=COLORTEMP1	QVX:NCGS1	NCGS1=COLORTEMP1	✓	✓
	COLOR TEMP-NAME CLEAR USER1	COLORTEMP1		VXX:NCL11=+00000			✓	✓
	WHITE BALANCE LOW-RED	-127		VOR:001	QOR	001	✓	✓
	WHITE BALANCE LOW-GREEN	-127		VOG:001	QOG	001	✓	✓
		+127		VOG:255		255	✓	✓
	WHITE BALANCE LOW-BLUE	-127		VOB:001	QOB	001	✓	✓
		+127		VOB:255		255	✓	✓
	WHITE BALANCE HIGH-RED	0		VHR:000	QHR	000	✓	✓
		+255		VHR:255		255	✓	✓
	WHITE BALANCE HIGH-GREEN	0		VHG:000	QHG	000	✓	✓
		+255		VHG:255		255	✓	✓
	WHITE BALANCE HIGH-BLUE	0		VHB:000	QHB	000	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
	GAMMA	+255		VHB: 255		255	✓	✓
		1.8		VGA: 1.8		1.8	✓	✓
		2.0		VGA: 2.0		2.0	✓	✓
		2.2		VGA: 2.2		2.2	✓	✓
		DEFAULT		VGA: DEF		DEF	✓	✓
	DAYLIGHT VIEW	OFF		VXX: DLVI0=+00000	QVX: DLVI0	DLVI0=+00000	✓	✓
		AUTO		VXX: DLVI0=+00001		DLVI0=+00001	✓	✓
		1		VXX: DLVI0=+00002		DLVI1=+00002	✓	✓
		2		VXX: DLVI0=+00003		DLVI0=+00003	✓	✓
	NOISE REDUCTION	3		VXX: DLVI0=+00004		DLVI0=+00004	✓	✓
		OFF		VNS: 0	QNS	0	✓	✓
		1		VNS: 1		1	✓	✓
		2		VNS: 2		2	✓	✓
		3		VNS: 3		3	✓	✓
	DYNAMIC CONTRAST/IRIS	OFF		OAI: 0	QAI	0	✓	✓
		1		OAI: 1		1	✓	✓
		AUTO1		VSG: AT1		AT1	✓	✓
		NTSC		VSG: NTS		NTS	✓	✓
		NTSC4.43		VSG: N44		N44	✓	✓
		PAL		VSG: PAL		PAL	✓	✓
		PAL-M		VSG: PAM		PAM	✓	✓
		PAL-N		VSG: PAN		PAN	✓	✓
	SYSTEM SELECTOR RGB(VGA/480P)	PAL60		VSG: P60		P60	✓	✓
		SECAM		VSG: SEC		SEC	✓	✓
		VGA60		ORF: 0	QRF	0	✓	✓
	SYSTEM SELECTOR RGB(Other)/DVI/SLOT-DVI	480P(YCbCr)		ORF: 1		1	✓	✓
		480p(RGB)		ORF: 3		3	✓	✓
		RGB		ORF: 0	QRF	0	✓	✓
	SYSTEM SELECTOR HDMI/DIGITAL LINK/SLOT-HDMI	YPbPr		ORF: 1		1	✓	✓
		RGB		ORF: 0	QRF	0	✓	✓
		YPbPr		ORF: 1		1	✓	✓
		AUTO		ORF: 2		2	✓	✓
POSITION	GEOMETRY	OFF		VXX: GMMI0=+00000	QVX: GMMI0	GMMI0=+00000	✓	✓
		KEYSTONE		VXX: GMMI0=+00001		GMMI0=+00001	✓	✓
		CURVED		VXX: GMMI0=+00002		GMMI0=+00002	✓	✓
		PC-1		VXX: GMMI0=+00003		GMMI0=+00003	✓	✓
		PC-2		VXX: GMMI0=+00004		GMMI0=+00004	✓	✓
		PC-3		VXX: GMMI0=+00005		GMMI0=+00005	✓	✓
		CORNER-CORRECTION		VXX: GMMI0=+00010		GMMI0=+00010	✓	✓
	GEOMETRY-KEystone- LENS THROW RATIO	0.7		VXX: GMKS0=+00.7	QVX: GMKS0	GMKS0=+00.7	✓	✓
		16.5		VXX: GMKS0=+16.5		GMKS0=+16.5	✓	✓
	GEOMETRY-KEystone- VERTICAL BALANCE	-60		VXX: GMKI4=-00060	QVX: GMKI4	GMKI4=-00060	✓	✓
		+60		VXX: GMKI4=+00060		GMKI4=+00060	✓	✓
	GEOMETRY-KEystone- HORIZONTAL BALANCE	-30		VXX: GMKI7=-00030	QVX: GMKI7	GMKI7=-00030	✓	✓
		+30		VXX: GMKI7=+00030		GMKI7=+00030	✓	✓
	GEOMETRY-KEystone- VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX: GMKS8=-40.0	QVX: GMKS8	GMKS8=-40.0	✓	✓
		+40.0 (+45.0)*		VXX: GMKS8=+40.0		GMKS8=+40.0	✓	✓
	GEOMETRY-KEystone- HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX: GMKS9=-15.0	QVX: GMKS9	GMKS9=-15.0	✓	✓
		+15.0 (+40.0)*		VXX: GMKS9=+15.0		GMKS9=+15.0	✓	✓
	GEOMETRY-CURVED-LENS THROW RATIO	0.7		VXX: GMCS0=+00.7	QVX: GMCS0	GMCS0=+00.7	✓	✓
		16.5		VXX: GMCS0=+16.5		GMCS0=+16.5	✓	✓
	GEOMETRY-CURVED- VERTICAL ARC	-50 (-100)*		VXX: GMCI3=-00050	QVX: GMCI3	GMCI3=-00050	✓	✓
		+50 (+100)*		VXX: GMCI3=+00050		GMCI3=+00050	✓	✓
	GEOMETRY-CURVED- HORIZONTAL ARC	-50 (-100)*		VXX: GMCI7=-00050	QVX: GMCI7	GMCI7=-00050	✓	✓
		+50 (+100)*		VXX: GMCI7=+00050		GMCI7=+00050	✓	✓
	GEOMETRY-CURVED- VERTICAL BALANCE	-60		VXX: GMCI2=-00060	QVX: GMCI2	GMCI2=-00060	✓	✓
		+60		VXX: GMCI2=+00060		GMCI2=+00060	✓	✓
	GEOMETRY-CURVED- HORIZONTAL BALANCE	-30		VXX: GMCI6=-00030	QVX: GMCI6	GMCI6=-00030	✓	✓
		+30		VXX: GMCI6=+00030		GMCI6=+00030	✓	✓
	GEOMETRY-CURVED- VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX: GMCS8=-40.0	QVX: GMCS8	GMCS8=-40.0	✓	✓
		+40.0 (+45.0)*		VXX: GMCS8=+40.0		GMCS8=+40.0	✓	✓
	GEOMETRY-CURVED- HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX: GMCS9=-15.0	QVX: GMCS9	GMCS9=-15.0	✓	✓
		+15.0 (+40.0)*		VXX: GMCS9=+15.0		GMCS9=+15.0	✓	✓
	GEOMETRY-CURVED- MAINTAIN ASPECT RATIO	OFF		VXX: GMCIA=+00000	QVX: GMCIA	GMCIA=+00000	✓	✓
		ON		VXX: GMCIA=+00001		GMCIA=+00001	✓	✓
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	min.		VXX: GMFI1=+00000	QVX: GMFI1	GMFI1=+00000	0	0
		max.		VXX: GMFI1=+00300		GMFI1=+00300	+300	+300
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	min.		VXX: GMFI2=+00000	QVX: GMFI2	GMFI2=+00000	0	0
		max.		VXX: GMFI2=+00300		GMFI2=+00300	+300	+300
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	min.		VXX: GMFI3=-00300	QVX: GMFI3	GMFI3=-00300	-300	-300
		max.		VXX: GMFI3=+00000		GMFI3=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	min.		VXX: GMFI4=-00300	QVX: GMFI4	GMFI4=-00300	-300	-300
		max.		VXX: GMFI4=+00000		GMFI4=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(V)	min.		VXX: GMFI5=-00127	QVX: GMFI5	GMFI5=-00127	-127	-127
		max.		VXX: GMFI5=+00127		GMFI5=+00127	+127	+127
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	min.		VXX: GMFI6=+00000	QVX: GMFI6	GMFI6=+00000	0	0
		max.		VXX: GMFI6=+00480		GMFI6=+00480	+480	+480
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	min.		VXX: GMFI7=-00480	QVX: GMFI7	GMFI7=-00480	-480	-480
		max.		VXX: GMFI7=+00000		GMFI7=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	min.		VXX: GMFI8=+00000	QVX: GMFI8	GMFI8=+00000	0	0
		max.		VXX: GMFI8=+00480		GMFI8=+00480	+480	+480
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	min.		VXX: GMFI9=-00480	QVX: GMFI9	GMFI9=-00480	-480	-480
		max.		VXX: GMFI9=+00000		GMFI9=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(H)	min.		VXX: GMFIA=-00127	QVX: GMFIA	GMFIA=-00127	-127	-127
		max.		VXX: GMFIA=+00127		GMFIA=+00127	+127	+127
	SHIFT-HORIZONTAL	0		VTH: 0000	QTH	0000	✓	✓
		+4095		VTH: 4095		4095	✓	✓
	SHIFT-VERTICAL	0		VTV: 0000	QTV	0000	✓	✓
		+4094		VTV: 4094		4094	✓	✓
	CLOCK PHASE	0		VCP: 000	QCP	000	✓	✓
		+31		VCP: 031		063	✓	✓
	ASPECT	AUTO/VID AUTO/DEFAULT		VSE: 0	QSE	0	✓	✓
		NORMAL(4:3)		VSE: 1		1	✓	✓
		WIDE(16:9)		VSE: 2		2	✓	✓
		NATIVE(through)		VSE: 5		5	✓	✓
		FULL(HV FIT)		VSE: 6		6	✓	✓
		H-FIT		VSE: 9		9	✓	✓
		V-FIT		VSE: 10		10	✓	✓
		50		OZH: 050	QZH	050	✓	✓
	ZOOM-HORIZONTAL	999		OZH: 999		999	✓	✓
		50		OZV: 050	QZV	050	✓	✓
	ZOOM-VERTICAL	999		OZV: 999		999	✓	✓
		50		OZO: 050	QZO	050	✓	✓
	ZOOM-BOTH	999		OZO: 999		999	✓	✓
		OFF		OZS: 0	QZS	0	✓	✓
	ZOOM-INTERLOCKED	ON		OZS: 1		1	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
ADVANCED	ZOOM-MODE	INTERNAL FULL		0ZT:0 0ZT:1	QZT	0 1	✓ ✓	✓ ✓
	DIGITAL CINEMA REALITY	AUTO OFF 30p/25p FIXED		OPD:0 OPD:1 OPD:2	QPD	0 1 2	✓ ✓ ✓	✓ ✓ ✓
	BLANKING-UPPER	min. max.		DBU:000 DBU:1199	QLU	000 1199	0 599	0 599
	BLANKING-LOWER	min. max.		DBB:000 DBB:1199	QLB	000 1199	0 599	0 599
	BLANKING-RIGHT	min. max.		DBR:000 DBR:1919	QLR	000 1919	0 959	0 959
	BLANKING-LEFT	min. max.		DBL:000 DBL:1919	QLL	000 1919	0 959	0 959
	INPUT RESOLUTION-TOTAL DOTS	330 4095		VTD:0330 VTD:4095	QTD	0330 4095	✓ ✓	✓ ✓
	INPUT RESOLUTION-DISPLAY DOTS	300 4065		VDD:0300 VDD:4065	QDD	0300 4065	✓ ✓	✓ ✓
	INPUT RESOLUTION-TOTAL LINES	155 2047		VTL:0155 VTL:2047	QTL	0155 2047	✓ ✓	✓ ✓
	INPUT RESOLUTION-DISPLAY LINES	150 2037		VDL:0150 VDL:2037	QDL	0150 2037	✓ ✓	✓ ✓
	CLAMP POSITION	1 255		VLT:001 VLT:255	QLT	001 255	✓ ✓	✓ ✓
	CUSTOM MASKING *	OFF PC-1 PC-2 PC-3		VXX:MSKI1=+00000 VXX:MSKI1=+00001 VXX:MSKI1=+00002 VXX:MSKI1=+00003	QVX:MSKI1	MSKI1=+00000 MSKI1=+00001 MSKI1=+00002 MSKI1=+00003	✓ ✓ ✓ ✓	✓ ✓ ✓ ✓
	EDGE BLENDING	OFF ON USER		VXX:EDBI0=+00000 VXX:EDBI0=+00001 VXX:EDBI0=+00002	QVX:EDBI0	EDBI0=+00000 EDBI0=+00001 EDBI0=+00002	✓ ✓ ✓	✓ ✓ ✓
	EDGE BLENDING-UPPER ON/OFF	OFF ON		VGU:0 VGU:1	QGU	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-LOWER ON/OFF	OFF ON		VGB:0 VGB:1	QGB	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-LEFT ON/OFF	OFF ON		VGL:0 VGL:1	QGL	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-RIGHT ON/OFF	OFF ON		VGR:0 VGR:1	QGR	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-START-UPPER	min. max.		VEU:0000 VEU:2272	QEU	0000 2272	✓ ✓	✓ ✓
	EDGE BLENDING-START-LOWER	min. max.		VEB:0000 VEB:2272	QEB	0000 2272	✓ ✓	✓ ✓
	EDGE BLENDING-START-LEFT	min. max.		VEL:0000 VEL:3712	QEL	0000 3712	✓ ✓	✓ ✓
	EDGE BLENDING-START-RIGHT	min. max.		VER:0000 VER:3712	QER	0000 3712	✓ ✓	✓ ✓
	EDGE BLENDING-WIDTH-UPPER	min. max.		VXX:EUIW0=+00000 VXX:EUIW0=+02272	QVX:EUIW0	EUIW0=+00000 EUIW0=+02272	✓ ✓	✓ ✓
	EDGE BLENDING-WIDTH-LOWER	min. max.		VXX:EBWI0=+00000 VXX:EBWI0=+02272	QVX:EBWI0	EBWI0=+00000 EBWI0=+02272	✓ ✓	✓ ✓
	EDGE BLENDING-WIDTH-LEFT	min. max.		VXX:ELWI0=+00000 VXX:ELWI0=+03712	QVX:ELWI0	ELWI0=+00000 ELWI0=+03712	✓ ✓	✓ ✓
	EDGE BLENDING-WIDTH-RIGHT	min. max.		VXX:ERWI0=+00000 VXX:ERWI0=+03712	QVX:ERWI0	ERWI0=+00000 ERWI0=+03712	✓ ✓	✓ ✓
	EDGE BLENDING-MARKER-ON/OFF	OFF ON		VGM:0 VGM:1	QGM	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJI:000.000.000.000 VJI:255.255.255.255	QJI	000.000.000.000 255.255.255.255	✓ ✓	✓ ✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-	OFF ON		VXX:EBII1=+00000 VXX:EBII1=+00001	QVX:EBII1	EBII1=+00000 EBII1=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJO:000,000,000,000 VJO:255,255,255,255	QJO	000.000.000.000 255.255.255.255	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF ON		VXX:EBII2=+00000 VXX:EBII2=+00001	QVX:EBII2	EBII2=+00000 EBII2=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min. max.		VJU:0000 VJU:2272	QJU	0000 2272	0 1023	0 1023
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min. max.		VJB:0000 VJB:2272	QJB	0000 2272	0 1199	0 1199
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min. max.		VJL:0000 VJL:3712	QJL	0000 3712	0 1023	0 1023
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min. max.		VJR:0000 VJR:3712	QJR	0000 3712	0 1919	0 1919
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER KEYSTONE AREA	min. max.		VXX:EBBI4=-02272 VXX:EBBI4=+02272	QVX:EBBI4	EBBI4=-02272 EBBI4=+02272	-1199 1919	-1199 1919
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER KEYSTONE AREA	min. max.		VXX:EBBI5=-02272 VXX:EBBI5=+02272	QVX:EBBI5	EBBI5=-02272 EBBI5=+02272	-1199 1919	-1199 1919
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT KEYSTONE AREA	min. max.		VXX:EBBI6=-03712 VXX:EBBI6=+03712	QVX:EBBI6	EBBI6=-03712 EBBI6=+03712	-1199 1919	-1199 1919
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT KEYSTONE AREA	min. max.		VXX:EBBI7=-03712 VXX:EBBI7=+03712	QVX:EBBI7	EBBI7=-03712 EBBI7=+03712	-1199 1919	-1199 1919
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS0=000,000,000,000 VXX:EBBS0=255,255,255,255	QVX:EBBS0	EBBS0=000,000,000,000 EBBS0=255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS1=000,000,000,000 VXX:EBBS1=255,255,255,255	QVX:EBBS1	EBBS1=000,000,000,000 EBBS1=255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS2=000,000,000,000 VXX:EBBS2=255,255,255,255	QVX:EBBS2	EBBS2=000,000,000,000 EBBS2=255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS3=000,000,000,000 VXX:EBBS3=255,255,255,255	QVX:EBBS3	EBBS3=000,000,000,000 EBBS3=255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	OFF ON		VXX:EBII3=+00000 VXX:EBII3=+00001	QVX:EBII3	EBII3=+00000 EBII3=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	OFF ON		VXX:EBII4=+00000 VXX:EBII4=+00001	QVX:EBII4	EBII4=+00000 EBII4=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT INTERLOCKED	OFF ON		VXX:EBII5=+00000 VXX:EBII5=+00001	QVX:EBII5	EBII5=+00000 EBII5=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	OFF ON		VXX:EBII6=+00000 VXX:EBII6=+00001	QVX:EBII6	EBII6=+00000 EBII6=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-AUTO TESTPATTERN	OFF ON		VXX:EATI1=+00000 VXX:EATI1=+00001	QVX:EATI1	EATI1=+00000 EATI1=+00001	✓ ✓	✓ ✓
	FRAME RESPONSE	NORMAL FAST		VXX:FDYI0=+00000 VXX:FDYI0=+00001	QVX:FDYI0	FDYI0=+00000 FDYI0=+00001	✓ ✓	✓ ✓
	RASTER POSITION-HORIZONTAL	-2048 +2047		VRH:2952 VRH:7047	QRH	2952 7047	✓ ✓	✓ ✓
	RASTER POSITION-VERTICAL	-2048 +2047		VRV:2952 VRV:7047	QRV	2952 7047	✓ ✓	✓ ✓
	LANGUAGE	English German		OLG:ENG OLG:DEU	QLG	ENG DEU	✓ ✓	✓ ✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
DISPLAY LANGUAGE		French		OLG:FRA		FRA	✓	✓
		Spanish		OLG:ESP		ESP	✓	✓
		Italian		OLG:ITL		ITL	✓	✓
		Japanese		OLG:JPN		JPN	✓	✓
		Chinese		OLG:CHI		CHI	✓	✓
		Russian		OLG:RUS		RUS	✓	✓
		Korea		OLG:KOR		KOR	✓	✓
		Portuguse		OLG:POR		POR	✓	✓
		Swedish		OLG:SVE		SVE	✓	✓
		Norwegian		OLG:NOR		NOR	✓	✓
		Danish		OLG:DAN		DAN	✓	✓
		Polish		OLG:POL		POL	✓	✓
		Czech		OLG:CZS		CZS	✓	✓
		Hungarian		OLG:MAC		MAC	✓	✓
		Thai		OLG:THA		THA	✓	✓
		Dutch		OLG:NLD		NLD	✓	✓
		Finnish		OLG:FIN		FIN	✓	✓
		Romanian		OLG:RUM		RUM	✓	✓
		Turkish		OLG:TUR		TUR	✓	✓
		Arabic		OLG:ARA		ARA	✓	✓
		Kazakh		OLG:KAZ		KAZ	✓	✓
		Vietnamese		OLG:VIE		VIE	✓	✓
	COLOR MATCHING	OFF		VXX:CMAI0=+00000	QVX:CMAI0	CMAI0=+00000	✓	✓
		3COLORS		VXX:CMAI0=+00001		CMAI0=+00001	✓	✓
		7COLORS		VXX:CMAI0=+00002		CMAI0=+00002	✓	✓
		MEASURED		VXX:CMAI0=+00004		CMAI0=+00004	✓	✓
	COLOR MATCHING-3COLOR-RED	0 (R,G,B)		VMR:0000,0000,0000	QMR	0000,0000,0000	✓	✓
		2048,2048,2048(R,G,B)		VMR:2048,2048,2048		2048,2048,2048	✓	✓
	COLOR MATCHING-3COLOR-GREEN	0 (R,G,B)		VMG:0000,0000,0000	QMG	0000,0000,0000	✓	✓
		2048,2048,2048(R,G,B)		VMG:2048,2048,2048		2048,2048,2048	✓	✓
	COLOR MATCHING-3COLOR-BLUE	0 (R,G,B)		VMB:0000,0000,0000	QMB	0000,0000,0000	✓	✓
		2048,2048,2048(R,G,B)		VMB:2048,2048,2048		2048,2048,2048	✓	✓
	COLOR MATCHING-3COLOR-WHITE	256 (GAIN)		VMW:0256	QMW	0256	✓	✓
		2048(GAIN)		VMW:2048		2048	✓	✓
	COLOR MATCHING-3COLOR-AUTO TESTPATTERN	OFF		VXX:CATI0=+00000	QVX:CATI0	CATI0=+00000	✓	✓
		ON		VXX:CATI0=+00001		CATI0=+00001	✓	✓
	COLOR MATCHING-7COLOR-RED	0 (R,G,B)		VXX:C7CS0=0000,0000,0000	QVX:C7CS0	C7CS0=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS0=2048,2048,2048		C7CS0=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLOR-GREEN	0 (R,G,B)		VXX:C7CS1=0000,0000,0000	QVX:C7CS1	C7CS1=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS1=2048,2048,2048		C7CS1=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLOR-BLUE	0 (R,G,B)		VXX:C7CS2=0000,0000,0000	QVX:C7CS2	C7CS2=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS2=2048,2048,2048		C7CS2=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLOR-CYAN	0 (R,G,B)		VXX:C7CS3=0000,0000,0000	QVX:C7CS3	C7CS3=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS3=2048,2048,2048		C7CS3=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLOR-MAGEN	0 (R,G,B)		VXX:C7CS4=0000,0000,0000	QVX:C7CS4	C7CS4=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS4=2048,2048,2048		C7CS4=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLOR-YELLOW	0 (R,G,B)		VXX:C7CS5=0000,0000,0000	QVX:C7CS5	C7CS5=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS5=2048,2048,2048		C7CS5=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLOR-WHITE	0 (R,G,B)		VXX:C7CS5=0000,0000,0000	QVX:C7CS6	C7CS5=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS5=2048,2048,2048		C7CS5=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLOR-AUTO TESTPATTERN	OFF		VXX:CATI1=+00000	QVX:CATI1	CATI1=+00000	✓	✓
		ON		VXX:CATI1=+00001		CATI1=+00001	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y)		VXX:CMMS0=00000,0001,0001	QVX:CMMS0	CMMS0=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMMS0=65535,0999,0999		CMMS0=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y)		VXX:CMMS1=00000,0001,0001	QVX:CMMS1	CMMS1=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMMS1=65535,0999,0999		CMMS1=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y)		VXX:CMMS2=00000,0001,0001	QVX:CMMS2	CMMS2=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMMS2=65535,0999,0999		CMMS2=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y)		VXX:CMMS3=00000,0001,0001	QVX:CMMS3	CMMS3=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMMS3=65535,0999,0999		CMMS3=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y)		VXX:CMMS4=00000,0001,0001	QVX:CMMS4	CMMS4=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMMS4=65535,0999,0999		CMMS4=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y)		VXX:CMTS0=00000,0001,0001	QVX:CMTS0	CMTS0=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMTS0=65535,0999,0999		CMTS0=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y)		VXX:CMTS1=00000,0001,0001	QVX:CMTS1	CMTS1=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMTS1=65535,0999,0999		CMTS1=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y)		VXX:CMTS2=00000,0001,0001	QVX:CMTS2	CMTS2=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMTS2=65535,0999,0999		CMTS2=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y)		VXX:CMTS3=00000,0001,0001	QVX:CMTS3	CMTS3=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMTS3=65535,0999,0999		CMTS3=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y)		VXX:CMTS4=00000,0001,0001	QVX:CMTS4	CMTS4=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMTS4=65535,0999,0999		CMTS4=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y)		VXX:CMTS5=00000,0001,0001	QVX:CMTS5	CMTS5=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMTS5=65535,0999,0999		CMTS5=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y)		VXX:CMTS6=00000,0001,0001	QVX:CMTS6	CMTS6=00000,0001,0001	✓	✓
		65535,999,999(Y,x,y)		VXX:CMTS6=65535,0999,0999		CMTS6=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-AUTO TESTPATTERN	OFF		VXX:CATI3=+00000	QVX:CATI3	CATI3=+00000	✓	✓
		ON		VXX:CATI3=+00001		CATI3=+00001	✓	✓
	COLOR CORRECTION	OFF		VCM:0	QMC	0	✓	✓
		USER		VCM:1		1	✓	✓
	COLOR CORRECTION-RED	-30		VXX:CCRI0=-00030	QVX:CCRI0	CCRI0=-00030	✓	✓
		+30		VXX:CCRI0=+00030		CCRI0=+00030	✓	✓
	COLOR CORRECTION-GREEN	-30		VXX:CCRI1=-00030	QVX:CCRI1	CCRI1=-00030	✓	✓
		+30		VXX:CCRI1=+00030		CCRI1=+00030	✓	✓
	COLOR CORRECTION-BLUE	-30		VXX:CCRI2=-00030	QVX:CCRI2	CCRI2=-00030	✓	✓
		+30		VXX:CCRI2=+00030		CCRI2=+00030	✓	✓
	COLOR CORRECTION-CYAN	-30		VXX:CCRI3=-00030	QVX:CCRI3	CCRI3=-00030	✓	✓
		+30		VXX:CCRI3=+00030		CCRI3=+00030	✓	✓
	COLOR CORRECTION-MAGENTA	-30		VXX:CCRI4=-00030	QVX:CCRI4	CCRI4=-00030	✓	✓
		+30		VXX:CCRI4=+00030		CCRI4=+00030	✓	✓
	COLOR CORRECTION-YELLOW	-30		VXX:CCRI5=-00030	QVX:CCRI5	CCRI5=-00030	✓	✓
		+30		VXX:CCRI5=+00030		CCRI5=+00030	✓	✓
	AUTO SIGNAL	OFF		VXX:AASI0=+00000	QVX:AASI0	AASI0=+00000	✓	✓
		ON		VXX:AASI0=+00001		AASI0=+00001	✓	✓
	AUTO SETUP -MODE	USER		OAM:0	QAM	0	✓	✓
		DEFAULT		OAM:1		1	✓	✓
		WIDE		OAM:2		2	✓	✓
	AUTO SETUP -POSITION ADJ.	OFF		VXX:APAI0=+00000	QVX:APAI0	APAI0=+00000	✓	✓
		ON		VXX:APAI0=+00001		APAI0=+00001	✓	✓
	AUTO SETUP -SIGNAL LEVEL ADJ.	OFF		VXX:ASLI0=+00000	QVX:ASLI0	ASLI0=+00000	✓	✓
		ON		VXX:ASLI0=+00001		ASLI0=+00001	✓	✓
	BACKUP INPUT SETTING-BACKUP INPUT	PRIMARY		VXX:BACI1=+00001	QVX:BACI1	BACI1=+00001	✓	✓
		SECONDARY		VXX:BACI1=+00002		BACI1=+00002	✓	✓
		TOGGLE		VXX:BACI1=+00010		BACI1=+00010	✓	✓
	BACKUP INPUT SETTING-BACKUP INPUT MODE	OFF		VXX:BACI2=+00000	QVX:BACI2	BACI2=+00000	✓	✓
		ON/1		VXX:BACI2=+00001		BACI2=+00001	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
DISPLAY OPTION		2		VXX:BACI2=+00002		BACI2=+00002	✓	✓
	RGB IN-RGB1 INPUT SETTING	RGB/YPBPR Y/C		VXX:RYCI1=+00000 VXX:RYCI1=+00001	QVX:RYCI1	RYCI1=+00000 RYCI1=+00001	✓ ✓	✓ ✓
	RGB IN-RGB1 SYNC SLICE LEVEL	LOW HIGH		VXX:STRI0=+00000 VXX:STRI0=+00001	QVX:STRI0	STRI0=+00000 STRI0=+00001	✓ ✓	✓ ✓
	RGB IN-RGB1 EDID MODE	DEFAULT SCREEB FIT USER		VXX:EDMI7=+00000 VXX:EDMI7=+00001 VXX:EDMI7=+00010	QVX:EDMI7	EDMI7=+00000 EDMI7=+00001 EDMI7=+00010	✓ ✓ ✓	✓ ✓ ✓
	RGB IN-RGB1 EDID RESOLUTION	1024x768p 1280x720p 1280x768p 1280x800p 1280x1024p 1366x768p 1400x1050p 1440x900p 1600x900p 1600x1200p 1680x1050p 1920x1080p 1920x1080i 1920x1200p		VXX:EDRS7=1024:0768:p VXX:EDRS7=1280:0720:p VXX:EDRS7=1280:0768:p VXX:EDRS7=1280:0800:p VXX:EDRS7=1280:1024:p VXX:EDRS7=1366:0768:p VXX:EDRS7=1400:1050:p VXX:EDRS7=1440:0900:p VXX:EDRS7=1600:0900:p VXX:EDRS7=1600:1200:p VXX:EDRS7=1680:1050:p VXX:EDRS7=1920:1080:p VXX:EDRS7=1920:1080:i VXX:EDRS7=1920:1200:p	QVX:EDRS1	EDRS7=1024:0768:p EDRS7=1280:0720:p EDRS7=1280:0768:p EDRS7=1280:0800:p EDRS7=1280:1024:p EDRS7=1366:0768:p EDRS7=1400:1050:p EDRS7=1440:0900:p EDRS7=1600:0900:p EDRS7=1600:1200:p EDRS7=1680:1050:p EDRS7=1920:1080:p EDRS7=1920:1080:i EDRS7=1920:1200:p	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	RGB IN-RGB1 EDID VERTICAL SCAN FREQUENCY	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz		VXX:EDVI7=+00000 VXX:EDVI7=+05000 VXX:EDVI7=+04800 VXX:EDVI7=+03000 VXX:EDVI7=+02500 VXX:EDVI7=+02400	QVX:EDVI7	EDVI7=+00000 EDVI7=+05000 EDVI7=+04800 EDVI7=+03000 EDVI7=+02500 EDVI7=+02400	✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓
	RGB IN-RGB2 SYNC SLICE LEVEL	LOW HIGH		VXX:STRI1=+00000 VXX:STRI1=+00001	QVX:STRI1	STRI1=+00000 STRI1=+00001	✓ ✓	✓ ✓
	RGB IN-RGB2 EDID MODE	DEFAULT SCREEB FIT USER		VXX:EDMI1=+00000 VXX:EDMI1=+00001 VXX:EDMI1=+00010	QVX:EDMI1	EDMI1=+00000 EDMI1=+00001 EDMI1=+00010	✓ ✓ ✓	✓ ✓ ✓
	RGB IN-RGB2 EDID RESOLUTION	1024x768p 1280x720p 1280x768p 1280x800p 1280x1024p 1366x768p 1400x1050p 1440x900p 1600x900p 1600x1200p 1680x1050p 1920x1080p 1920x1080i 1920x1200p		VXX:EDRS1=1024:0768:p VXX:EDRS1=1280:0720:p VXX:EDRS1=1280:0768:p VXX:EDRS1=1280:0800:p VXX:EDRS1=1280:1024:p VXX:EDRS1=1366:0768:p VXX:EDRS1=1400:1050:p VXX:EDRS1=1440:0900:p VXX:EDRS1=1600:0900:p VXX:EDRS1=1600:1200:p VXX:EDRS1=1680:1050:p VXX:EDRS1=1920:1080:p VXX:EDRS1=1920:1080:i VXX:EDRS1=1920:1200:p	QVX:EDRS1	EDRS1=1024:0768:p EDRS1=1280:0720:p EDRS1=1280:0768:p EDRS1=1280:0800:p EDRS1=1280:1024:p EDRS1=1366:0768:p EDRS1=1400:1050:p EDRS1=1440:0900:p EDRS1=1600:0900:p EDRS1=1600:1200:p EDRS1=1680:1050:p EDRS1=1920:1080:p EDRS1=1920:1080:i EDRS1=1920:1200:p	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	RGB IN-RGB2 EDID VERTICAL SCAN FREQUENCY	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz		VXX:EDVI1=+00000 VXX:EDVI1=+05000 VXX:EDVI1=+04800 VXX:EDVI1=+03000 VXX:EDVI1=+02500 VXX:EDVI1=+02400	QVX:EDVI1	EDVI1=+00000 EDVI1=+05000 EDVI1=+04800 EDVI1=+03000 EDVI1=+02500 EDVI1=+02400	✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓
	DVI-D IN-EDID	EDID1 EDID2(PC) EDID3		0ED:1 0ED:2 0ED:3	QED	1 2 3	✓ ✓ ✓	✓ ✓ ✓
	DVI-D IN-SIGNAL LEVEL	0-255 PC 15-235 AUTO		VXX:DVII0=+00000 VXX:DVII0=+00001 VXX:DVII0=+00002	QVX:DVII0	DVII0=+00000 DVII0=+00001 DVII0=+00002	✓ ✓ ✓	✓ ✓ ✓
	DVI-D IN-EDID MODE	DEFAULT SCREEN FIT USER		VXX:EDMI2=+00000 VXX:EDMI2=+00001 VXX:EDMI2=+00010	QVX:EDMI0	EDMI2=+00000 EDMI2=+00001 EDMI2=+00010	✓ ✓ ✓	✓ ✓ ✓
	DVI-D IN-EDID RESOLUTION	1024x768p 1280x720p 1280x768p 1280x800p 1280x1024p 1366x768p 1400x1050p 1440x900p 1600x900p 1600x1200p 1680x1050p 1920x1080p 1920x1080i 1920x1200p		VXX:EDRS2=1024:0768:p VXX:EDRS2=1280:0720:p VXX:EDRS2=1280:0768:p VXX:EDRS2=1280:0800:p VXX:EDRS2=1280:1024:p VXX:EDRS2=1366:0768:p VXX:EDRS2=1400:1050:p VXX:EDRS2=1440:0900:p VXX:EDRS2=1600:0900:p VXX:EDRS2=1600:1200:p VXX:EDRS2=1680:1050:p VXX:EDRS2=1920:1080:p VXX:EDRS2=1920:1080:i VXX:EDRS2=1920:1200:p	QVX:EDRS2	EDRS2=1024:0768:p EDRS2=1280:0720:p EDRS2=1280:0768:p EDRS2=1280:0800:p EDRS2=1280:1024:p EDRS2=1366:0768:p EDRS2=1400:1050:p EDRS2=1440:0900:p EDRS2=1600:0900:p EDRS2=1600:1200:p EDRS2=1680:1050:p EDRS2=1920:1080:p EDRS2=1920:1080:i EDRS2=1920:1200:p	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	DVI-D IN-EDID VERTICAL SCAN FREQUENCY	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz		VXX:EDVI2=+00000 VXX:EDVI2=+05000 VXX:EDVI2=+04800 VXX:EDVI2=+03000 VXX:EDVI2=+02500 VXX:EDVI2=+02400	QVX:EDVI2	EDVI2=+00000 EDVI2=+05000 EDVI2=+04800 EDVI2=+03000 EDVI2=+02500 EDVI2=+02400	✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓
	HDMI IN-EDID MODE	DEFAULT SCREEN FIT USER		VXX:EDMI3=+00000 VXX:EDMI3=+00001 VXX:EDMI3=+00010	QVX:EDMI3	EDMI3=+00000 EDMI3=+00001 EDMI3=+00010	✓ ✓ ✓	✓ ✓ ✓
	HDMI IN-EDID RESOLUTION	1024x768p 1280x720p 1280x768p 1280x800p 1280x1024p 1366x768p 1400x1050p 1440x900p 1600x900p 1600x1200p 1680x1050p 1920x1080p 1920x1080i 1920x1200p		VXX:EDRS3=1024:0768:p VXX:EDRS3=1280:0720:p VXX:EDRS3=1280:0768:p VXX:EDRS3=1280:0800:p VXX:EDRS3=1280:1024:p VXX:EDRS3=1366:0768:p VXX:EDRS3=1400:1050:p VXX:EDRS3=1440:0900:p VXX:EDRS3=1600:0900:p VXX:EDRS3=1600:1200:p VXX:EDRS3=1680:1050:p VXX:EDRS3=1920:1080:p VXX:EDRS3=1920:1080:i VXX:EDRS3=1920:1200:p	QVX:EDRS3	EDRS3=1024:0768:p EDRS3=1280:0720:p EDRS3=1280:0768:p EDRS3=1280:0800:p EDRS3=1280:1024:p EDRS3=1366:0768:p EDRS3=1400:1050:p EDRS3=1440:0900:p EDRS3=1600:0900:p EDRS3=1600:1200:p EDRS3=1680:1050:p EDRS3=1920:1080:p EDRS3=1920:1080:i EDRS3=1920:1200:p	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	HDMI IN-EDID VERTICAL SCAN FREQUENCY	60Hz 50Hz 48Hz 30Hz 25Hz 24Hz		VXX:EDVI3=+00000 VXX:EDVI3=+05000 VXX:EDVI3=+04800 VXX:EDVI3=+03000 VXX:EDVI3=+02500 VXX:EDVI3=+02400	QVX:EDVI3	EDVI3=+00000 EDVI3=+05000 EDVI3=+04800 EDVI3=+03000 EDVI3=+02500 EDVI3=+02400	✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓
	HDMI IN-HDMI1 SIGNAL LEVEL	0-1023		VXX:HSLI1=+00000	QVX:HSLI0	HSLI1=+00000	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
	HDMI IN-HDMI2 SIGNAL LEVEL	64-940		VXX:HSLI1=+00001		HSLI1=+00001	✓	✓
		AUTO		VXX:HSLI1=+00002		HSLI1=+00002	✓	✓
		0-1023		VXX:HSLI2=+00000	QVX:HSLI0	HSLI2=+00000	✓	✓
		64-940		VXX:HSLI2=+00001		HSLI2=+00001	✓	✓
	HDMI IN-HDMI2 EDID MODE	AUTO		VXX:HSLI2=+00002		HSLI2=+00002	✓	✓
		DEFAULT		VXX:EDMI6=+00000	QVX:EDMI3	EDMI6=+00000	✓	✓
		SCREEN FIT		VXX:EDMI6=+00001		EDMI6=+00001	✓	✓
		USER		VXX:EDMI6=+00010		EDMI6=+00010	✓	✓
	HDMI IN-HDMI2 EDID RESOLUTION	1024x768p		VXX:EDRS6=1024:0768:p	QVX:EDRS3	EDRS6=1024:0768:p	✓	✓
		1280x720p		VXX:EDRS6=1280:0720:p		EDRS6=1280:0720:p	✓	✓
		1280x768p		VXX:EDRS6=1280:0768:p		EDRS6=1280:0768:p	✓	✓
		1280x800p		VXX:EDRS6=1280:0800:p		EDRS6=1280:0800:p	✓	✓
		1280x1024p		VXX:EDRS6=1280:1024:p		EDRS6=1280:1024:p	✓	✓
		1366x768p		VXX:EDRS6=1366:0768:p		EDRS6=1366:0768:p	✓	✓
		1400x1050p		VXX:EDRS6=1400:1050:p		EDRS6=1400:1050:p	✓	✓
		1440x900p		VXX:EDRS6=1440:0900:p		EDRS6=1440:0900:p	✓	✓
		1600x900p		VXX:EDRS6=1600:0900:p		EDRS6=1600:0900:p	✓	✓
		1600x1200p		VXX:EDRS6=1600:1200:p		EDRS6=1600:1200:p	✓	✓
		1680x1050p		VXX:EDRS6=1680:1050:p		EDRS6=1680:1050:p	✓	✓
		1920x1080p		VXX:EDRS6=1920:1080:p		EDRS6=1920:1080:p	✓	✓
		1920x1080i		VXX:EDRS6=1920:1080:i		EDRS6=1920:1080:i	✓	✓
		1920x1200p		VXX:EDRS6=1920:1200:p		EDRS6=1920:1200:p	✓	✓
	HDMI IN-HDMI2 EDID VERTICAL SCAN FREQUENCY	60Hz		VXX:EDVI6=+00000	QVX:EDVI3	EDVI6=+00000	✓	✓
		50Hz		VXX:EDVI6=+05000		EDVI6=+05000	✓	✓
		48Hz		VXX:EDVI6=+04800		EDVI6=+04800	✓	✓
		30Hz		VXX:EDVI6=+03000		EDVI6=+03000	✓	✓
		25Hz		VXX:EDVI6=+02500		EDVI6=+02500	✓	✓
		24Hz		VXX:EDVI6=+02400		EDVI6=+02400	✓	✓
	DIGITAL LINK-SIGNAL LEVEL	AUTO		VXX:DKLI1=+00000	QVX:DKLI1	DKLI1=+00000	✓	✓
		0-1023		VXX:DKLI1=+00001		DKLI1=+00001	✓	✓
		64-940		VXX:DKLI1=+00002		DKLI1=+00002	✓	✓
	DIGITAL LINK-EDID MODE	DEFAULT		VXX:EDMI4=+00000	QVX:EDMI4	EDMI4=+00000	✓	✓
		SCREEN FIT		VXX:EDMI4=+00001		EDMI4=+00001	✓	✓
		USER		VXX:EDMI4=+00010		EDMI4=+00010	✓	✓
	DIGITAL LINK-EDID RESOLUTION	1024x768p		VXX:EDRS4=1024:0768:p	QVX:EDRS4	EDRS4=1024:0768:p	✓	✓
		1280x720p		VXX:EDRS4=1280:0720:p		EDRS4=1280:0720:p	✓	✓
		1280x768p		VXX:EDRS4=1280:0768:p		EDRS4=1280:0768:p	✓	✓
		1280x800p		VXX:EDRS4=1280:0800:p		EDRS4=1280:0800:p	✓	✓
		1280x1024p		VXX:EDRS4=1280:1024:p		EDRS4=1280:1024:p	✓	✓
		1366x768p		VXX:EDRS4=1366:0768:p		EDRS4=1366:0768:p	✓	✓
		1400x1050p		VXX:EDRS4=1400:1050:p		EDRS4=1400:1050:p	✓	✓
		1440x900p		VXX:EDRS4=1440:0900:p		EDRS4=1440:0900:p	✓	✓
		1600x900p		VXX:EDRS4=1600:0900:p		EDRS4=1600:0900:p	✓	✓
		1600x1200p		VXX:EDRS4=1600:1200:p		EDRS4=1600:1200:p	✓	✓
		1680x1050p		VXX:EDRS4=1680:1050:p		EDRS4=1680:1050:p	✓	✓
		1920x1080p		VXX:EDRS4=1920:1080:p		EDRS4=1920:1080:p	✓	✓
		1920x1080i		VXX:EDRS4=1920:1080:i		EDRS4=1920:1080:i	✓	✓
		1920x1200p		VXX:EDRS4=1920:1200:p		EDRS4=1920:1200:p	✓	✓
	DIGITAL LINK-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX:EDVI4=+00000	QVX:EDVI4	EDVI4=+00000	✓	✓
		50Hz		VXX:EDVI4=+05000		EDVI4=+05000	✓	✓
		48Hz		VXX:EDVI4=+04800		EDVI4=+04800	✓	✓
		30Hz		VXX:EDVI4=+03000		EDVI4=+03000	✓	✓
		25Hz		VXX:EDVI4=+02500		EDVI4=+02500	✓	✓
		24Hz		VXX:EDVI4=+02400		EDVI4=+02400	✓	✓
	INPUT GUIDE	OFF		OID:0	QDI	0	✓	✓
		ON (SIMPLE)		OID:1		1	✓	✓
	OSD POSITION	UPPER LEFT		ODP:1	QDP	1	✓	✓
		CETRE LEFT		ODP:2		2	✓	✓
		LOWER LEFT		ODP:3		3	✓	✓
		TOP CENTER		ODP:4		4	✓	✓
		CENTER		ODP:5		5	✓	✓
		LOEER CENTER		ODP:6		6	✓	✓
		UPPER RIGHT		ODP:7		7	✓	✓
		CENTER RIGHT		ODP:8		8	✓	✓
		LOWER RIGHT		ODP:9		9	✓	✓
	OSD ROTATION	OFF		VXX:OSRI1=+00000	QVX:OSRI1	OSRI1=+00000	✓	✓
		CLOCKWISE		VXX:OSRI1=+00001		OSRI1=+00001	✓	✓
		COUNTER CLOCKWISE		VXX:OSRI1=+00002		OSRI1=+00002	✓	✓
	OSD MEMORY	OFF		VXX:OMYI0=+00000	QVX:OMYI0	OMYI0=+00000	✓	✓
		ON		VXX:OMYI0=+00001		OMYI0=+00001	✓	✓
	ON SCREEN	OFF		OOS:0	QOS	0	✓	✓
		ON		OOS:1		1	✓	✓
	WARNING MESSAGE	OFF		VXX:WMDI0=+00000	QVX:WMDI0	WMDI0=+00000	✓	✓
		ON		VXX:WMDI0=+00001		WMDI0=+00001	✓	✓
	OSD DESIGN	1(YELLOW)		MOD:0	QOD	0	✓	✓
		2(BLUE)		MOD:1		1	✓	✓
		3(WHITE)		MOD:2		2	✓	✓
		4(GREEN)		MOD:3		3	✓	✓
		5(Peach)		MOD:4		4	✓	✓
		6(BROWN)		MOD:5		5	✓	✓
	CLOSED CAPTION SETTING	OFF		OCC:0	QCC	0	✓	✓
		CC1		OCC:1		1	✓	✓
		CC2		OCC:2		2	✓	✓
		CC3		OCC:3		3	✓	✓
		CC4		OCC:4		4	✓	✓
	IMAGE ROTATION	OFF		VXX:IROI1=+00000	QVX:IROI1	IROI1=+00000	✓	✓
		CLOCKWISE		VXX:IROI1=+00001		IROI1=+00001	✓	✓
		COUNTER CLOCKWISE		VXX:IROI1=+00002		IROI1=+00002	✓	✓
	SCREEN SETTING	16:10		VSF:0	QSF	0	✓	✓
		16:9		VSF:1		1	✓	✓
		4:3		VSF:2		2	✓	✓
	SCREEN POSITION-VERTICAL	min.		VXX:VSPI0=-00120	QVX:VSPI0	VSPI0=-00120	-60	-60
		max.		VXX:VSPI0=+00120		VSPI0=+00120	60	60
	SCREEN POSITION-HORZONTAL	min.		VXX:HSPi0=-00320	QVX:HSPi0	HSPi0=-00320	-160	-160
		max.		VXX:HSPi0=+00320		HSPi0=+00320	+160	+160
	STARTUP LOGO	OFF		MLO:0	QLO	0	✓	✓
		USER LOGO		MLO:1		1	✓	✓
		DEFAULT LOGO		MLO:2		2	✓	✓
	UNIFORMITY-PC CORRECTION *	OFF		VXX:UFMI1=+00000	QVX:UFMI1	UFMI1=+00000	✓	✓
		ON		VXX:UFMI1=+00001		UFMI1=+00001	✓	✓
	UNIFORMITY-WHITE/RED/GREEN/RED	* PARAMETER		ESW:*,**,**,**,**,**	ESR:*,**	**,**,**,**,**,**	✓	✓
			WHITE	ESW:W,****,**,**,**	ESR:W,**	**,**,**,**,**,**	✓	✓
			RED	ESW:R,****,**,**,**	ESR:R,**	**,**,**,**,**,**	✓	✓
		* PARAMETER 1	GREEN	ESW:G,****,**,**,**	ESR:G,**	**,**,**,**,**,**	✓	✓
			BLUE	ESW:B,****,**,**,**	ESR:B,**	**,**,**,**,**,**	✓	✓
		* PARAMETER 2	VERTICAL(-127)	ESW:*, -127,****,**	ESR:*,**	**,-127,****	✓	✓

				CONTROL		QUERY		RZ570/RZ575 SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS		COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
	PARAMETER 2	* PARAMETER 3	VERTICAL(+127)	ESW:*,+127,****,**		ESR:*,**	**,+127,****	✓	✓
			HORIZONTAL(-127)	ESW:*,****,-127,**		ESR:*,**	**,****,-127	✓	✓
			HORIZONTAL(+127)	ESW:*,****,+127,**		ESR:*,**	**,****,+127	✓	✓
		* PARAMETER 4	L1(OFF)	ESW:*,****,****,0*		ESR:*,0*	0*,****,****	✓	✓
	L1(ON)		ESW:*,****,****,1*		ESR:*,1*	1*,****,****	✓	✓	
	L2(OFF)		ESW:*,****,****,*0		ESR:*,*0	*0,****,****	✓	✓	
	SHUTTER SETTING-FADE IN	0.0s(OFF) 0.5s 1.0s 1.5s 2.0s 2.5s 3.0s 3.5s 4.0s 5.0s 7.0s 10.0s	L2(ON)	VXX:SEFS1=0.0		QVX:SEFS1	SEFS1=0.0	✓	✓
				VXX:SEFS1=0.5			SEFS1=0.5	✓	✓
				VXX:SEFS1=1.0			SEFS1=1.0	✓	✓
				VXX:SEFS1=1.5			SEFS1=1.5	✓	✓
				VXX:SEFS1=2.0			SEFS1=2.0	✓	✓
				VXX:SEFS1=2.5			SEFS1=2.5	✓	✓
				VXX:SEFS1=3.0			SEFS1=3.0	✓	✓
				VXX:SEFS1=3.5			SEFS1=3.5	✓	✓
				VXX:SEFS1=4.0			SEFS1=4.0	✓	✓
				VXX:SEFS1=5.0			SEFS1=5.0	✓	✓
	VXX:SEFS1=7.0			SEFS1=7.0	✓	✓			
	VXX:SEFS1=10.0			SEFS1=10.0	✓	✓			
	SHUTTER SETTING-FADE OUT	0.0s(OFF) 0.5s 1.0s 1.5s 2.0s 2.5s 3.0s 3.5s 4.0s 5.0s 7.0s 10.0s		VXX:SEFS2=0.0		QVX:SEFS2	SEFS2=0.0	✓	✓
				VXX:SEFS2=0.5			SEFS2=0.5	✓	✓
				VXX:SEFS2=1.0			SEFS2=1.0	✓	✓
				VXX:SEFS2=1.5			SEFS2=1.5	✓	✓
				VXX:SEFS2=2.0			SEFS2=2.0	✓	✓
				VXX:SEFS2=2.5			SEFS2=2.5	✓	✓
				VXX:SEFS2=3.0			SEFS2=3.0	✓	✓
				VXX:SEFS2=3.5			SEFS2=3.5	✓	✓
				VXX:SEFS2=4.0			SEFS2=4.0	✓	✓
				VXX:SEFS2=5.0			SEFS2=5.0	✓	✓
	VXX:SEFS2=7.0			SEFS2=7.0	✓	✓			
	VXX:SEFS2=10.0			SEFS2=10.0	✓	✓			
	SHUTTER SETTING-STARTUP	OPEN		VXX:SEFI3=+00000		QVX:SEFI3	SEFI3=+00000	✓	✓
		CLOSE		VXX:SEFI3=+00001			SEFI3=+00001	✓	✓
	BACK COLOR	BLUE		OBC:0		QBC	0	✓	✓
		BLACK		OBC:1			1	✓	✓
		USER LOGO		OBC:2			2	✓	✓
		DEFAULT LOGO		OBC:3			3	✓	✓
	WAVEFORM MONITOR	OFF		OWM:0		QWM	0	✓	✓
		LUMINANCE		OWM:5			5	✓	✓
		RED		OWM:6			6	✓	✓
		GREEN		OWM:7			7	✓	✓
BLUE			OWM:8			8	✓	✓	
WAVEFORM MONITOR-LINE ADJ.	0		VXX:WMLI0=+00000		QVX:WMLI0	WMLI0=+00000	✓	✓	
	+2159		VXX:WMLI0=+02159			WMLI0=+02159	✓	✓	
CUT OFF-RED	OFF		VXX:CUTI1=+00000		QVX:CUTI1	CUTI1=+00000	✓	✓	
	ON		VXX:CUTI1=+00001			CUTI1=+00001	✓	✓	
CUT OFF-GREEN	OFF		VXX:CUTI2=+00000		QVX:CUTI2	CUTI2=+00000	✓	✓	
	ON		VXX:CUTI2=+00001			CUTI2=+00001	✓	✓	
CUT OFF-BLUE	OFF		VXX:CUTI3=+00000		QVX:CUTI3	CUTI3=+00000	✓	✓	
	ON		VXX:CUTI3=+00001			CUTI3=+00001	✓	✓	
COMPUTER1 INPUT/OUTPUT	RGB/YBPBR		VXX:RYCI1=+00000		QVX:RYCI1	RYCI1=+00000	✓	✓	
	Y/C		VXX:RYCI1=+00001			RYCI1=+00001	✓	✓	
	COMPUTER2 IN/OUTPUT SELECT	COMPUTER2 IN		ORI:2IN	QRI	2IN	✓	✓	
		COMPUTER2 OUT		ORI:20U		20U	✓	✓	
	PROJECTOR ID	0(ALL)		RIS:00			✓	✓	
		64		RIS:64			✓	✓	
	PROJECTION METHOD INSTALLATION	FRONT/DESK		OIL:0		QSP	0	✓	✓
		REAR/DESK		OIL:1			1	✓	✓
		FRONT/CEILING		OIL:2			2	✓	✓
		REAR/CEILING		OIL:3			3	✓	✓
		FRONT/AUTO		OIL:4			4	✓	✓
		REAR/AUTO		OIL:5			5	✓	✓
	PROJECTION METHOD(AUTO)	FRONT/DESK				QVX:PJMI2	PJMI2=+00000	✓	✓
		REAR/DESK					PJMI2=+00001	✓	✓
		FRONT/CEILING					PJMI2=+00002	✓	✓
		REAR/CEILING					PJMI2=+00003	✓	✓
	AUTO COOLING CONDITION-STATUS	FLOOR				QVX:ADRI1	ADRI1=+00000	✓	✓
		CEILING					ADRI1=+00001	✓	✓
		VERTICAL UP					ADRI1=+00002	✓	✓
		VERTICAL DOWN					ADRI1=+00003	✓	✓
HIGH ALTITUDE MODE	Under 2700m(OFF)		OFM:0			0	✓	✓	
	Over 2700m(ON)		OFM:1			1	✓	✓	
OPERATING MODE	NORMAL		VXX:OPEI1=+00000		QVX:OPEI1	OPEI1=+00000	✓	✓	
	ECO		VXX:OPEI1=+00001			OPEI1=+00001	✓	✓	
	SILENT		VXX:OPEI1=+00002			OPEI1=+00002	✓	✓	
	LONG LIFE1		VXX:OPEI1=+00011			OPEI1=+00011	✓	✓	
	LONG LIFE2		VXX:OPEI1=+00012			OPEI1=+00012	✓	✓	
	LONG LIFE3		VXX:OPEI1=+00013			OPEI1=+00013	✓	✓	
	USER1(USER)		VXX:OPEI1=+00101			OPEI1=+00101	✓	✓	
	USER2		VXX:OPEI1=+00102			OPEI1=+00102	✓	✓	
	USER3		VXX:OPEI1=+00103			OPEI1=+00103	✓	✓	
	LIGHT OUTPUT	min.		VXX:LOPI2=+00100		QVX:LOPI2	LOPI2=+00100	✓	✓
	max.		VXX:LOPI2=+01000			LOPI2=+01000	✓	✓	
MAX LIGHT OUTPUT	min.		VXX:LOPI3=+00100		QVX:LOPI3	LOPI3=+00100	✓	✓	
	max.		VXX:LOPI3=+01000			LOPI3=+01000	✓	✓	
ECO MANAGEMENT-AUTO POWER SAVE	OFF		VXX:ECOIO=+00000		QVX:ECOIO	ECOIO=+00000	✓	✓	
	ON		VXX:ECOIO=+00001			ECOIO=+00001	✓	✓	
ECO MANAGEMENT-AMBIENT LIGHT DETECTION	OFF		VXX:ECOII=+00000		QVX:ECOII	ECOII=+00000	✓	✓	
	ON		VXX:ECOII=+00001			ECOII=+00001	✓	✓	
BRIGHTNESS CONTROL-SETUP-CALIBRATION TIME	OFF		VXX:BTMI1=+00000		QVX:BTMI1	BTMI1=+00000	✓	✓	
	00:01		VXX:BTMI1=+00001			BTMI1=+00001	✓	✓	
	23:59		VXX:BTMI1=+02359			BTMI1=+02359	✓	✓	
	00:00		VXX:BTMI1=+02400			BTMI1=+02400	✓	✓	
BRIGHTNESS CONTROL-SETUP-CALIBRATION MESSAGE	OFF		VXX:BMGI1=+00000		QVX:BMGI1	BMGI1=+00000	✓	✓	
	ON		VXX:BMGI1=+00001			BMGI1=+00001	✓	✓	
BRIGHTNESS CONTROL-GAIN	20%		VXX:TGAIO=+00020		QVX:TGAIO	TGAIO=+00020	✓	✓	
	100%		VXX:TGAIO=+00100			TGAIO=+00100	✓	✓	
BRIGHTNESS CONTROL-SETUP-CONSTANT MDOE	OFF		VXX:BCMI0=+00000		QVX:BCMI0	BCMI0=+00000	✓	✓	
	AUTO		VXX:BCMI0=+00001			BCMI0=+00001	✓	✓	
	PC		VXX:BCMI0=+00002			BCMI0=+00002	✓	✓	
	OFF		VXX:BCLIO=+00000		QVX:BCLIO	BCLIO=+00000	✓	✓	
BRIGHTNESS CONTROL-SETUP-LINK	GROUP A		VXX:BCLIO=+00001			BCLIO=+00001	✓	✓	
	GROUP B		VXX:BCLIO=+00002			BCLIO=+00002	✓	✓	
	GROUP C		VXX:BCLIO=+00003			BCLIO=+00003	✓	✓	
	GROUP D		VXX:BCLIO=+00004			BCLIO=+00004	✓	✓	
	BRIGHTNESS CONTROL-SETUP APPLY	APPLY		VXX:BCSIO=+00001				✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
PROJECTOR SETUP	STANDBY MODE	NORMAL		VXX:STMI0=+00000	QVX:STMI0	STMI0=+00000	✓	✓
	ECO			VXX:STMI0=+00003		STMI0=+00003	✓	✓
	QUICK STARTUP	OFF		VXX:QSUI1=+00000	QVX:QSUI1	QSUI1=+00000	✓	✓
	ON			VXX:QSUI1=+00001		QSUI1=+00001	✓	✓
	QUICK STARTUP-VALID PERIOD	30MIN.		VXX:QSUI2=+00030	QVX:QSUI2	QSUI2=+00030	✓	✓
	60MIN.			VXX:QSUI2=+00060		QSUI2=+00060	✓	✓
	90MIN.			VXX:QSUI2=+00090		QSUI2=+00090	✓	✓
	SCHEDULE	OFF		VXX:SCHIO=+00000	QVX:SCHIO	SCHIO=+00000	✓	✓
	ON			VXX:SCHIO=+00001		SCHIO=+00001	✓	✓
	SCHEDULE-PROGRAM ASSIGN	OFF		VXX:SPGI*=+00000	QVX:SPGI*	SPGI*=+00000	✓	✓
	PROGRAM1			VXX:SPGI*=+00001		SPGI*=+00001	✓	✓
	PROGRAM2			VXX:SPGI*=+00002		SPGI*=+00002	✓	✓
	PROGRAM3			VXX:SPGI*=+00003		SPGI*=+00003	✓	✓
	PROGRAM4			VXX:SPGI*=+00004		SPGI*=+00004	✓	✓
	PROGRAM5			VXX:SPGI*=+00005		SPGI*=+00005	✓	✓
	PROGRAM6			VXX:SPGI*=+00006		SPGI*=+00006	✓	✓
	PROGRAM7			VXX:SPGI*=+00007		SPGI*=+00007	✓	✓
	* PARAMETER	SUN		VXX:SPGI0=+0000*	QVX:SPGI0	SPGI0=+0000*	✓	✓
		MON		VXX:SPGI1=+0000*	QVX:SPGI1	SPGI1=+0000*	✓	✓
		TUE		VXX:SPGI2=+0000*	QVX:SPGI2	SPGI2=+0000*	✓	✓
		WED		VXX:SPGI3=+0000*	QVX:SPGI3	SPGI3=+0000*	✓	✓
		THU		VXX:SPGI4=+0000*	QVX:SPGI4	SPGI4=+0000*	✓	✓
		FRI		VXX:SPGI5=+0000*	QVX:SPGI5	SPGI5=+0000*	✓	✓
		SAT		VXX:SPGI6=+0000*	QVX:SPGI6	SPGI6=+0000*	✓	✓
	SCHEDULE-COMMAND SETTING	COMMAND Del		VXX:SCCS*=**00****	QVX:SCCS*=**	SCCS*=**00****	✓	✓
	STANDBY			VXX:SCCS*=**10****		SCCS*=**10****	✓	✓
	POWER ON			VXX:SCCS*=**11****		SCCS*=**11****	✓	✓
	SHUTTER OPEN			VXX:SCCS*=**20****		SCCS*=**20****	✓	✓
	SHUTTER CLOSE			VXX:SCCS*=**21****		SCCS*=**21****	✓	✓
	RGB1 INPUT			VXX:SCCS*=**31****		SCCS*=**31****	✓	✓
	RGB2 INPUT			VXX:SCCS*=**32****		SCCS*=**32****	✓	✓
	VIDEO INPUT			VXX:SCCS*=**41****		SCCS*=**41****	✓	✓
	DVI-D INPUT			VXX:SCCS*=**51****		SCCS*=**51****	✓	✓
	HDMI1 INPUT			VXX:SCCS*=**53****		SCCS*=**53****	✓	✓
	HDMI2 INPUT			VXX:SCCS*=**54****		SCCS*=**54****	✓	✓
	NORMAL			VXX:SCCS*=**70****		SCCS*=**70****	✓	✓
	ECO			VXX:SCCS*=**71****		SCCS*=**71****	✓	✓
	LONG LIFE1			VXX:SCCS*=**72****		SCCS*=**72****	✓	✓
	LONG LIFE2			VXX:SCCS*=**73****		SCCS*=**73****	✓	✓
	LONG LIFE3			VXX:SCCS*=**74****		SCCS*=**74****	✓	✓
	USER1(USER)			VXX:SCCS*=**75****		SCCS*=**75****	✓	✓
	USER2			VXX:SCCS*=**76****		SCCS*=**76****	✓	✓
	USER3			VXX:SCCS*=**77****		SCCS*=**77****	✓	✓
	SILENT			VXX:SCCS*=**78****		SCCS*=**78****	✓	✓
	DIGITAL LINK			VXX:SCCS*=**B0****		SCCS*=**B0****	✓	✓
	INPUT 1			VXX:SCCS*=**B1****		SCCS*=**B1****	✓	✓
	INPUT 2			VXX:SCCS*=**B2****		SCCS*=**B2****	✓	✓
	INPUT 3			VXX:SCCS*=**B3****		SCCS*=**B3****	✓	✓
	INPUT 4			VXX:SCCS*=**B4****		SCCS*=**B4****	✓	✓
	INPUT 5			VXX:SCCS*=**B5****		SCCS*=**B5****	✓	✓
	INPUT 6			VXX:SCCS*=**B6****		SCCS*=**B6****	✓	✓
	INPUT 7			VXX:SCCS*=**B7****		SCCS*=**B7****	✓	✓
	INPUT 8			VXX:SCCS*=**B8****		SCCS*=**B8****	✓	✓
	INPUT 9			VXX:SCCS*=**B9****		SCCS*=**B9****	✓	✓
	INPUT 10			VXX:SCCS*=**BA****		SCCS*=**BA****	✓	✓
	AUDIO IN STANDBY OFF			VXX:SCCS*=**A0****		SCCS*=**A0****	✓	✓
	AUDIO IN STANDBY ON			VXX:SCCS*=**A1****		SCCS*=**A1****	✓	✓
	QUICK STARTUP OFF			VXX:SCCS*=**A2****		SCCS*=**A2****	✓	✓
	QUICK STARTUP ON			VXX:SCCS*=**A3****		SCCS*=**A3****	✓	✓
	AUDIO VOLUME	0		VXX:SCCS*=**C0****		SCCS*=**C0****	✓	✓
		63		VXX:SCCS*=**FF****		SCCS*=**FF****	✓	✓
	* PARAMETER1	PROGRAM1		VXX:SCCS1=*****	QVX:SCCS1=**	SCCS1=*****	✓	✓
		PROGRAM2		VXX:SCCS2=*****	QVX:SCCS2=**	SCCS2=*****	✓	✓
		PROGRAM3		VXX:SCCS3=*****	QVX:SCCS3=**	SCCS3=*****	✓	✓
		PROGRAM4		VXX:SCCS4=*****	QVX:SCCS4=**	SCCS4=*****	✓	✓
		PROGRAM5		VXX:SCCS5=*****	QVX:SCCS5=**	SCCS5=*****	✓	✓
		PROGRAM6		VXX:SCCS6=*****	QVX:SCCS6=**	SCCS6=*****	✓	✓
		PROGRAM7		VXX:SCCS7=*****	QVX:SCCS7=**	SCCS7=*****	✓	✓
	* PARAMETER2	COMMAND 1		VXX:SCCS*=01*****	QVX:SCCS*=01	SCCS*=01*****	✓	✓
		COMMAND 16		VXX:SCCS*=16*****	QVX:SCCS*=16	SCCS*=16*****	✓	✓
	* PARAMETER3	00:00		VXX:SCCS*=****0000		SCCS*=****0000	✓	✓
		23:59		VXX:SCCS*=****2359		SCCS*=****2359	✓	✓
	STARTUP INPUT SELECT	RGB1		VXX:SISS1=RG1	QVX:SISS1	SISS1=RG1	✓	✓
	RGB2			VXX:SISS1=RG2		SISS1=RG2	✓	✓
	DVI-D			VXX:SISS1=DVI		SISS1=DVI	✓	✓
	HDMI1			VXX:SISS1=HD1		SISS1=HD1	✓	✓
	HDMI2			VXX:SISS1=HD2		SISS1=HD2	✓	✓
	DIGITAL LINK			VXX:SISS1=DL1		SISS1=DL1	✓	✓
	SDI1			VXX:SISS1=SD1		SISS1=SD1	✓	✓
	LAST USED			VXX:SISS1=LSU		SISS1=LSU	✓	✓
	STARTUP INPUT SELECT (DIGITAL LINK)	LAST USED		VXX:SISS2=+00000	QVX:SISS2	SISS2=+00000	✓	✓
	INPUT1			VXX:SISS2=+00001		SISS2=+00001	✓	✓
	INPUT2			VXX:SISS2=+00002		SISS2=+00002	✓	✓
	INPUT3			VXX:SISS2=+00003		SISS2=+00003	✓	✓
	INPUT4			VXX:SISS2=+00004		SISS2=+00004	✓	✓
	INPUT5			VXX:SISS2=+00005		SISS2=+00005	✓	✓
	INPUT6			VXX:SISS2=+00006		SISS2=+00006	✓	✓
	INPUT7			VXX:SISS2=+00007		SISS2=+00007	✓	✓
	INPUT8			VXX:SISS2=+00008		SISS2=+00008	✓	✓
	INPUT9			VXX:SISS2=+00009		SISS2=+00009	✓	✓
	INPT10			VXX:SISS2=+00010		SISS2=+00010	✓	✓
	NO SIGNAL SHUT-OFF	DISABLE		QAF:00	QAF	00	✓	✓
	10min			QAF:10		10	✓	✓
	20min			QAF:20		20	✓	✓
	30min			QAF:30		30	✓	✓
	40min			QAF:40		40	✓	✓
	50min			QAF:50		50	✓	✓
	60min			QAF:60		60	✓	✓
	70min			QAF:70		70	✓	✓
	80min			QAF:80		80	✓	✓
	90min			QAF:90		90	✓	✓
	NO SIGNAL LIGHTS-OUT	DISABLE		VXX:SLOI1=+00000	QVX:SLOI1	SLOI1=+00000	✓	✓
	10SEC.			VXX:SLOI1=+00010		SLOI1=+00010	✓	✓
	20SEC.			VXX:SLOI1=+00020		SLOI1=+00020	✓	✓
	30SEC.			VXX:SLOI1=+00030		SLOI1=+00030	✓	✓
	1MIN.			VXX:SLOI1=+00060		SLOI1=+00060	✓	✓
	2MIN.			VXX:SLOI1=+00120		SLOI1=+00120	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK		RZ570 FRZ570C	RZ575 FRZ575C
	FUNCTION BUTTON	3MIN.		VXX: SLOI1=+00180		SLOI1=+00180		✓	✓
		5MIN.		VXX: SLOI1=+00300		SLOI1=+00300		✓	✓
		DISABLE		OFC: 0	QFC	0		✓	✓
		SYSTEM SELECTOR		OFC: 1		1		✓	✓
	DATE AND TIME-DATE SETTING	SYSTEM DAYLIGHT VIEW		OFC: 2		2		✓	✓
		SUB MEMORY		OFC: 3		3		✓	✓
		WAVEFORM MONITOR		OFC: 6		6		✓	✓
		Year: yyyy		TSD: 201506151	QGD	201506161		✓	✓
	DATE AND TIME-TIME SETTING	Month: mm		TSD: yyyymmddw		yyyymmddw		✓	✓
		Date: dd						✓	✓
		Day:w(1~7;Mon~Sun)						✓	✓
		Hour: hh		TST: 154503	QGT	154503		✓	✓
	DATE AND TIME-NTP SYNCHRONIZATION	Minute: mm		TST: hhmss		hhmss		✓	✓
		Second: ss						✓	✓
		OFF		VXX: NTPi0=+00000	QVX: NTPi0	NTPi0=+00000		✓	✓
		ON		VXX: NTPi0=+00001		NTPi0=+00001		✓	✓
	LENS CALIBRATION	EXECUTE		VXX: LNSi0=+00001				✓	✓
	INITIALIZE-ALL USER DATA	USER INITILIZE		VXX: RSTs1=0password				✓	✓
		USER RESTORE		VXX: RSTs1=1password				✓	✓
	INITIAL START UP	STANDBY		OPY: 0	QPY	0		✓	✓
		ON		OPY: 1		1		✓	✓
		LAST MEMORY		OPY: 2		2		✓	✓
	AUDIO SETTING-VOLUME	0		AVL: 000	QAV	000		✓	✓
		63		AVL: 063		063		✓	✓
	AUDIO SETTING-BALANCE	-16		ABL: -16	QBL	-16		✓	✓
		16		ABL: 016		16		✓	✓
	AUDIO SETTING-IN STANDBY MODE	OFF		VXX: ASBi0=+00000	QVX: ASBi0	ASBi0=+00000		✓	✓
		ON		VXX: ASBi0=+00001		ASBi0=+00001		✓	✓
	AUDIO SETTING-IN SHUTTER MODE	OFF		VXX: ASHi0=+00000	QVX: ASHi0	ASHi0=+00000		✓	✓
		ON		VXX: ASHi0=+00001		ASHi0=+00001		✓	✓
	AUDIO SETTING-AUDIO IN SELECT-COMPUTER1	AUDIO IN 1		VXX: AINi0=+00000	QVX: AINi0	AINi0=+00000		✓	✓
		AUDIO IN 2		VXX: AINi0=+00001		AINi0=+00001		✓	✓
		AUDIO IN 3		VXX: AINi0=+00002		AINi0=+00002		✓	✓
	AUDIO SETTING-AUDIO IN SELECT-COMPUTER2	AUDIO IN 1		VXX: AINI1=+00000	QVX: AINI1	AINI1=+00000		✓	✓
		AUDIO IN 2		VXX: AINI1=+00001		AINI1=+00001		✓	✓
		AUDIO IN 3		VXX: AINI1=+00002		AINI1=+00002		✓	✓
	AUDIO SETTING-AUDIO IN SELECT-HDMI1	HDMI1 AUDIO IN		VXX: AINI3=+00003	QVX: AINI3	AINI3=+00003		✓	✓
		AUDIO IN 1		VXX: AINI3=+00000		AINI3=+00000		✓	✓
		AUDIO IN 2		VXX: AINI3=+00001		AINI3=+00001		✓	✓
		AUDIO IN 3		VXX: AINI3=+00002		AINI3=+00002		✓	✓
	AUDIO SETTING-AUDIO IN SELECT-VIDEO	AUDIO IN 1		VXX: AINI4=+00000	QVX: AINI4	AINI4=+00000		✓	✓
		AUDIO IN 2		VXX: AINI4=+00001		AINI4=+00001		✓	✓
		AUDIO IN 3		VXX: AINI4=+00002		AINI4=+00002		✓	✓
	AUDIO SETTING-AUDIO IN SELECT-HDMI2	HDMI2 AUDIO IN		VXX: AINI7=+00003	QVX: AINI7	AINI7=+00003		✓	✓
		AUDIO IN 1		VXX: AINI7=+00000		AINI7=+00000		✓	✓
		AUDIO IN 2		VXX: AINI7=+00001		AINI7=+00001		✓	✓
		AUDIO IN 3		VXX: AINI7=+00002		AINI7=+00002		✓	✓
	AUDIO SETTING-AUDIO IN SELECT-DIGITAL LINK	DIGITAL LINK AUDIO IN		VXX: AINI8=+00005	QVX: AINI8	AINI8=+00005		✓	✓
		AUDIO IN 1		VXX: AINI8=+00000		AINI8=+00000		✓	✓
		AUDIO IN 2		VXX: AINI8=+00001		AINI8=+00001		✓	✓
		AUDIO IN 3		VXX: AINI8=+00002		AINI8=+00002		✓	✓
	MODEL NAME	MODEL NAME			QID	MODEL NAME		✓	✓
	SERIAL NUMBER	SW0101234			QSN	Sw0101234		✓	✓
	PROJECTOR RUNTIME	7864320H			QVX: RTMS1	RTMS1=7864320		✓	✓
	LAMP1(LIGHT1) RUNTIME	9999H			QSL: 1	9999		✓	✓
	LIGHT1 RUNTIME	7864320H			QVX: LRTS3=00	LRTS3=00: 7864320		✓	✓
	LIGHT STATUS	ALL OFF			QLS	0		✓	✓
		1:ON, 2:OFF				1		✓	✓
	MAC ADDRESS	AB0102030405			QMA	AB0102030405		✓	✓
	MAIN FIRMWARE VERSION	V1.00.01			QVX: SVRS0	SVRS0=1.00.01		✓	✓
	SUB FIRMWARE VERSION	V1.00.01			QVX: SVRS2	SVRS2=1.00.01		✓	✓
P IN P	P IN P-MODE	OFF		OPP: 0	OPP	0		✓	✓
		USER1		OPP: 1		1		✓	✓
		USER2		OPP: 2		2		✓	✓
		USER3		OPP: 3		3		✓	✓
	P IN P-MAIN WINDOW	RGB1		MSI: RG1	QIM	RG1		✓	✓
		RGB2		MSI: RG2		RG2		✓	✓
		VIDEO		MSI: VID		VID		✓	✓
		DVI		MSI: DVI		DVI		✓	✓
		HDMI1		MSI: HD1		HD1		✓	✓
		HDMI2		MSI: HD2		HD2		✓	✓
		DIGITAL LINK		MSI: DL1		DL1		✓	✓
	P IN P-MAIN WIDNOW-SIZE-INTERLOCKED	OFF		MSL: 0				✓	✓
		ON		MSL: 1				✓	✓
	P IN P-MAIN WIDNOW-SIZE-VERTICAL	10		MSV: 010				✓	✓
		100		MSV: 100				✓	✓
	P IN P-MAIN WIDNOW-SIZE-HORIZONTAL	10		MSH: 010				✓	✓
		100		MSH: 100				✓	✓
	P IN P-MAIN WIDNOW-SIZE-BOTH	10		MSZ: 010				✓	✓
		100		MSZ: 100				✓	✓
	P IN P-MAIN WIDNOW-POSITION-VERTICAL	min.		MPV: -600				-600	-600
		max.		MPV: +600				+600	+600
	P IN P-MAIN WIDNOW-POSITION-HORIZONTAL	min.		MPH: -960				-960	-960
		max.		MPH: +960				+960	+960
	P IN P-MAIN WINDOW-SIZE	INTERLOCKED	OFF		QSM	OF.V010.H010.HV100		✓	✓
			ON			ON.V010.H010.HV100		✓	✓
		VERTICAL SIZE	10-100			**.V010.H***.HV***		✓	✓
		HORIZONTAL SIZE	10-100			***.V***.H010.HV***		✓	✓
	P IN P-MAIN WINDOW-POSITION	H/V SIZE	10-100			***.V***.H***.HV100		✓	✓
		V: -364 +364			QPA	V-364.H-651		✓	✓
	P IN P-SUB WINDOW	H: -651 +651				V+364.H+651		✓	✓
		RGB1		SIS: RG1	QIS	RG1		✓	✓
		RGB2		SIS: RG2		RG2		✓	✓
		VIDEO		SIS: VID		VID		✓	✓
		DVI		SIS: DVI		DVI		✓	✓
		HDMI1		SIS: HD1		HD1		✓	✓
		HDMI2		SIS: HD2		HD2		✓	✓
	P IN P-SUB WINDOW-SIZE	DIGITAL LINK		SIS: DL1		DL1		✓	✓
		INTERLOCKED	OFF		QSS	OF.V010.H010.HV100		✓	✓
			ON			ON.V010.H010.HV100		✓	✓
		VERTICAL SIZE	10-100			**.V010.H***.HV***		✓	✓
		HORIZONTAL SIZE	10-100			***.V***.H010.HV***		✓	✓
	P IN P-SUB WINDOW-POSITION	H/V SIZE	10-100			***.V***.H***.HV100		✓	✓
		V: -364 +364			QPS	V-364.H-651		✓	✓
	P IN P-SUB WIDNOW-SIZE-	H: -651 +651				V+364.H+651		✓	✓
		OFF		SSL: 0		0		✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ570/RZ575 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ570 FRZ570C	RZ575 FRZ575C
	INTERLOCKED	ON		SSL:1		1	✓	✓
	P IN P-SUB WIDNOW-SIZE-VERTICAL	10		SSV:010		010	✓	✓
		100		SSV:100		100	✓	✓
	P IN P-SUB WIDNOW-SIZE-HORIZONTAL	10		SSH:010		010	✓	✓
		100		SSH:100		100	✓	✓
	P IN P-SUB WIDNOW-SIZE-BOTH	10		SSZ:010		010	✓	✓
		100		SSZ:100		100	✓	✓
	P IN P-SUB WIDNOW-POSITION-VERTICAL	-600		SPV:-600		-600	-600	-600
		+600		SPV:+600		+600	+600	+600
	P IN P-SUB WIDNOW-POSITION-HORIZONTAL	-960		SPH:-960		-960	-960	-960
		+960		SPH:+960		+960	+960	+960
	P IN P-SUB WINDOW-CLOCK PHASE	0		VXX:SCPI0=+00000	QVX:SCPI0	SCPI0=+00000	✓	✓
		31		VXX:SCPI0=+00031		SCPI0=+00031	✓	✓
	P IN P-FRAME LOCK	MAIN WINDOW		PFL:0	QPF	0	✓	✓
		SUB WINDOW		PFL:1		1	✓	✓
	P IN P-TYPE	MAIN WINDOW		PTP:0	QPT	0	✓	✓
		SUB WINDOW		PTP:1		1	✓	✓
TEST PATTERN	TEST PATTERN	Off		OTS:00		00	✓	✓
		White		OTS:01		01	✓	✓
		Black		OTS:02		02	✓	✓
		Window		OTS:05		05	✓	✓
		Reversed Window		OTS:06		06	✓	✓
		Color Bar V		OTS:08		08	✓	✓
		Convergence		OTS:11		11	✓	✓
		Color Bar Side		OTS:51		51	✓	✓
		16:9/4:3		OTS:59		59	✓	✓
		Focus Red		OTS:70		70	✓	✓
		Focus Green		OTS:71		71	✓	✓
		Focus Blue		OTS:72		72	✓	✓
		Focus Cyan		OTS:73		73	✓	✓
		Focus Magenta		OTS:74		74	✓	✓
		Focus Yellow		OTS:75		75	✓	✓
SIGNAL LIST	SIGNAL LIST-REGISTRATION			OEM			✓	✓
	SIGNAL LIST-DELETE	A1		ODM:A1			✓	✓
		A2		ODM:A2			✓	✓
		A7		ODM:A7			✓	✓
		A8		ODM:A8			✓	✓
		L1		ODM:L1			✓	✓
		L2		ODM:L2			✓	✓
		L7		ODM:L7			✓	✓
		L8		ODM:L8			✓	✓
	SUB MEMORY LIST-CHANGEVER	01		OCS:01			✓	✓
		96		OCS:96			✓	✓
	SUB MEMORY LIST-CHANGEVER (EXTENDED)	01		OCS:01-01			✓	✓
SECURITY	SUB MEMORY LIST-REGISTRATION	96		OCS:95-96			✓	✓
	SUB MEMORY LIST-DELETE	01		ODS:01-01			✓	✓
		96		ODS:95-96			✓	✓
	SUB MEMORY USAGE STATE	01			QSB	01	✓	✓
NETWORK	SECURITY SETTING	OFF			QVX:SPWI1	SPWI1=+00000	✓	✓
		ON				SPWI1=+00001	✓	✓
	DIGITAL LINK MODE	AUTO		VXX:DKMI1=+00001	QVX:DKMI1	DKMI1=+00001	✓	✓
		DIGITAL LINK		VXX:DKMI1=+00002		DKMI1=+00002	✓	✓
		ETHERNET		VXX:DKMI1=+00003		DKMI1=+00003	✓	✓
		LONG REACH MODE		VXX:DKMI1=+00004		DKMI1=+00004	✓	✓
	DIGITAL LINK-DUPLEX(Ethernet)	Auto negotiation		VXX:DKDI1=+00000	QVX:DKDI1	DKDI1=+00000	✓	✓
		100BaseTX-Full		VXX:DKDI1=+00001		DKDI1=+00001	✓	✓
		100BaseTX-Half		VXX:DKDI1=+00002		DKDI1=+00002	✓	✓
	DIGITAL LINK-DUPLEX(DIGITAL LINK)	Auto negotiation		VXX:DKDI2=+00000	QVX:DKDI2	DKDI2=+00000	✓	✓
		100BaseTX-Full		VXX:DKDI2=+00001		DKDI2=+00001	✓	✓
		100BaseTX-Half		VXX:DKDI2=+00002		DKDI2=+00002	✓	✓
	DIGITAL LINK STATUS-LINK	NO LINK			QVX:DKSI1	DKSI1=+00000	✓	✓
		DIGITAL LINK				DKSI1=+00001	✓	✓
		LPM				DKSI1=+00002	✓	✓
		ETHERNET				DKSI1=+00003	✓	✓
	DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL			QVX:DKSI2	DKSI2=+00000	✓	✓
		OFF				DKSI2=+00001	✓	✓
		ON				DKSI2=+00002	✓	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255			QVX:DKSI3	DKSI3=-00255	✓	✓
		0				DKSI3=+00000	✓	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	-255			QVX:DKSI4	DKSI4=-00255	✓	✓
		0				DKSI4=+00000	✓	✓
	DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2-...			QVX:DL1S1	DL1S1=HD1:HDMI1,****:*	✓	✓
	PROJECTOR NAME SETTING	PROJECTOR1		VXX:NCGS8=PROJECTOR1	QVX:NCGS8	NCGS8=PROJECTOR1	✓	✓
	Art-Net SETUP	OFF		VXX:DANI1=+00000	QVX:DANI1	DANI1=+00000	✓	✓
		ON(2.*.*.*)		VXX:DANI1=+00002		DANI1=+00002	✓	✓
		ON(10.*.*.*)		VXX:DANI1=+00003		DANI1=+00003	✓	✓
		ON(MANUAL)		VXX:DANI1=+00004		DANI1=+00004	✓	✓
	Art-Net SETUP-START ADDRESS	1		VXX:DANI3=+00001	QVX:DANI3	DANI3=+00001	✓	✓
		501		VXX:DANI3=00501		DANI3=00501	✓	✓
	Art-Net SETUP-NET	0		VXX:DANI4=+00000	QVX:DANI4	DANI4=+00000	✓	✓
		127		VXX:DANI4=+00127		DANI4=+00127	✓	✓
	Art-Net SETUP-SUB NET	0		VXX:DANI5=+00000	QVX:DANI5	DANI5=+00000	✓	✓
		15		VXX:DANI5=+00015		DANI5=+00015	✓	✓
	Art-Net SETUP-UNIVERS	0		VXX:DANI6=+00000	QVX:DANI6	DANI6=+00000	✓	✓
		15		VXX:DANI6=+00015		DANI6=+00015	✓	✓
	Art-Net SETUP-CHANNEL SETTING	DEFAULT		VXX:DANI8=+00000	QVX:DANI8	DANI8=+00000	✓	✓
		1		VXX:DANI8=+00001		DANI8=+00001	✓	✓
		USER		VXX:DANI8=+00100		DANI8=+00100	✓	✓

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.