

SANYO: PLC-XK2200/2600/3010 IR Command List

- Transmission format of LCD projector operation key
: NEC Format (single command / command pipelining mode)
- Custom Code + Custom Code
: 2 patterns as below
33h+00h(Default;code1), 33h+11h(code2)

Key No.	Data Code (HEX)	Function
1	17	AUTO SET
2	00	ON-OFF
3	38	COMPUTER 1
4	39	COMPUTER 2
5	3D	VIDEO
6	3E	S-VIDEO
7	83	COMPONENT
8	8C	CURSOR UP
9	1E	CURSOR LEFT
10	0F	SELECT
11	1D	CURSOR RIGHT
12	8D	CURSOR DOWN
13	1C	MENU
14	82	SCREEN
15	5B	KEYSTONE
16	16	INFORMATION
17	43	FREEZE
18	8B	NO SHOW
19	8A	P-TIMER
20	18	LAMP CONTROL
21	01	D.ZOOM +
22	09	VOLUME +
23	0C	IMAGE
24	02	D.ZOOM -
25	0A	VOLUME -
26	0B	MUTE