

SANYO: PLC-WL2500 / WL2501 IR Command List

- Transmission format of LCD projector operation key
: NEC Format (single command / command pipelining mode)
- Custom Code + Custom Code
: 2 patterns as below
33h+FFh(Default;code1), 33h+EEh(code2)

Key No.	Data Code (HEX)	Function
K01	17	AUTO SET
K02	00	ON-OFF
K03	38	COMPUTER 1
K04	39	COMPUTER 2
K05	37	HDMI
K06	3D	VIDEO
K07	3E	S-VIDEO
K08	83	COMPONENT
K09	8C	CURSOR UP
K10	1E	CURSOR LEFT
K11	0F	SELECT
K12	1D	CURSOR RIGHT
K13	8D	CURSOR DOWN
K14	1C	MENU
K15	82	SCREEN
K16	5B	KEYSTONE
K17	16	INFORMATION
K18	43	FREEZE
K19	8B	NO SHOW
K20	8A	P-TIMER
K21	18	LAMP CONTROL
K22	01	D. ZOOM +
K23	09	VOLUME +
K24	0C	IMAGE
K25	20	ASPECT
K26	02	D. ZOOM -
K27	0A	VOLUME -
K28	0B	MUTE